



Cisco IOS IP Routing: EIGRP Command Reference

July 2010

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco IOS IP Routing: EIGRP Command Reference
© 2010 Cisco Systems, Inc. All rights reserved.



CONTENTS

Introduction IRE-1

EIGRP Commands IRE-3

- address-family (EIGRP) IRE-4
- af-interface IRE-7
- authentication key-chain (EIGRP) IRE-9
- authentication mode (EIGRP) IRE-11
- autonomous-system (EIGRP) IRE-13
- auto-summary (EIGRP) IRE-15
- bandwidth-percent IRE-17
- clear eigrp address-family neighbors IRE-19
- clear ip eigrp neighbors IRE-21
- clear ip eigrp vrf neighbors IRE-23
- dampening-change IRE-25
- dampening-interval IRE-27
- default-information IRE-29
- default-metric (EIGRP) IRE-31
- distance eigrp IRE-34
- eigrp event-log-size IRE-37
- eigrp interface IRE-39
- eigrp log-neighbor-changes IRE-41
- eigrp log-neighbor-warnings IRE-43
- eigrp router-id IRE-45
- eigrp stub IRE-47
- exit-address-family IRE-51
- exit-af-interface IRE-53
- exit-af-topology IRE-54
- hello-interval IRE-56
- hold-time IRE-58
- ip authentication key-chain eigrp IRE-60
- ip authentication mode eigrp IRE-62

ip bandwidth-percent eigrp	IRE-64
ip hello-interval eigrp	IRE-66
ip hold-time eigrp	IRE-68
ip next-hop-self eigrp	IRE-70
ip split-horizon eigrp	IRE-71
ip summary-address eigrp	IRE-73
log-neighbor-changes (EIGRP)	IRE-75
log-neighbor-warnings	IRE-76
match extcommunity	IRE-78
maximum-prefix	IRE-80
metric holddown	IRE-83
metric maximum-hops	IRE-85
metric weights (EIGRP)	IRE-87
neighbor (EIGRP)	IRE-90
neighbor description	IRE-92
neighbor maximum-prefix (EIGRP)	IRE-94
network (EIGRP)	IRE-97
next-hop-self	IRE-99
nsf (EIGRP)	IRE-100
offset-list (EIGRP)	IRE-102
passive-interface (EIGRP)	IRE-104
redistribute eigrp	IRE-106
redistribute maximum-prefix (EIGRP)	IRE-108
router eigrp	IRE-111
set metric (EIGRP)	IRE-113
show eigrp address-family accounting	IRE-115
show eigrp address-family events	IRE-117
show eigrp address-family interfaces	IRE-119
show eigrp address-family neighbors	IRE-122
show eigrp address-family timers	IRE-125
show eigrp address-family topology	IRE-127
show eigrp address-family traffic	IRE-131
show eigrp plugins	IRE-133
show eigrp protocols	IRE-135
show eigrp tech-support	IRE-138

show ip eigrp accounting	IRE-140
show ip eigrp events	IRE-142
show ip eigrp interfaces	IRE-144
show ip eigrp neighbors	IRE-147
show ip eigrp topology	IRE-150
show ip eigrp traffic	IRE-154
show ip eigrp vrf accounting	IRE-156
show ip eigrp vrf interfaces	IRE-158
show ip eigrp vrf neighbors	IRE-160
show ip eigrp vrf topology	IRE-162
show ip eigrp vrf traffic	IRE-165
shutdown (address-family)	IRE-167
split-horizon (EIGRP)	IRE-169
stub	IRE-171
summary-address (EIGRP)	IRE-174
timers active-time	IRE-176
timers graceful-restart purge-time	IRE-178
timers nsf converge	IRE-180
timers nsf route-hold	IRE-182
timers nsf signal	IRE-184
topology (EIGRP)	IRE-186
traffic-share balanced	IRE-188
variance (EIGRP)	IRE-190



Introduction

This book describes the commands used to configure and monitor Enhanced Interior Gateway Routing Protocol (EIGRP) routing capabilities and features.

For EIGRP configuration information and examples, refer to the *Cisco IOS IP Routing: EIGRP Configuration Guide*.



EIGRP Commands

address-family (EIGRP)

To enter address-family configuration mode to configure an Enhanced Interior Gateway Routing Protocol (EIGRP) routing instance, use the **address-family** (EIGRP) command in router configuration mode. To remove the address-family from the EIGRP configuration, use the **no** form of this command.

EIGRP Autonomous-System Configuration

address-family ipv4 [**unicast**] **vrf** *vrf-name* [**autonomous-system** *autonomous-system-number*]

no address-family ipv4 [**unicast**] **vrf** *vrf-name* [**autonomous-system** *autonomous-system-number*]

EIGRP Named IPv4 Configuration

address-family ipv4 [**multicast**] [**unicast**] [**vrf** *vrf-name*] **autonomous-system** *autonomous-system-number*

no address-family ipv4 [**multicast**] [**unicast**] [**vrf** *vrf-name*] **autonomous-system** *autonomous-system-number*

EIGRP Named IPv6 Configuration

address-family ipv6 [**unicast**] [**vrf** *vrf-name*] **autonomous-system** *autonomous-system-number*

no address-family ipv6 [**unicast**] [**vrf** *vrf-name*] **autonomous-system** *autonomous-system-number*

Syntax Description

ipv4	Selects the IPV4 protocol address-family.
ipv6	Selects the IPV6 protocol address-family. IPv6 is supported only in EIGRP named configurations.
multicast	(Optional) Specifies the multicast address-family. This keyword is available only in EIGRP named IPv4 configurations.
unicast	(Optional) Specifies the unicast address-family.
autonomous-system <i>autonomous-system-number</i>	(Optional) Specifies the autonomous system number. This keyword/argument pair is required for EIGRP named configurations.
vrf <i>vrf-name</i>	(Optional) Specifies the name of the VRF. This keyword/argument pair is required for EIGRP AS configurations.

Command Default

No EIGRP process is running.

Command Modes

Router configuration (config-router)

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(15)T	This command was integrated into Cisco IOS Release 12.2(15)T.
12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.

Release	Modification
12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. The autonomous-system keyword is required for named configurations.
12.2(33)SRE	This command was modified. The autonomous-system keyword is required for named configurations.
12.2(33)XNE	This command was modified. The autonomous-system keyword is required for named configurations.
Cisco IOS XE Release 2.5	This command was modified. The autonomous-system keyword is required for named configurations.
12.2(33)SX14	This command was modified. The autonomous-system keyword is required for named configurations.

Usage Guidelines

The **address-family** (EIGRP) command is used to configure IPv4 or IPv6 address-family sessions under EIGRP. To leave address-family configuration mode without removing the address family configuration, use the **exit-address-family** command.

EIGRP Autonomous-System Configuration

Use the **router eigrp** *number* command to configure an EIGRP autonomous-system (AS) configuration.

In this configuration, EIGRP VPNs can be configured only under IPv4 address-family configuration mode. A virtual routing and forwarding instance (VRF) and route distinguisher must be defined before the address family session can be created.

It is recommended that you configure an autonomous-system number when the address-family is configured, either by entering the **address-family** command or the **autonomous-system** command.

EIGRP Named Configuration

Use the **router eigrp** *virtual-name* command to configure an EIGRP named configuration.

In this configuration, EIGRP VPNs can be configured in IPv4 and IPv6 named configurations. A virtual routing and forwarding instance (VRF) and a route distinguisher may or may not be used to create the address-family.

If a VRF is not used in creating the address-family, the EIGRP VPN instance assumes the default route distinguisher and will communicate with the default route distinguisher of other routers in the same network.

EIGRP VPNs can be configured under EIGRP named configurations. A virtual routing and forwarding instance (VRF) and route distinguisher must be defined before the address-family session can be created.

A single EIGRP routing process can support multiple VRFs. The number of VRFs that can be configured is limited only by available system resources on the router, which is determined by the number of VRFs, running processes, and available memory. However, only a single VRF can be supported by each VPN, and redistribution between different VRFs is not supported.

MPLS VPN support between PE and CE routers is configured only on PE routers that provide VPN services over the service provider backbone. The customer site does not require any changes to equipment or configurations to support the EIGRP VPN. A metric must be configured for routes to be advertised to the CE router. The metric can be configured using the **redistribute (IP)** command or configured with the **default-metric (EIGRP)** command.

Examples

The following example configures an IPv4 address-family session for the VRF named RED in Cisco IOS releases prior to Cisco IOS Release 15.0(1)M, 12.2(33)SRE, 12.2(33)XNE and Cisco IOS XE Release 2.5:

```
Router(config)# ip vrf RED
Router(config-vrf)# rd 1:1
Router(config-vrf)# exit
Router(config)# router eigrp 1
Router(config-router)# address-family ipv4 vrf RED
Router(config-router-af)# autonomous-system 101
Router(config-router-af)# network 172.16.0.0
Router(config-router-af)# default-metric 10000 100 255 1 1500
Router(config-router-af)# exit-address-family
```

The following examples configure a single VRF named VRF-RED in Cisco IOS Release 15.0(1)M, 12.2(33)SRE, 12.2(33)XNE and Cisco IOS XE Release 2.5 and later releases:

```
Router(config)# ip vrf VRF-RED
Router(config-vrf)# rd 1:1
Router(config-vrf)# exit
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 vrf VRF-RED autonomous-system 1
Router(config-router-af)# network 10.0.0.0 0.0.0.255
Router(config-router-af)# topology base
Router(config-router-topology)# default-metric 10000 100 255 1 1500
Router(config-router-topology)# exit-af-topology
Router(config-router-af)# exit-address-family
```

The following example configures a non-VRF address-family in Cisco IOS Release 15.0(1)M, 12.2(33)SRE, 12.2(33)XNE and Cisco IOS XE Release 2.5, and later releases:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 3
Router(config-router-af)# network 10.0.0.0 0.0.0.255
Router(config-router-af)# topology base
Router(config-router-af-topology)# default-metric 10000 100 255 1 1500
Router(config-router-af-topology)# exit-af-topology
Router(config-router-af)# exit-address-family
```

Related Commands

Command	Description
autonomous-system (EIGRP)	Configures the autonomous-system number for an EIGRP routing process to run within a VRF instance.
default-metric (EIGRP)	Sets metrics for EIGRP.
exit-address-family	Exits address-family configuration mode.
network (EIGRP)	Specifies a list of networks for the EIGRP routing process.
redistribute (IP)	Redistributes routes from one routing domain into another routing domain.

af-interface

To enter address-family interface configuration mode and to configure interface-specific Enhanced Interior Gateway Routing Protocol (EIGRP) commands, use the **af-interface** command in address-family configuration mode. To reset the address-family interface setting to factory values, use the **no** form of this command.

af-interface { **default** | *interface-type interface-number* }

no af-interface { **default** | *interface-type interface-number* }

Syntax Description

default	Specifies the default address-family interface configuration mode. Commands applied under this mode affect all interfaces used by this address-family instance.
<i>interface-type interface-number</i>	Interface type and number of the interface that the address-family submenu commands will affect.

Command Default

Address-family interface configuration mode is not entered.

Command Modes

Address-family configuration (config-router-af)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

The **af-interface default** command is useful for defining user defaults to apply to EIGRP interfaces that belong to an address-family when EIGRP is configured using the named method. For example, authentication mode is disabled by default, and you can enable MD5 authentication for all EIGRP interfaces in the address-family using address-family interface configuration mode and then selectively override the new default setting using different address-family interface configuration commands.



Note

Use the **af-interface default** command with caution, because some default settings can be different depending on the interface type. For example, the default hello-interval is 5 seconds for most interfaces but is 60 seconds for slow NBMA interfaces, and changing the hello-interval in address-family interface configuration mode will affect *all* interfaces.

Examples

The following example shows how to enter address-family interface configuration mode and to configure EIGRP interface-specific commands:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# af-interface default
Router(config-router-af-interface)# shutdown
Router(config-router-af-interface)# exit
Router(config-router-af)# af-interface Ethernet 0/0
Router (config-router-af-interface)# no shutdown
Router (config-router-af-interface)# exit-af-interface
Router(config-router-af)#
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
exit-address-family	Exits address-family configuration mode.

authentication key-chain (EIGRP)

To specify an authentication key chain for Enhanced Interior Gateway Routing Protocol (EIGRP), use the **authentication key-chain** (EIGRP) command in address-family interface configuration mode or service-family interface configuration mode. To remove the authentication key-chain, use the **no** form of this command.

authentication key-chain *name-of-chain*

no authentication key-chain *name-of-chain*

Syntax Description

<i>name-of-chain</i>	Group of keys that are valid.
----------------------	-------------------------------

Command Default

No key chains are specified for EIGRP.

Command Modes

Address-family interface configuration (router-config-af-interface)
Service-family interface configuration (router-config-sf-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines

The **key-chain** command has no effect until the **authentication mode md5** command is configured. Only one authentication key chain is applied to EIGRP at one time. That is, if you configure a second **authentication key-chain** command, the first is overridden.

Examples

The following example configures EIGRP to apply authentication to address-family autonomous system 1 and identifies a key chain named SITE1:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 1
Router(config-router-af)# af-interface ethernet0/0
Router(config-router-af-interface)# authentication key-chain SITE1
Router(config-router-af-interface)# authentication mode md5
```

The following example configures EIGRP to apply authentication to service-family autonomous system 1 and identifies a key chain named SITE1:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 1
Router(config-router-sf)# sf-interface ethernet0/0
Router(config-router-sf-interface)# authentication key-chain SITE1
Router(config-router-sf-interface)# authentication mode md5
```

Related Commands

Command	Description
authentication mode (EIGRP)	Specifies the type of authentication used in EIGRP address-family packets for the EIGRP instance.
key chain	Defines an authentication key chain needed to enable authentication for routing protocols.
router eigrp	Configures the EIGRP address-family process.

authentication mode (EIGRP)

To specify the type of authentication used in Enhanced Interior Gateway Routing Protocol (EIGRP) address-family or service-family packets for the EIGRP instance, use the **authentication mode** command in address-family interface configuration mode or service-family interface configuration mode. To disable a configured authentication type, use the **no** form of this command.

authentication mode md5

no authentication mode

Syntax Description	md5 Message Digest 5 (MD5) authentication.
---------------------------	---------------------------------------------------

Command Default	No authentication mode is provided for EIGRP packets.
------------------------	-------------------------------------------------------

Command Modes	Address-family interface configuration (config-router-af-interface) Service-family interface configuration (config-router-sf-interface)
----------------------	--------------------------------------------------------------------------------------------------------------------------------------------

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
	12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines	Configure authentication to prevent unapproved sources from introducing unauthorized or false service messages.
-------------------------	-----------------------------------------------------------------------------------------------------------------

When the **authentication mode (EIGRP)** command is used in conjunction with the **authentication key-chain** command, an MD5 keyed digest is added to each EIGRP packet.

Examples	The following example configures the interface to use MD5 authentication in address-family packets:
-----------------	-----------------------------------------------------------------------------------------------------

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 1
Router(config-router-af)# af-interface ethernet0/0
Router(config-router-af-interface)# authentication key-chain TEST1
Router(config-router-af-interface)# authentication mode md5
```

The following example configures the interface to use MD5 authentication in EIGRP service-family packets:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 1
Router(config-router-sf)# sf-interface ethernet0/0
Router(config-router-sf-interface)# authentication key-chain TEST1
Router(config-router-sf-interface)# authentication mode md5
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
authentication key-chain	Specifies the type of authentication used in EIGRP address-family or service-family packets for the EIGRP instance.
key chain	Defines an authentication key-chain needed to enable authentication for routing protocols.
router eigrp	Configures the EIGRP address-family process.

autonomous-system (EIGRP)

To configure the autonomous-system number for an Enhanced Interior Gateway Routing Protocol (EIGRP) routing process to run within a VPN routing and forwarding (VRF) instance, use the **autonomous-system** command in address-family configuration mode. To remove the autonomous-system for an EIGRP routing process from within a VPN VRF instance, use the **no** form of this command.

autonomous-system *autonomous-system-number*

no autonomous-system *autonomous-system-number*

Syntax Description

autonomous-system-number Autonomous system number of the EIGRP routing process.

Command Default

The autonomous-system number is not configured.

Command Modes

Address-family configuration (config-router-af)

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(15)T	This command was integrated into Cisco IOS Release 12.2(15)T.
12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.
12.2(27)SBC	The command was integrated into Cisco IOS Release 12.2(27)SBC.
15.0(1)M	This command was modified. This command can now be configured as a keyword of the address-family (EIGRP) command. This command can still be configured as a separate command in address-family configuration mode.
12.2(33)SRE	This command was modified. This command can now be configured as a keyword of the address-family (EIGRP) command. This command can still be configured as a separate command in address-family configuration mode.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	The command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines

This standalone **autonomous-system** command is not available in EIGRP named configurations. This command is present only in EIGRP autonomous-system (AS) configurations.

When configuring an EIGRP process, you must configure an autonomous-system value. You can configure an autonomous-system value using the standalone **autonomous-system** (EIGRP) command in address-family configuration mode or by configuring the **address-family** command in router configuration mode with the *autonomous-system-number* argument, or both.

Once configured, the standalone **autonomous-system** command can optionally be removed, but only if the *autonomous-system* argument is also configured on the **address-family** command.

Once configured, the *autonomous-system-number* argument on the **address-family** command cannot be removed without also removing the address-family itself.

Examples

The following example shows how to configure an EIGRP routing process within a VRF with the autonomous system configured by the **autonomous-system** command in address-family configuration mode:

```
Router(config)# router eigrp 65200
Router(config-router)# address-family ipv4 vrf VRF2
Router(config-router-af)# autonomous-system 65500
```

The following example shows how to configure an EIGRP address family within a VRF with the autonomous system configured by the **address-family** *autonomous-system-number* command in router configuration mode:

```
Router(config)# router eigrp 65200
Router(config-router)# address-family ipv4 vrf VRF2 autonomous-system 65500
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
router eigrp	Configures the EIGRP address-family process.

auto-summary (EIGRP)

To allow automatic summarization of subnet routes into network-level routes, use the **auto-summary** command in router configuration mode or address-family topology configuration mode. To disable this function and send subprefix routing information across classful network boundaries, use the **no** form of this command.

auto-summary

no auto-summary

Syntax Description

This command has no arguments or keywords.

Command Default

The behavior of this command is enabled by default (the software does not send subprefix routing information across classful network boundaries).

Cisco IOS Release 15.0(1)M, 12.2(33)SRE, 12.2(33)XNE, Cisco IOS XE Release 2.5, Cisco IOS Release 12.2(33)SX14 and Later Releases

The behavior of this command is disabled by default (the software sends subprefix routing information across classful network boundaries).

Command Modes

Router configuration (config-router)

Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
12.2(8)T	The command default behavior changed to disabled.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family topology configuration mode was added. The default behavior was changed to disabled.
12.2(33)SRE	This command was modified. Address-family topology configuration mode was added. The default behavior was changed to disabled.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was modified. Address-family topology configuration mode was added. The default behavior was changed to disabled.

Usage Guidelines

To allow the software to create summary subprefixes to the classful network boundary when crossing classful network boundaries, use the **auto-summary** command.

Enhanced Interior Gateway Routing Protocol (EIGRP) summary routes are given an administrative distance value of 5. You cannot configure this value.

Examples

The following example enables automatic summarization for EIGRP process 109:

```
Router(config)# router eigrp 109  
Router(config-router)# auto-summary
```

The following example enables automatic summarization for EIGRP autonomous-system 4473:

```
Router(config)# router eigrp virtual-name  
Router(config-router)# address-family ipv4 autonomous-system 4473  
Router(config-router-af)# topology base  
Router(config-router-af-topology)# auto-summary
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
ip summary-address eigrp	Configures a summary aggregate address for a specified interface.
router eigrp	Configures the EIGRP address-family process.
topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters router address-family topology configuration mode.

bandwidth-percent

To configure the percentage of bandwidth that may be used by an Enhanced Interior Gateway Routing Protocol (EIGRP) address family or service family on an interface, use the **bandwidth-percent** command in address-family interface configuration mode or service-family interface configuration mode. To restore the default value, use the **no** form of this command.

bandwidth-percent *maximum-bandwidth-percentage*

no bandwidth-percent

Syntax Description	<i>maximum-bandwidth-percentage</i>	Percent of configured bandwidth that EIGRP may use to send packets. Valid range is 1 to 999999. The default is 50 percent.
---------------------------	-------------------------------------	----------------------------------------------------------------------------------------------------------------------------

Command Default	EIGRP limits bandwidth usage to 50 percent of the configured interface bandwidth.
------------------------	-----------------------------------------------------------------------------------

Command Modes	Address-family interface configuration (config-router-af-interface) Service-family interface configuration (config-router-sf-interface)
----------------------	--------------------------------------------------------------------------------------------------------------------------------------------

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
	12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines	Use the bandwidth-percent command to configure a different percentage of bandwidth for use by EIGRP than specified for the link by using the bandwidth interface command. Values greater than 100 percent may be configured. This option might be useful if the link bandwidth is set artificially low for other reasons. The default bandwidth percent uses 50 percent of the configured bandwidth of the link.
-------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Examples

The following example uses up to 75 percent (42 kbps) of a 56-kbps serial link for address-family autonomous system 4453:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# af-interface ethernet0/0
Router(config-router-af-interface)# bandwidth-percent 75
```

The following example uses up to 75 percent (42 kbps) of a 56-kbps serial link for service-family autonomous system 4533:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 4533
Router(config-router-sf)# sf-interface serial 0
Router(config-router-sf-interface)# bandwidth-percent 75
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
router eigrp	Configures the EIGRP address-family process.
service-family	Configures VRF metrics for an EIGRP service-family.
sf-interface	Configures interface-specific commands for an EIGRP service-family.

clear eigrp address-family neighbors

To delete entries from the Enhanced Interior Gateway Routing Protocol (EIGRP) neighbor table, use the **clear eigrp address-family neighbors** command in privileged EXEC mode.

```
clear eigrp address-family {ipv4 [autonomous-system-number | vrf [vrf-name] |
[autonomous-system-number]] | ipv6 [autonomous-system-number]} neighbors [ip-address]
[interface-type interface-number] [soft]
```

Syntax Description		
ipv4		Selects neighbors formed using the IPv4 protocol family.
ipv6		Selects neighbors formed using the IPv6 protocol family.
<i>autonomous-system-number</i>		(Optional) Autonomous system number of the EIGRP routing process. If no autonomous system number is specified, all autonomous systems are affected.
vrf		(Optional) Deletes entries from the neighbor table for the specified IPv4 VRF.
<i>vrf-name</i>		(Optional) Name of the VRF address-family to which the command is applied.
<i>ip-address</i>		(Optional) IPv4 or IPv6 address of the neighbor. Specifying an address removes all entries with this address from the neighbor table.
<i>interface-type</i>		(Optional) Interface type. Specifying this argument removes the specified interface type that all entries learned via this interface from the neighbor table.
<i>interface-number</i>		(Optional) Interface number. Specifying this arguments removes the specified interface number that all entries learned via this interface from the neighbor table.
soft		(Optional) Gracefully informs the peer that adjacency is being resynced. This method does not take the peer down and back up with a hard reset.

Command Default Entries in the EIGRP neighbor table are not cleared.

Command Modes Privileged EXEC (#)

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines



Caution

This command causes peers to bounce and routes to be relearned. Use this command only with the guidance of Cisco technical support.

Specifying the *interface-type* and *interface-number* arguments clears the neighbors on the specified interface from the neighbor table.

Specifying the VRF for an IPv4 address family clears neighbors in that VRF only. If an autonomous-system number is provided along with the VRF, then only the neighbors of that autonomous-system number in the VRF are cleared.

Examples

The following example removes the neighbor whose address is 172.16.8.3:

```
Router# clear eigrp address-family ipv4 neighbors 172.16.8.3
```

The following example clears EIGRP neighbors reached through the VRF named VRF1 in autonomous system 101:

```
Router# clear eigrp address-family ipv4 vrf VRF1 101 neighbors
```

The following example clears EIGRP neighbors reached through the VRF named VRF1 in autonomous system 101 learned through Ethernet interface 0/0:

```
Router# clear eigrp address-family ipv4 vrf VRF1 101 neighbors ethernet0/0
```

Related Commands

Command	Description
clear eigrp topology	Clears an EIGRP process for a topology instance.
clear ip eigrp neighbors	Deletes entries from the EIGRP neighbor table.
show eigrp address-family neighbors	Displays neighbors discovered by EIGRP.
show ip eigrp address-family neighbors	Displays neighbors discovered by EIGRP.

clear ip eigrp neighbors

To delete entries from the Enhanced Interior Gateway Routing Protocol (EIGRP) neighbor table, use the **clear ip eigrp neighbors** command in privileged EXEC mode.

```
clear ip eigrp [vrf vrf-name [autonomous-system-number] | autonomous-system-number]
neighbors [ip-address | interface-type interface-number] [soft]
```

Syntax Description		
vrf		(Optional) Deletes entries from the neighbor table for the specified IPv4 VRF.
<i>vrf-name</i>		(Optional) Name of the VRF address family to which the command is applied.
<i>autonomous-system-number</i>		(Optional) Autonomous-system (AS) number of the EIGRP routing process. If no autonomous-system number is specified, all autonomous systems are affected.
<i>ip-address</i>		(Optional) Address of the neighbor.
<i>interface-type</i>		(Optional) Interface type. Specifying this argument removes the specified interface type that all entries learned via this interface from the neighbor table.
<i>interface-number</i>		(Optional) Interface number. Specifying this argument removes the specified interface number that all entries learned via this interface from the neighbor table.
soft		(Optional) Gracefully informs the peer that adjacency is being resynced. This method does not take the peer down and back up with a hard reset.

Command Modes	Privileged EXEC (#)
----------------------	---------------------

Command History	Release	Modification
	10.0	This command was introduced.
	12.0(22)S	This command was integrated into Cisco IOS Release 12.0(22)S.
	12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.
	12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
	15.0(1)M	This command was modified. The vrf keyword, <i>vrf-name</i> argument, and soft keyword were added. This command replaces the clear ip eigrp vrf neighbors command.
	12.2(33)SRE	This command was modified. The vrf keyword, <i>vrf-name</i> argument, and soft keyword were added. This command replaces the clear ip eigrp vrf neighbors command.

Release	Modification
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines



Caution

This command causes peers to bounce and routes to be relearned. Use this command only with the guidance of Cisco technical support.

Specifying the *interface-type* and *interface-number* arguments clears the neighbors on the specified interface from the neighbor table.

Specifying the VRF or AS clears the neighbors in that VRF or AS.

This is a IPv4-only command in that it clears only the specified EIGRP IPv4 neighbors.

Examples

The following example removes the neighbor whose address is 172.16.8.3:

```
Router# clear ip eigrp neighbors 172.16.8.3
```

The following example clears EIGRP neighbors reached through the VRF named VRF1 in autonomous-system 101:

```
Router# clear ip eigrp vrf VRF1 101 neighbors
```

The following example clears EIGRP neighbors reached through the VRF named VRF1 in autonomous-system 101 learned through Ethernet interface 0/0:

```
Router# clear ip eigrp vrf VRF1 101 neighbor ethernet0/0
```

Related Commands

Command	Description
clear eigrp address-family neighbors	Deletes entries from the EIGRP neighbor table.
show ip eigrp interfaces	Displays information about interfaces configured for EIGRP.
show ip eigrp neighbors	Displays neighbors discovered by EIGRP.

clear ip eigrp vrf neighbors

**Note**

Effective with Cisco IOS Release 15.0(1)M and 12.2(33)SRE, the **clear ip eigrp vrf neighbors** command is replaced by the **clear ip eigrp neighbors** command. See the **clear ip eigrp neighbors** for more information.

To clear neighbor entries of the specified Enhanced Interior Gateway Routing Protocol (EIGRP) virtual routing and forwarding instance (VRF) from the Routing Information Base (RIB), use the **clear ip eigrp vrf neighbors** command in privileged EXEC mode.

```
clear ip eigrp vrf vrf-name [autonomous-system-number] neighbors [interface-name
interface-number]
```

Syntax Description

<i>vrf-name</i>	Name of the VRF whose EIGRP neighbors will be cleared. The * keyword can be used as a wildcard to specify all VRFs.
<i>autonomous-system-number</i>	(Optional) Autonomous system number of the VRF whose neighbors will be cleared.
<i>interface-name</i> <i>interface-number</i>	(Optional) Interface that VRF neighbors were learned through. The exact interface is specified by interface name and number using the <i>interface-name</i> and <i>interface-number</i> arguments.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(15)T	This command was integrated into 12.2(15)T.
12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.
12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was replaced by the clear ip eigrp neighbors command.
12.2(33)SRE	This command was replaced by the clear ip eigrp neighbors command.

Examples

The following example shows how to clear EIGRP neighbors reached through the VRF named RED in autonomous system 45000:

```
Router# clear ip eigrp vrf RED 45000 neighbors
```

The following example shows how to clear EIGRP neighbors reached through the VRF named GREEN in autonomous-system 101 learned through Ethernet interface 0/0:

```
Router# clear ip eigrp vrf GREEN 45000 neighbors ethernet 0/0
```

Related Commands

Command	Description
show ip eigrp vrf interfaces	Displays EIGRP interfaces that are defined under the specified VRF.
show ip eigrp vrf neighbors	Displays neighbors discovered by EIGRP that carry VRF information.
show ip eigrp vrf topology	Displays VRF entries in the EIGRP topology table.
show ip eigrp vrf traffic	Displays EIGRP VRF traffic statistics.
show ip route vrf	Displays routing protocol information that is associated with a VRF.

dampening-change

To set a threshold percentage to minimize or dampen the effect of frequent routing changes through an interface in an Enhanced Interior Gateway Routing Protocol (EIGRP) address family or service family, use the **dampening-change** command in address-family interface configuration mode or service-family interface configuration mode. To restore the default value, use the **no** form of this command.

dampening-change [*change-percentage*]

no dampening-change

Syntax Description

<i>change-percentage</i>	(Optional) The percentage a metric must change before the value is stored for future decisions on advertisements. Value range is 1 to 100. If a <i>change-percentage</i> value is not specified, the default is 50 percent of the computed metric.
--------------------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Default

No threshold percentage is configured.

Command Modes

Address-family interface configuration (config-router-af-interface)
Service-family interface configuration (config-router-sf-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines

The **dampening-change** command is supported only for Mobile Ad Hoc Networking (MANET) router-to-radio links.

When a peer metric changes on an interface that is configured with the **dampening-change** command, EIGRP multiplies the dampening-change percentage with the old peer metric and compares the result (the threshold) to the difference between the old and new metrics. If the metric difference is greater than the calculated threshold, then the new metric is applied and routes learned from that peer are updated and advertised to other peers. If the metric difference is less than the threshold, the new metric is discarded.

There are exceptions that will result in an immediate update regardless of the dampening-change setting:

- An interface is down.
- A route is down.
- A change in metric which results in the router selecting a new next hop.

Peer metric changes that do not exceed a configured change percentage and that do not result in a routing change do not result in an update being sent to other adjacencies. Peer metric changes are based on the stored last-update of the peer. Peer metric changes that exceed the threshold value are stored and used for future comparisons.

Examples

The following example configures an EIGRP address family to accept a peer metric change if the change is greater than 75 percent of the last updated value:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 5400
Router(config-router-af)# af-interface ethernet0/0
Router(config-router-af-interface)# dampening-change 75
```

The following example configures an EIGRP service family to accept a peer metric change if the change is greater than 75 percent of the last updated value:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 4533
Router(config-router-sf)# sf-interface serial 0
Router(config-router-sf-interface)# dampening-change 75
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
dampening-interval	Sets a threshold time interval to minimize or dampen the effect of frequent routing changes through an interface in an EIGRP address family or service family.
router eigrp	Configures the EIGRP address-family process.
service-family	Specifies service-family configuration mode.
sf-interface	Configures interface-specific commands under a service family.

dampening-interval

To set a threshold time interval to minimize or dampen the effect of frequent routing changes through an interface in an Enhanced Interior Gateway Routing Protocol (EIGRP) address family or service family, use the **dampening-interval** command in address-family interface configuration mode or service-family interface configuration mode. To restore to the default value, use the **no** form of this command.

dampening-interval [*interval*]

no dampening-interval [*interval*]

Syntax Description	<i>interval</i>	(Optional) Time interval, in seconds, that must elapse before a route change will cause an update to occur. Value range is 1 to 65535. If an <i>interval</i> value is not specified, the default is 30 seconds.
---------------------------	-----------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Default	A dampening interval is not enabled.
------------------------	--------------------------------------

Command Modes	Address-family interface configuration (config-router-af-interface) Service-family interface configuration (config-router-sf-interface)
----------------------	--------------------------------------------------------------------------------------------------------------------------------------------

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
	12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines	<p>The dampening-interval command is supported only in Mobile Ad Hoc Networking (MANET) Router-to-Radio links.</p> <p>When a peer metric changes on an interface that is configured with a dampening interval, EIGRP will apply the metric change only if the time difference since the last metric changed exceeds the specified interval. If the time difference is less than the specified interval, the update is discarded.</p> <p>There are exceptions that result in an immediate update regardless of the dampening interval settings:</p> <ul style="list-style-type: none"> • An interface is down. • A route is down. • A change in metric that results in the router selecting a new next hop.
-------------------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Examples

The following example configures EIGRP address-family Ethernet interface 0/0 to limit the metric change frequency to no more than one change in a 45-second interval:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 5400
Router(config-router-af)# af-interface ethernet0/0
Router(config-router-af-interface)# dampening-interval 45
```

The following example configures EIGRP service-family Serial interface 0 to limit the metric change frequency to no more than one change in a 30 second interval:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 4533
Router(config-router-sf)# sf-interface serial0
Router(config-router-sf-interface)# dampening-interval 30
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
dampening-change	Sets a threshold percentage to minimize or dampen the effect of frequent routing changes through an interface in an EIGRP address family or service family.
router eigrp	Configures the EIGRP address-family process.
service-family	Specifies service-family configuration mode.
sf-interface	Configures interface-specific commands under a service family.
shutdown	Disables service family on the interface.

default-information

To accept exterior or default routing information into Enhanced Interior Gateway Routing Protocol (EIGRP) processes, use the **default-information** command in router configuration mode or address-family topology configuration mode. To suppress exterior or default routing information in inbound or outbound updates, use the **no** form of this command.

default-information { **allowed** { **in** | **out** } | **in** | **out** } [*acl-number* / *acl-name*]

no default-information { **allowed** { **in** | **out** } | **in** | **out** }

Cisco IOS Release 15.0(1)M, 12.2(33)SRE, 12.2(33)XNE, Cisco IOS XE Release 2.5 and Later Releases

default-information { **in** | **out** } [*acl-number* / *acl-name*]

no default-information { **in** | **out** } [*acl-number* / *acl-name*]

Syntax Description

allowed	Configures EIGRP to accept default routing information.
in	Configures EIGRP to accept exterior or default routing information.
out	Configures EIGRP to advertise external routing information.
<i>acl-number</i>	(Optional) Standard access list number from 1 to 99 or an expanded standard access list from 1300 to 1999.
<i>acl-name</i>	(Optional) Named standard access list.

Command Default

Exterior routes are always accepted and default information is passed between EIGRP processes when redistribution occurs.

Command Modes

Router configuration (config-router)
Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
11.2	The <i>acl-number</i> and <i>acl-name</i> arguments were added.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family topology configuration mode was added. The allowed keyword was removed.
12.2(33)SRE	This command was modified. Address-family topology configuration mode was added. The allowed keyword was removed.

Release	Modification
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

The default network of 0.0.0.0 used by Routing Information Protocol (RIP) can be redistributed by EIGRP.

Examples

The following example allows exterior or default routes to be received by the EIGRP process in autonomous system 23:

```
Router(config)# router eigrp 23
Router(config-router)# default-information in
```

The following example allows EIGRP exterior or default routes to be received by the EIGRP process in autonomous system 4473 in Cisco IOS Release 15.0(1)M, 12.2(33)SRE, 12.2(33)XNE, Cisco IOS XE Release 2.5 and later releases:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4473
Router(config-router-af)# topology base
Router(config-router-af-topology)# default-information in
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
router eigrp	Configures the EIGRP address-family process.
topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters router address-family topology configuration mode.

default-metric (EIGRP)

To set metrics for Enhanced Interior Gateway Routing Protocol (EIGRP), use the **default-metric** command in router configuration mode or address-family topology configuration mode. To remove the metric value and restore the default state, use the **no** form of this command.

default-metric *bandwidth delay reliability loading mtu*

no default-metric *bandwidth delay reliability loading mtu*

Syntax Description

<i>bandwidth</i>	Minimum bandwidth of the route in kilobytes per second. It can be from 1 to 4294967295.
<i>delay</i>	Route delay in tens of microseconds. It can be 1 or any positive number that is a multiple of 39.1 nanoseconds.
<i>reliability</i>	Likelihood of successful packet transmission expressed as a number from 0 through 255. The value 255 means 100 percent reliability; 0 means no reliability.
<i>loading</i>	Effective bandwidth of the route expressed as a number from 1 to 255 (255 is 100 percent loading).
<i>mtu</i>	The smallest allowed value for the maximum transmission unit (MTU), expressed in bytes. It can be from 1 to 65535.

Command Default

Only connected routes can be redistributed without a default metric. The metric of redistributed connected routes is set to 0.

Command Modes

Router configuration (config-router)
Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
12.0(22)S	Address family support was added.
12.2(15)T	Address family support was added.
12.2(18)S	Address family support was added.
12.4(6)T	Support for IPv6 was added.
12.2(28)SB	This command was integrated into Cisco IOS Release 12.2(28)SB.
12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family topology configuration mode was added. This command must be entered in address-family topology configuration mode when EIGRP is configured with a named router configuration.

Release	Modification
12.2(33)SRE	This command was modified. Address-family topology configuration mode was added. This command must be entered in address-family topology configuration mode when EIGRP is configured with a named router configuration.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

You must use a default metric to redistribute a protocol into EIGRP, unless you use the **redistribute** command.

Metric defaults have been carefully set to work for a wide variety of networks. Take great care when changing these values.

Default metrics are supported only when you are redistributing from EIGRP or static routes.

Examples

The following example shows how the redistributed Routing Information Protocol (RIP) metrics are translated into EIGRP metrics with values as follows: bandwidth = 1000, delay = 100, reliability = 250, loading = 100, and MTU = 1500:

```
Router(config)# router eigrp 109
Router(config-router)# network 172.16.0.0
Router(config-router)# redistribute rip
Router(config-router)# default-metric 1000 100 250 100 1500
```

The following example shows how the redistributed EIGRP service family 6473 metrics are translated into EIGRP metric with values as follows: bandwidth = 1000, delay = 100, reliability = 250, loading = 100, and MTU = 1500.

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# af-interface default
Router(config-router-af-interface)# no shutdown
Router(config-router-af-interface)# exit
Router(config-router-af)# topology base
Router(config-router-af-topology)# default-metric 1000 100 250 100 1500
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
ipv6 router eigrp	Configures the EIGRP IPv6 routing process.
redistribute (IP)	Redistributes routes from one routing domain into another routing domain.
redistribute (IPv6)	Redistributes IPv6 routes from one routing domain into another routing domain.

Command	Description
router eigrp	Configures the EIGRP address-family process.
topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters router address-family topology configuration mode.

distance eigrp

To allow the use of two administrative distances—internal and external—that could be a better route to a node, use the **distance eigrp** command in router configuration mode or address-family topology configuration mode. To reset these values to their defaults, use the **no** form of this command.

distance eigrp *internal-distance external-distance*

no distance eigrp

Syntax Description

<i>internal-distance</i>	Administrative distance for Enhanced Internal Gateway Routing Protocol (EIGRP) internal routes. Internal routes are those that are learned from another entity within the same autonomous system. The distance can be a value from 1 to 255. The default administrative distance for EIGRP internal routes is 90.
<i>external-distance</i>	Administrative distance for EIGRP external routes. External routes are those for which the best path is learned from a neighbor external to the autonomous system. The distance can be a value from 1 to 255. The default administrative distance for EIGRP external routes is 170.

Command Default

EIGRP uses the default internal and external administrative distances.

Command Modes

Router configuration (config-router)
Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family topology configuration mode was added. This command must be entered in address-family topology configuration mode when EIGRP is configured with a named router configuration.
12.2(33)SRE	This command was modified. Address-family topology configuration mode was added. This command must be entered in address-family topology configuration mode when EIGRP is configured with a named router configuration.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

An administrative distance is a rating of the trustworthiness of a routing information source, such as an individual router or a group of routers. Numerically, an administrative distance is an integer from 0 to 255. In general, the higher the value, the lower the trust rating. An administrative distance of 255 means the routing information source cannot be trusted at all and should be ignored.

Use the **distance eigrp** command if another protocol is known to be able to provide a better route to a node than was actually learned via external EIGRP, or if some internal routes should really be preferred by EIGRP.

Table 1 lists the default administrative distances.

Table 1 *Default Administrative Distances*

Route Source	Default Distance
Connected interface	0
Static route	1
EIGRP summary route	5
External BGP	20
Internal EIGRP	90
Open Shortest Path First (OSPF)	110
Intermediate System-to-Intermediate System (IS-IS)	115
Routing Information Protocol (RIP)	120
EIGRP external route	170
Internal Border Gateway Protocol (BGP)	200
Unknown	255

To display the default administrative distance for a specified routing process, use the **show ip protocols** command.

Examples

In the following example, the **router eigrp** global configuration command sets up EIGRP routing in autonomous system number 109. The **network** router configuration commands specify EIGRP routing on networks 192.168.7.0 and 172.16.0.0. The **distance eigrp** command sets the administrative distance of all EIGRP internal routes to 80 and all EIGRP external routes to 130.

```
Router(config)# router eigrp 109
Router(config-router)# network 192.168.7.0
Router(config-router)# network 172.16.0.0
Router(config-router)# distance eigrp 80 130
```

In the following example, the **distance eigrp** command sets the administrative distance of all EIGRP address-family internal routes to 80 and all external routes to 130:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4473
Router(config-router-af)# topology base
Router(config-router-af-topology)# distance eigrp 80 130
```

Related Commands	Command	Description
	address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
	router eigrp	Configures the EIGRP address-family process.
	show ip protocols	Displays the parameters and current state of the active routing protocol process.
	topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters router address-family topology configuration mode.

eigrp event-log-size

To set the size of the Enhanced Interior Gateway Routing Protocol (EIGRP) event log, use the **eigrp event-log-size** command in router configuration mode or address-family topology configuration mode. To reset the size of the EIGRP event log to its default value, use the **no** form of this command.

eigrp event-log-size *size*

no eigrp event-log-size

Syntax Description

<i>size</i>	Size of the EIGRP event log; valid values are from 0 to half of the available memory on the system at the time of configuration. Default value is 500.
-------------	--------------------------------------------------------------------------------------------------------------------------------------------------------

Command Default

The EIGRP event log size is 500.

Command Modes

Router configuration (config-router)
Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
12.2(18)SXF	This command was introduced in Cisco IOS Release 12.2(18)SXF.
15.0(1)M	This command was modified. Address-family topology configuration mode was added.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

When the configured size (number of lines) of the event log is exceeded, the last configured number of lines is retained, and the log becomes a rolling number of events with the most recent at the top of the log.

Examples

The following example shows how to set the size of the EIGRP event log to 5000010:

```
Router# configure terminal
Router(config)# router eigrp 2
Router (config-router)# eigrp event-log-size 5000010
Router (config-router)#
```

The following example shows how to set the size of the EIGRP event log in an EIGRP named configuration to 10000:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 1
Router(config-router-af)# topology base
Router(config-router-af-topology)# eigrp event-log-size 10000
```

Related Commands

Command	Description
clear ip eigrp event	Clears the IP EIGRP event log.

eigrp interface



Note

Effective with Cisco IOS Release 15.0(1)M, the **eigrp interface** command is replaced by the **dampening-change** command and the **dampening-interval** command. See the **dampening-change** and **dampening-interval** commands for more information.

To set a threshold value to minimize hysteresis in a router-to-radio configuration, use the **eigrp interface** command in interface configuration mode. To reset the hysteresis threshold to the default value, use the **no** form of this command.

eigrp *vmi-interface-number* **interface** [**dampening-change** *value*] [**dampening-interval** *value*]

no eigrp *vmi-interface-number* **interface** [**dampening-change** *value*] [**dampening-interval** *value*]

Syntax Description

vmi-interface-number	The number assigned to the VMI interface.
dampening-change <i>value</i>	(Optional) Value used to minimize the effect of frequent routing changes in router-to-radio configurations. Percent interface metric must change to cause update. Value range is 1 to 100.
dampening-interval <i>value</i>	(Optional) Specifies the time interval in seconds to check the interface metrics at which advertising of routing changes occurs. The default value is 30 seconds. Value range is 1 to 65535.

Command Default

Default for change-based dampening is 50 percent of the computed metric.
Default for interval-based dampening is 30 seconds.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
12.4(15)XF	This command was introduced.
12.4(15)T	This command was integrated into Cisco IOS Release 12.4(15)T.
15.0(1)M	This command was replaced. This command was replaced by the dampening-change command and the dampening-interval command.

Usage Guidelines

This command advertises routing changes for EIGRP traffic only.

The REPLY sent to any QUERY will always contain the latest metric information. Exceptions which will result in immediate UPDATE being sent:

- A down interface
- A down route
- Any change in metric which results in the router selecting a new next hop

Change-based Dampening

The **default** value for the change tolerance will be 50% of the computed metric. It can be configured in the range from 0 to 100 percent. If the metric change of the interface is not greater (or less) than the current metric plus or minus the specified amount, the change will not result in a routing change, and no update will be sent to other adjacencies.

Interval-based Dampening

The **default** value for the update intervals is 30 seconds. It can be configured in the range from 0 to 64535 seconds. If this option is specified, changes in routes learned through this interface, or in the interface metrics, will not be advertised to adjacencies until the specified interval is met. When the timer expires, any changes detected in any routes learned through the interface, or the metric reported by the interfaces will be sent out.

Examples

Change-based Dampening Example

The following example sets the threshold to 50 percent tolerance routing updates involving VMI interfaces and peers:

```
interface vm1
 ip address 10.2.2.1 255.255.255.0
 ipv6 address 2001:0DB1:2::1/96
 ipv6 enable
 eigrp 1 interface dampening-change 50
 physical-interface Ethernet0/0
```

Interval-based Dampening Example

The following example sets the interval to 30 seconds at which updates occur for topology changes that affect VMI interfaces and peers:

```
interface vm1
 ip address 10.2.2.1 255.255.255.0
 ipv6 address 2001:0DB1:2::1/96
 ipv6 enable
 eigrp 1 interface dampening-interval 30
 physical-interface Ethernet0/0
```

Related Commands

Command	Description
debug vmi	Displays debugging output for virtual multipoint interfaces (VMIs)
interface vmi	Creates a virtual multipoint interface (VMI) that can be configured and applied dynamically.

eigrp log-neighbor-changes

To enable the logging of changes in Enhanced Interior Gateway Routing Protocol (EIGRP) neighbor adjacencies, use the **eigrp log-neighbor-changes** command in router configuration mode, address-family configuration mode, or service-family configuration mode. To disable the logging of changes in EIGRP neighbor adjacencies, use the **no** form of this command.

eigrp log-neighbor-changes

no eigrp log-neighbor-changes

Syntax Description This command has no arguments or keywords.

Command Default Adjacency changes are logged.

Command Modes
 Router configuration (config-router)
 Address-family configuration (config-router-af)
 Service-family configuration (config-router-sf)

Command History	Release	Modification
	11.2	This command was introduced.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
	15.0(1)M	This command was modified. Address-family configuration mode and service-family configuration mode were added.
	12.2(33)SRE	This command was modified. Address-family configuration mode and service-family configuration mode were added.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines This command enables the logging of neighbor adjacency changes to monitor the stability of the routing system and to help detect problems. Logging is enabled by default. To disable the logging of neighbor adjacency changes, use the **no** form of this command.

To enable the logging of changes for EIGRP address-family neighbor adjacencies, use the **eigrp log-neighbor-changes** command in address-family configuration mode.

To enable the logging of changes for EIGRP service-family neighbor adjacencies, use the **eigrp log-neighbor-changes** command in service-family configuration mode.

Examples

The following configuration disables logging of neighbor changes for EIGRP process 209:

```
Router(config)# router eigrp 209
Router(config-router)# no eigrp log-neighbor-changes
```

The following configuration enables logging of neighbor changes for EIGRP process 209:

```
Router(config)# router eigrp 209
Router(config-router)# eigrp log-neighbor-changes
```

The following example shows how to disable logging of neighbor changes for EIGRP address-family with autonomous-system 4453:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# no eigrp log-neighbor-changes
Router(config-router-af)# exit-address-family
```

The following configuration enables logging of neighbor changes for EIGRP service-family process 209:

```
Router(config)# router eigrp 209
Router(config-router)# service-family ipv4 autonomous-system 4453
Router(config-router-sf)# eigrp log-neighbor-changes
Router(config-router-sf)# exit-service-family
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
exit-address-family	Exits address-family configuration mode.
exit-service-family	Exits service-family configuration mode.
router eigrp	Configures the EIGRP routing process.
service-family	Specifies service-family configuration mode.

eigrp log-neighbor-warnings

To enable the logging of Enhanced Interior Gateway Routing Protocol (EIGRP) neighbor warning messages, use the **eigrp log-neighbor-warnings** command in router configuration mode, address-family configuration mode, or service-family configuration mode. To disable the logging of EIGRP neighbor warning messages, use the **no** form of this command.

eigrp log-neighbor-warnings [*seconds*]

no eigrp log-neighbor-warnings

Syntax Description	<i>seconds</i>	(Optional) The time interval (in seconds) between repeated neighbor warning messages. The range is from 1 to 65535. The default is 10.
---------------------------	----------------	----------------------------------------------------------------------------------------------------------------------------------------

Command Default	Neighbor warning messages are logged at 10-second intervals.
------------------------	--------------------------------------------------------------

Command Modes	Router configuration (config-router) Address-family configuration (config-router-af) Service-family configuration (config-router-sf)
----------------------	--------------------------------------------------------------------------------------------------------------------------------------------

Command History	Release	Modification
	12.0(5)	This command was introduced.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
	15.0(1)M	This command was modified. Address-family and service-family configuration modes were added.
	12.2(33)SRE	This command was modified. Address-family and service-family configuration modes were added.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines	<p>When neighbor warning messages occur, they are logged by default. With this command, you can disable and enable neighbor warning messages, and you can configure the interval between repeated neighbor warning messages.</p> <p>To enable the logging of warning messages for an EIGRP address family, use the eigrp log-neighbor-warnings command in address-family configuration mode.</p> <p>To enable the logging of warning messages for an EIGRP service family, use the eigrp log-neighbor-warnings command in service-family configuration mode.</p>
-------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Examples

The following command will log neighbor warning messages for EIGRP process 209 and repeat the warning messages in 5-minute (300 seconds) intervals:

```
Router(config)# router eigrp 209
Router(config-router)# eigrp log-neighbor-warnings 300
```

The following example logs neighbor warning messages for the service family with autonomous system number 4453 and repeats the warning messages in five-minute (300 second) intervals:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 4453
Router(config-router-sf)# eigrp log-neighbor-warnings 300
```

The following example logs neighbor warning messages for the address family with autonomous system number 4453 and repeats the warning messages in five-minute (300 second) intervals:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# eigrp log-neighbor-warnings 300
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
exit-address-family	Exits address-family configuration mode.
exit-service-family	Exits service-family configuration mode.
router eigrp	Configures the EIGRP routing process.
service-family	Specifies service-family configuration mode.

eigrp router-id

To set the router ID used by Enhanced Interior Gateway Routing Protocol (EIGRP) when communicating with its neighbors, use the **eigrp router-id** command in router configuration mode, address-family configuration mode, or service-family configuration mode. To remove the configured router ID, use the **no** form of this command.

eigrp router-id *router-id*

no eigrp router-id [*router-id*]

Syntax Description	<i>router-id</i>	EIGRP router ID in IP address format.
--------------------	------------------	---------------------------------------

Command Default	EIGRP automatically selects an IP address to use as the router ID when an EIGRP process is started. The highest local IP address is selected and loopback interfaces are preferred. The router ID is not changed unless the EIGRP process is removed with the no router eigrp command or if the router ID is manually configured with the eigrp router-id command.
-----------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Modes	Router configuration (config-router) Address-family configuration (config-router-af) Service-family configuration (config-router-sf)
---------------	--------------------------------------------------------------------------------------------------------------------------------------------

Command History	Release	Modification
	12.1	This command was introduced.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
	15.0(1)M	This command was modified. Address-family configuration mode and service-family configuration mode were added.
	12.2(33)SRE	This command was modified. Address-family configuration mode and service-family configuration mode were added.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines	The router ID is used to identify the originating router for external routes. If an external route is received with the local router ID, the route is discarded. The router ID can be configured with any IP address with two exceptions; 0.0.0.0 and 255.255.255.255 are not legal values and cannot be entered. A unique value should be configured for each router.
------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

In EIGRP named IPv4, named IPv6, and Cisco Service Advertisement Framework (SAF) configurations, the *router-id* is also included for identifying internal routes and loop detection.

Examples

The following example configures 172.16.1.3 as a fixed router ID:

```
Router(config)# router eigrp 209
Router(config-router)# eigrp router-id 172.16.1.3
```

The following example configures 172.16.1.3 as a fixed router ID for service-family autonomous-system 4533:

```
Router(config)# router eigrp 209
Router(config-router)# service-family ipv4 autonomous-system 4533
Router(config-router-sf)# eigrp router-id 172.16.1.3
```

The following example configures 172.16.1.3 as a fixed router ID for address-family autonomous-system 4533:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4533
Router(config-router-af)# eigrp router-id 172.16.1.3
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
router eigrp	Configures the EIGRP routing process.
service-family	Specifies service-family configuration mode.

eigrp stub

To configure a router as a stub using Enhanced Interior Gateway Routing Protocol (EIGRP), use the **eigrp stub** command in router configuration mode or address-family configuration mode. To disable the EIGRP stub routing feature, use the **no** form of this command.

eigrp stub [**receive-only**] [**leak-map** *name*] [**connected**] [**static**] [**summary**] [**redistributed**]

no eigrp stub

Syntax Description

receive-only	(Optional) Sets the router as a receive-only neighbor.
leak-map <i>name</i>	(Optional) Allows dynamic prefixes based on a leak map.
connected	(Optional) Advertises connected routes.
static	(Optional) Advertises static routes.
summary	(Optional) Advertises summary routes.
redistributed	(Optional) Advertises redistributed routes from other protocols and autonomous systems.

Command Default

Stub routing is not enabled by default.

Command Modes

Router configuration (config-router)
Address-family configuration (config-router-af)

Command History

Release	Modification
12.0(7)T	This command was introduced.
12.0(15)S	This command was integrated into Cisco IOS Release 12.0(15)S.
12.2	The redistributed keyword was added.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family configuration mode was added to support EIGRP named configurations. The leak-map keyword and <i>name</i> argument were added. This command replaces the stub command.
12.2(33)SRE	This command was modified. Address-family configuration mode was added to support EIGRP named configurations. The leak-map keyword and <i>name</i> argument were added. This command replaces the stub command.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Release	Modification
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was modified. Address-family configuration mode was added to support EIGRP named configurations. The leak-map keyword and <i>name</i> argument were added. This command replaces the stub command.

Usage Guidelines

Use the **eigrp stub** command to configure a router as a stub where the router directs all IP traffic to a distribution router, unless stub leaking is configured.

The **eigrp stub** command can be modified with several options, and these options can be used in any combination except for the **receive-only** keyword. The **receive-only** keyword will restrict the router from sharing any of its routes with any other router in that EIGRP autonomous system, and the **receive-only** keyword will not permit any other option to be specified because it prevents any type of route from being sent. The four other optional keywords (**connected**, **static**, **summary**, **leak-map**, and **redistributed**) can be used in any combination but cannot be used with the **receive-only** keyword.

If any of these five keywords is used with the **eigrp stub** command, only the route types specified by the particular keyword(s) will be sent. Route types specified by the remaining keywords will not be sent.

The **connected** keyword permits the EIGRP stub routing feature to send connected routes. If the connected routes are not covered by a network statement, it may be necessary to redistribute connected routes with the **redistribute connected** command under the EIGRP process. This option is enabled by default.

The **static** keyword permits the EIGRP stub routing feature to send static routes. Without the configuration of this option, EIGRP will not send any static routes, including internal static routes that normally would be automatically redistributed. It will still be necessary to redistribute static routes with the **redistribute static** command.

The **summary** keyword permits the EIGRP stub routing feature to send summary routes. Summary routes can be created manually with the **summary address** command or automatically at a major network border router with the **auto-summary** command enabled. This option is enabled by default.

The **redistributed** keyword permits the EIGRP stub routing feature to send other routing protocols and autonomous systems. Without the configuration of this option, EIGRP will not advertise redistributed routes.

The **leak-map** keyword permits the EIGRP stub routing feature to reference a leak map that identifies routes that are allowed to be advertised on an EIGRP stub router that would normally have been suppressed.

Examples

In the following example, the **eigrp stub** command is used to configure the router as a stub that advertises connected and summary routes:

```
Router(config)# router eigrp 1
Router(config-router)# network 10.0.0.0
Router(config-router)# eigrp stub
```

In the following named configuration example, the **eigrp stub** command is used to configure the router as a stub that advertises routes learned from a directly connected client:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# network 10.0.0.0
Router(config-router-af)# eigrp stub connected
```

In the following example, the **eigrp stub** command is issued with the **connected** and **static** keywords to configure the router as a stub that advertises connected and static routes (sending summary routes will not be permitted):

```
Router(config)# router eigrp 1
Router(config-router)# network 10.0.0.0
Router(config-router)# eigrp stub connected static
```

In the following named configuration example, the **eigrp stub** command is issued with the **connected** and **static** keywords to configure the router as a stub that advertises connected and static routes (sending summary routes will not be permitted):

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# network 10.0.0.0
Router(config-router-af)# eigrp stub connected static
```

In the following example, the **eigrp stub** command is issued with the **receive-only** keyword to configure the router as a receive-only neighbor (connected, summary, and static routes will not be sent):

```
Router(config)# router eigrp 1
Router(config-router)# network 10.0.0.0 eigrp
Router(config-router)# eigrp stub receive-only
```

In the following named configuration example, the **eigrp stub** command is issued with the **receive-only** keyword to configure the router as a receive-only neighbor (connected, summary, and static routes will not be sent):

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# network 10.0.0.0
Router(config-router-af)# eigrp stub receive-only
```

In the following example, the **eigrp stub** command is issued with the **redistributed** keyword to configure the router to advertise other protocols and autonomous systems:

```
Router(config)# router eigrp 1
Router(config-router)# network 10.0.0.0 eigrp
Router(config-router)# eigrp stub redistributed
```

In the following named configuration example, the **eigrp stub** command is issued with the **redistributed** keyword to configure the router to advertise other protocols and autonomous systems:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# network 10.0.0.0
Router(config-router-af)# eigrp stub redistributed
```

In the following example, the **eigrp stub** command is issued with the **leak-map** *name* keyword/argument pair to configure the router to reference a leak map that identifies routes that would normally have been suppressed:

```
Router(config)# router eigrp
Router(config-router)# network 10.0.0.0
Router(config-router)# eigrp stub leak-map map1
```

In the following named configuration example, the **eigrp stub** command is issued with the **leak-map** *name* keyword/argument pair to configure the router to reference a leak map that identifies routes that would normally have been suppressed:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
```

```
Router(config-router-af)# network 10.0.0.0  
Router(config-router-af) eigrp stub leak-map map1
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
network (EIGRP)	Specifies the network for an EIGRP routing process.
router eigrp	Configures the EIGRP address-family process.

exit-address-family

To exit from address-family configuration mode, use the **exit-address-family** command in address-family configuration mode.

exit-address-family

Syntax Description This command has no arguments or keywords.

Command Default The router remains in address-family configuration mode.

Command Modes Address-family configuration (config-router-af)
VRF address-family configuration (config-vrf-af)

Command History	Release	Modification
	12.0(5)T	This command was introduced.
	12.0(22)S	Enhanced Interior Gateway Routing Protocol (EIGRP) support was added in Cisco IOS Release 12.0(22)S.
	12.2(14)S	This command was integrated into Cisco IOS Release 12.2(14)S.
	12.2(15)T	EIGRP support was added in Cisco IOS Release 12.2(15)T.
	12.2(18)S	EIGRP support was added.
	12.2(17b)SXA	This command was integrated into Cisco IOS Release 12.2(17b)SXA.
	12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines Use the **exit-address-family** command to exit address-family configuration mode and return to router configuration mode.

This command can be abbreviated to **exit**.

Examples The following example shows how to exit address-family configuration mode and return to router configuration mode:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# exit-address-family
Router(config-router)#
```

The following example shows how to exit VRF address-family configuration mode and return to VRF configuration mode:

```
Router(config)# vrf definition vrf1
Router(config-vrf)# address-family ipv6
Router(config-vrf-af)# exit-address-family
Router(config-vrf)#
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
address-family ipv4	Enters IPv4 address family configuration mode.
address-family ipv6	Enters IPv6 address family configuration mode.
address-family nsap	Enters CLNS address family configuration mode.
address-family vpnv4	Enters VPNv4 address family configuration mode.
address-family (VRF)	Selects an address family type for a VRF table and enters VRF address-family configuration mode.
router eigrp	Configures the EIGRP address-family process.

exit-af-interface

To exit address-family interface configuration mode, use the **exit-af-interface** command in address-family interface configuration mode.

exit-af-interface

Syntax Description

This command has no arguments or keywords.

Command Default

The router remains in address-family interface configuration mode.

Command Modes

Address-family interface configuration (config-router-af-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Use the **exit-af-interface** command to exit address-family interface configuration mode and return to address-family configuration mode.

Examples

The following example shows how to exit address-family interface configuration mode:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# af-interface default
Router(config-router-af-interface)# exit-af-interface
Router(config-router-af)#
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
router eigrp	Configures the EIGRP address-family process.

exit-af-topology

To exit address-family topology configuration mode, use the **exit-af-topology** command in address-family topology configuration mode.

exit-af-topology

Syntax Description

This command has no arguments or keywords.

Command Default

The router remains in address-family topology configuration mode.

Command Modes

Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Use the **exit-af-topology** command to exit address-family topology configuration mode and return to address-family configuration mode.

Examples

The following example shows how to exit address-family topology configuration mode:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# topology base
Router(config-router-af-topology)# exit-af-topology
Router(config-router-af)#
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
router eigrp	Configures the EIGRP address-family process.
topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters address-family topology configuration mode.

hello-interval

To configure the hello interval for the Enhanced Interior Gateway Routing Protocol (EIGRP) address-family or service-family configurations, use the **hello-interval** command in address-family interface configuration mode or service-family interface configuration mode. To configure the default hello interval, use the **no** form of this command.

hello-interval *seconds*

no hello-interval

Syntax Description

<i>seconds</i>	Hello interval in seconds. The range is 1 to 65535. The default is 60 for low-speed nonbroadcast multiaccess (NBMA) networks, and 5 for all other networks.
----------------	-------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Default

The EIGRP hello interval is 60 seconds for low-speed NBMA networks and 5 seconds for all other networks.

Command Modes

Address-family interface configuration (config-router-af-interface)
Service-family interface configuration (config-router-sf-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines

The 60-second default applies only to low-speed, NBMA media. Low speed is considered a rate of T1 or slower, as specified by the **bandwidth** command in interface configuration mode.

For the purposes of EIGRP, Frame Relay and Switched Multimegabit Data Service (SMDS) networks are considered to be NBMA if the interface has not been configured to use physical multicasting. Otherwise, Frame Relay and SMDS networks are not considered to be NBMA.

Examples

The following example configures a 10-second hello interval for address-family Ethernet interface 0/0:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af-interface)# af-interface ethernet0/0
Router(config-router-af-interface)# hello-interval 10
```

The following example sets a 10 second hello-interval for service-family Ethernet interface 0/0:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 4533
Router(config-router-sf)# sf-interface Ethernet 0/0
Router(config-router-sf-interface)# hello-interval 10
```

Related Commands	Command	Description
	address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
	af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
	hold-time	Configures the hold time for EIGRP address-family or service-family configurations.
	router eigrp	Configures the EIGRP address-family process.
	service-family	Specifies service-family configuration mode.
	sf-interface	Configures interface-specific commands under a service family.

hold-time

To configure the hold time for Enhanced Interior Gateway Routing Protocol (EIGRP) address-family or service-family configurations, use the **hold-time** command in address-family interface configuration mode or service-family interface configuration mode. To configure the default hold time, use the **no** form of this command.

hold-time *seconds*

no hold-time

Syntax Description

<i>seconds</i>	Interval, in seconds, before a neighbor is considered down. Valid range is 1 to 65535 seconds (approximately 18 hours). The default is 180 seconds for low-speed nonbroadcast multiaccess (NBMA) networks and 15 seconds for all other networks.
----------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Default

The EIGRP hold time is 180 seconds for NBMA networks and 15 seconds for all other networks.

Command Modes

Address-family interface configuration (config-router-af-interface)
Service-family interface configuration (config-router-sf-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines

On very congested and large networks, the default hold time may not be sufficient for all routers and access servers to receive hello packets from neighbors. In this case, increase the hold time duration. The hold time should be at least three times the hello interval. If a router does not receive a hello packet within the specified hold time, services through this router are considered unavailable. Increasing the hold time will delay route convergence across the network.

Examples

The following example sets a 50-second hold time for address-family Ethernet interface 0/0:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af-interface)# af-interface ethernet0/0
Router(config-router-af-interface)# hold-time 50
```

The following example sets a 40-second hold time for service-family Ethernet interface 0/0:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 4533
Router(config-router-sf)# sf-interface Ethernet 0/0
Router(config-router-sf-interface)# hold-time 40
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
router eigrp	Configures the EIGRP routing process.
hello-interval	Configures the hello interval for EIGRP address-family or service-family configurations.
router eigrp	Configures the EIGRP address-family process.
service-family	Specifies service-family configuration mode.
sf-interface	Configures interface-specific commands under service-family.

ip authentication key-chain eigrp

To enable authentication of Enhanced Interior Gateway Routing Protocol (EIGRP) packets, use the **ip authentication key-chain eigrp** command in interface configuration mode. To disable such authentication, use the **no** form of this command.

ip authentication key-chain eigrp *as-number key-chain*

no ip authentication key-chain eigrp *as-number key-chain*

Syntax Description

<i>as-number</i>	Autonomous system number to which the authentication applies.
<i>key-chain</i>	Name of the authentication key chain.

Defaults

No authentication is provided for EIGRP packets.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
11.2F	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Examples

The following example applies authentication to autonomous system 2 and identifies a key chain named SPORTS:

```
ip authentication key-chain eigrp 2 SPORTS
```

Related Commands

Command	Description
accept-lifetime	Sets the time period during which the authentication key on a key chain is received as valid.
ip authentication mode eigrp	Specifies the type of authentication used in EIGRP packets.
key	Identifies an authentication key on a key chain.
key chain	Enables authentication of routing protocols.

Command	Description
key-string (authentication)	Specifies the authentication string for a key.
send-lifetime	Sets the time period during which an authentication key on a key chain is valid to be sent.

ip authentication mode eigrp

To specify the type of authentication used in Enhanced Interior Gateway Routing Protocol (EIGRP) packets, use the **ip authentication mode eigrp** command in interface configuration mode. To disable that type of authentication, use the **no** form of this command.

ip authentication mode eigrp *as-number* **md5**

no ip authentication mode eigrp *as-number* **md5**

Syntax Description

<i>as-number</i>	Autonomous system number.
md5	Keyed Message Digest 5 (MD5) authentication.

Defaults

No authentication is provided for EIGRP packets.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
11.2F	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

Configure authentication to prevent unapproved sources from introducing unauthorized or false routing messages. When authentication is configured, an MD5 keyed digest is added to each EIGRP packet in the specified autonomous system.

Examples

The following example configures the interface to use MD5 authentication in EIGRP packets in autonomous system 10:

```
ip authentication mode eigrp 10 md5
```

Related Commands

Command	Description
accept-lifetime	Sets the time period during which the authentication key on a key chain is received as valid.
ip authentication key-chain eigrp	Enables authentication of EIGRP packets.
key	Identifies an authentication key on a key chain.
key chain	Enables authentication of routing protocols.
key-string (authentication)	Specifies the authentication string for a key.
send-lifetime	Sets the time period during which an authentication key on a key chain is valid to be sent.

ip bandwidth-percent eigrp

To configure the percentage of bandwidth that may be used by Enhanced Interior Gateway Routing Protocol (EIGRP) on an interface, use the **ip bandwidth-percent eigrp** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ip bandwidth-percent eigrp *as-number percent*

no ip bandwidth-percent eigrp *as-number percent*

Syntax Description

<i>as-number</i>	Autonomous system number.
<i>percent</i>	Percent of bandwidth that EIGRP may use.

Defaults

EIGRP may use 50 percent of available bandwidth.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
11.2	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

EIGRP will use up to 50 percent of the bandwidth of a link, as defined by the **bandwidth** interface configuration command. This command may be used if some other fraction of the bandwidth is desired. Note that values greater than 100 percent may be configured. The configuration option may be useful if the bandwidth is set artificially low for other reasons.

Examples

The following example allows EIGRP to use up to 75 percent (42 kbps) of a 56-kbps serial link in autonomous system 209:

```
Router(config)# interface serial 0
Router(config-if)# bandwidth 56
Router(config-if)# ip bandwidth-percent eigrp 209 75
```

Related Commands

Command	Description
bandwidth (interface)	Sets a bandwidth value for an interface.

ip hello-interval eigrp

To configure the hello interval for an Enhanced Interior Gateway Routing Protocol (EIGRP) process, use the **ip hello-interval eigrp** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ip hello-interval eigrp *as-number seconds*

no ip hello-interval eigrp *as-number [seconds]*

Syntax Description

<i>as-number</i>	Autonomous system number.
<i>seconds</i>	Hello interval (in seconds). The range is from 1 to 65535.

Defaults

The hello interval for low-speed, nonbroadcast multiaccess (NBMA) networks is 60 seconds and 5 seconds for all other networks.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

The default of 60 seconds applies only to low-speed, NBMA media. Low speed is considered to be a rate of T1 or slower, as specified with the **bandwidth** interface configuration command. Note that for the purposes of EIGRP, Frame Relay and Switched Multimegabit Data Service (SMDS) networks may be considered to be NBMA. These networks are considered NBMA if the interface has not been configured to use physical multicasting; otherwise, they are considered not to be NBMA.

Examples

The following example sets the hello interval for Ethernet interface 0 to 10 seconds:

```
Router(config)# interface ethernet 0
Router(config-if)# ip hello-interval eigrp 109 10
```

Related Commands

Command	Description
bandwidth (interface)	Sets a bandwidth value for an interface.
ip hold-time eigrp	Configures the hold time for a particular EIGRP routing process designated by the autonomous system number.

ip hold-time eigrp

To configure the hold time for an Enhanced Interior Gateway Routing Protocol (EIGRP) process, use the **ip hold-time eigrp** command in interface configuration mode. To restore the default value, use the **no** form of this command.

ip hold-time eigrp *as-number seconds*

no ip hold-time eigrp *as-number seconds*

Syntax Description

<i>as-number</i>	Autonomous system number.
<i>seconds</i>	Hold time (in seconds). The range is from 1 to 65535.

Defaults

The EIGRP hold time is 180 seconds for low-speed, nonbroadcast multiaccess (NBMA) networks and 15 seconds for all other networks.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

On very congested and large networks, the default hold time might not be sufficient time for all routers and access servers to receive hello packets from their neighbors. In this case, you may want to increase the hold time.

We recommend that the hold time be at least three times the hello interval. If a router does not receive a hello packet within the specified hold time, routes through this router are considered unavailable.

Increasing the hold time delays route convergence across the network.

The default of 180 seconds hold time and 60 seconds hello interval apply only to low-speed, NBMA media. Low speed is considered to be a rate of T1 or slower, as specified with the **bandwidth** interface configuration command.

Examples

The following example sets the hold time for Ethernet interface 0 to 40 seconds:

```
Router(config)# interface ethernet 0
Router(config-if)# ip hold-time eigrp 109 40
```

Related Commands

Command	Description
bandwidth (interface)	Sets a bandwidth value for an interface.
ip hello-interval eigrp	Configures the hello interval for the EIGRP routing process designated by an autonomous system number.

ip next-hop-self eigrp

To instruct EIGRP that the IP next hop is itself, use the **ip next-hop-self eigrp** command in interface configuration mode. To instruct EIGRP to use the received next hop rather than itself, use the **no** form of this command.

ip next-hop-self eigrp *autonomous-system-number*

no ip next-hop-self eigrp *autonomous-system-number*

Syntax Description

autonomous-system-number Autonomous system number.

Command Default

EIGRP always sets the IP next-hop value to be itself.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
12.3	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

EIGRP will, by default, set the IP next-hop value to be itself for routes that it is advertising, even when advertising those routes back out the same interface where it learned them. To change this default, you must use the **no ip next-hop-self eigrp** interface configuration command to instruct EIGRP to use the received next hop value when advertising these routes. Some exceptions to this guideline follow:

- If spoke-to-spoke dynamic tunnels are not wanted, then the **no ip next-hop-self eigrp** command is not needed.
- If spoke-to-spoke dynamic tunnels are wanted, then you must use process switching on the tunnel interface on the spoke routers. Otherwise, you will need to use a different routing protocol over Dynamic Multipoint VPN (DMVPN).

Examples

The following example changes the default IP next hop value and instructs EIGRP to use the received next hop value:

```
interface serial 0
no ip next-hop-self eigrp 101
```

ip split-horizon eigrp

To enable Enhanced Interior Gateway Routing Protocol (EIGRP) split horizon, use the **ip split-horizon eigrp** command in interface configuration mode. To disable split horizon, use the **no** form of this command.

ip split-horizon eigrp *as-number*

no ip split-horizon eigrp *as-number*

Syntax Description

<i>as-number</i>	Autonomous system number.
------------------	---------------------------

Defaults

The behavior of this command is enabled by default.

Command Modes

Interface configuration (config-if)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

For networks that include links over X.25 packet-switched networks (PSNs), you can use the **neighbor** router configuration command to defeat the split horizon feature. As an alternative, you can explicitly specify the **no ip split-horizon eigrp** command in your configuration. However, if you do so, you must similarly disable split horizon for all routers and access servers in any relevant multicast groups on that network.



Note

In general, we recommend that you not change the default state of split horizon unless you are certain that your application requires the change in order to properly advertise routes. Remember that if split horizon is disabled on a serial interface and that interface is attached to a packet-switched network, you must disable split horizon for all routers and access servers in any relevant multicast groups on that network.

Examples

The following example disables split horizon on a serial link connected to an X.25 network:

```
interface serial 0
 encapsulation x25
```

ip split-horizon eigrp

```
no ip split-horizon eigrp 101
```

Related Commands

Command	Description
ip split-horizon (RIP)	Enables the split horizon mechanism.
neighbor (EIGRP)	Defines a neighboring router with which to exchange routing information.

ip summary-address eigrp

To configure a summary aggregate address for a specified interface, use the **ip summary-address eigrp** command in interface configuration mode. To disable a configuration, use the **no** form of this command.

ip summary-address eigrp *as-number ip-address mask* [*admin-distance*] [**leak-map** *name*]

no ip summary-address eigrp *as-number ip-address mask*

Syntax Description

<i>as-number</i>	Autonomous system number.
<i>ip-address</i>	Summary IP address to apply to an interface.
<i>mask</i>	Subnet mask.
<i>admin-distance</i>	(Optional) Administrative distance. A value from 0 to 255.
leak-map <i>name</i>	(Optional) Route-map reference to configure route leaking through the summary.

Defaults

- An administrative distance of 5 is applied to Enhanced Interior Gateway Routing Protocol (EIGRP) summary routes.
- EIGRP automatically summarizes to the network level, even for a single host route.
- No summary addresses are predefined.
- The default administrative distance metric for EIGRP is 90.

Command Modes

Interface configuration

Command History

Release	Modification
10.0	This command was introduced.
12.0(7)T	The <i>admin-distance</i> argument was introduced.
12.3(14)T	The leak-map keyword was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

The **ip summary-address eigrp** command is used to configure interface-level address summarization. EIGRP summary routes are given an administrative distance value of 5. The administrative distance metric is used to advertise a summary without installing it in the routing table.

By default, EIGRP summarizes subnet routes to the network level. The **no auto-summary** command can be entered to configure subnet level summarization.

EIGRP Support for Leaking Routes

Configuring the **leak-map** keyword allows to advertise a component route that would otherwise be suppressed by the manual summary. Any component subset of the summary can be leaked. A route map and access list must be defined to source the leaked route.

The following is default behavior if an incomplete configuration is entered:

- If the **leak-map** keyword is configured to reference a nonexistent route map, the configuration of this keyword has no effect. The summary address is advertised but all component routes are suppressed.
- If the **leak-map** keyword is configured but the access-list does not exist or the route map does not reference the access list, the summary address and all component routes are sent.

Examples

The following example configures an administrative distance of 95 on interface Ethernet 0/0 for the 192.168.0.0/16 summary address:

```
Router(config)# router eigrp 1
Router(config-router)# no auto-summary
Router(config-router)# exit
Router(config)# interface Ethernet 0/0
Router(config-if)# ip summary-address eigrp 1 192.168.0.0 255.255.0.0 95
```

The following example configures the 10.1.1.0/24 subnet to be leaked through the 10.0.0.0 summary address:

```
Router(config)# router eigrp 1
Router(config-router)# exit
Router(config)# access-list 1 permit 10.1.1.0 0.0.0.255
Router(config)# route-map LEAK-10-1-1 permit 10
Router(config-route-map)# match ip address 1
Router(config-route-map)# exit
Router(config)# interface Serial 0/0
Router(config-if)# ip summary-address eigrp 1 10.0.0.0 255.0.0.0 leak-map LEAK-10-1-1
Router(config-if)# end
```

Related Commands

Command	Description
auto-summary (EIGRP)	Configures automatic summarization of subnet routes to network-level routes (default behavior).

log-neighbor-changes (EIGRP)

To enable the logging of changes in Enhanced Interior Gateway Routing Protocol (EIGRP) neighbor adjacencies, use the **log-neighbor-changes** command in IPX-router configuration mode. To disable this function, use the **no** form of this command.

log-neighbor-changes

no log-neighbor-changes

Syntax Description This command has no arguments or keywords.

Defaults No adjacency changes are logged.

Command Modes IPX-router configuration

Command History	Release	Modification
	11.2	This command was introduced.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.

Usage Guidelines Enable the logging of neighbor adjacency changes in order to monitor the stability of the routing system and to help detect problems. Log messages are of the following form:

%DUAL-5-NBRCHANGE: IPX EIGRP *as-number*: Neighbor *address (interface)* is *state*: *reason*

where the arguments have the following meanings:

<i>as-number</i>	Autonomous system number
<i>address (interface)</i>	Neighbor address
<i>state</i>	Up or down
<i>reason</i>	Reason for change

Examples The following configuration will log neighbor changes for EIGRP process 209:

```
ipx router eigrp 209
 log-neighbor-changes
```

log-neighbor-warnings



Note

Effective with Cisco IOS Release 15.0(1)M, 12.2(33)SRE and Cisco IOS XE Release 2.5, the **log-neighbor-warnings** command was replaced by the **eigrp log-neighbor-warnings** command for IPv4 and IPv6 configurations. The **log-neighbor-warnings** command is still available for IPX configurations.

To enable the logging of Enhanced Interior Gateway Routing Protocol (EIGRP) neighbor warning messages, use the **log-neighbor-warnings** command in router configuration mode. To disable the logging of EIGRP neighbor warning messages, use the **no** form of this command.

log-neighbor-warnings [*seconds*]

no log-neighbor-warnings

Syntax Description

seconds (Optional) The time interval (in seconds) between repeated neighbor warning messages. The range of seconds is from 1 through 65535.

Command Default

Neighbor warning messages are logged.

Command Modes

Router configuration (config-router)

Command History

Release	Modification
12.4(6)T	This command was introduced.
12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB.
12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
Cisco IOS XE Release 2.1	This command was introduced on Cisco ASR 1000 Series Routers.
15.0(1)M	This command was replaced by the eigrp log-neighbor-warnings command for IPv4 and IPv6 configurations. The log-neighbor-warnings command is still available for IPX configurations.
12.2(33)SRE	This command was replaced by the eigrp log-neighbor-warnings command for IPv4 and IPv6 configurations. The log-neighbor-warnings command is still available for IPX configurations.
Cisco IOS XE Release 2.5	This command was replaced by the eigrp log-neighbor-warnings command for IPv4 and IPv6 configurations. The log-neighbor-warnings command is still available for IPX configurations.

Usage Guidelines

When neighbor warning messages occur, they are logged by default. With the **log-neighbor-warnings** command, you can disable and enable the logging of neighbor warning messages and configure the interval between repeated neighbor warning messages.

Examples

The following example shows that neighbor warning messages will be logged for EIGRP process 1 and warning messages will be repeated in 5-minute (300 seconds) intervals:

```
Router(config)# ipv6 router eigrp 1  
Router(config-router)# log-neighbor-warnings 300
```

Related Commands

Command	Description
log-neighbor-changes	Enables the logging of changes in EIGRP neighbor adjacencies.

match extcommunity

To match Border Gateway Protocol (BGP) or Enhanced Interior Gateway Routing Protocol (EIGRP) extended community list attributes, use the **match extcommunity** command in route-map configuration mode. To remove the **match extcommunity** command from the configuration file and remove the BGP or EIGRP extended community list attribute entry, use the **no** form of this command.

match extcommunity *extended-community-list-name*

no match extcommunity *extended-community-list-name*

Syntax Description

extended-community-list-name Name of an extended community list.

Command Default

BGP and EIGRP extended community list attributes are not matched.

Command Modes

Route-map configuration (config-route-map)

Command History

Release	Modification
12.1	This command was introduced.
12.0(22)S	The maximum number of expanded extended community list numbers was changed from 199 to 500 in Cisco IOS Release 12.0(22)S.
12.2(15)T	The maximum number of expanded extended community list numbers was changed from 199 to 500 in Cisco IOS Release 12.2(15)T.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Support for EIGRP was added.
12.2(33)SRE	This command was modified. Support for EIGRP was added.
Cisco IOS XE Release 2.5	This command was modified. Support for EIGRP was added.
12.2(33)XNE	This command was modified. Support for EIGRP was added.

Usage Guidelines

Extended community attributes are used to configure, filter, and identify routes for virtual routing and forwarding instances (VRFs) and Multiprotocol Label Switching (MPLS) Virtual Private Networks (VPNs).

The **match extcommunity** command is used to configure match clauses that use extended community attributes in route maps. All of the standard rules of match and set clauses apply to the configuration of extended community attributes.

Examples

The following example shows that the routes that match extended community list 500 will have the weight set to 100. Any route that has extended community 1 will have the weight set to 100.

```
Router(config)# ip extcommunity-list 500 rt 100:2
Router(config-extcomm-list)# exit
Router(config)# route-map MAP_NAME permit 10
Router(config-route-map)# match extcommunity 1
Router(config-route-map)# set weight 100
```

Related Commands


Command	Description
ip extcommunity-list	Creates an extended community list for BGP and controls access to it.
route-map (IP)	Defines the conditions for redistributing routes from one routing protocol into another.
set extcommunity	Sets BGP extended community attributes.
set weight	Specifies the BGP weight for the routing table.
show ip extcommunity-list	Displays routes that are permitted by the extended community list.
show route-map	Displays configured route maps.

maximum-prefix

To limit the number of prefixes that are accepted under an address family by an Enhanced Interior Gateway Routing Protocol (EIGRP) process, use the **maximum-prefix** command in address family configuration mode or address family topology configuration mode. To disable this function, use the **no** form of this command.

maximum-prefix *maximum* [[*threshold*] [**dampened**] [**reset-time** *minutes*] [**restart** *minutes*] [**restart-count** *number*]] | [**warning-only**]

no maximum-prefix

Syntax Description		
<i>maximum</i>	Maximum number of prefixes allowed under an address family. The range for this argument is a number from 1 to 4294967295.	
	Note	The number of prefixes that can be configured is limited only by the available system resources on the router.
<i>threshold</i>	(Optional) The prefix percentage number. Valid values are 1 to 100. The default is 75. This value causes the router to generate syslog warning messages when the specified percentage of the maximum-prefix limit has been exceeded.	
dampened	(Optional) Configures a decay penalty to be applied to the restart-time period each time the maximum-prefix limit is exceeded. The half-life for the decay penalty is 150 percent of the default or user-defined restart-time value in minutes. This keyword is disabled by default.	
reset-time <i>minutes</i>	(Optional) Configures the router to reset the restart count to 0 after the default or user-defined reset-time period has expired. The range of values that can be applied with the <i>minutes</i> argument is from 1 to 65535 minutes. The default reset-time period is 15 minutes.	
restart <i>minutes</i>	(Optional) Configures a time period in which the router will not form adjacencies or accept redistributed routes from the Routing Information Base (RIB) after the maximum-prefix limit has been exceeded. The value for the <i>minutes</i> argument is from 1 to 65535 minutes. The default restart-time period is 5 minutes.	
restart-count <i>number</i>	(Optional) Configures the number of times a peering session can be automatically reestablished after the peering session has been torn down or after a redistribute route has been cleared and relearned because the maximum-prefix limit has been exceeded. The default restart-count limit is 3.	
		
	Caution	Once the restart count threshold has been crossed, you will need to enter the clear ip route * or clear ip eigrp neighbor command to reestablish normal peering and/or redistribution.
warning-only	(Optional) Configures the router to generate syslog messages only when the maximum-prefix limit is reached, instead of suspending peering session or route redistribution. This keyword is disabled by default.	

Command Default

The number of prefixes that are accepted under an address family by an EIGRP process is not limited.

Command Modes

Address family configuration (config-router-af)
Address family topology configuration (config-router-af-topology)

Command History

Release	Modification
12.0(29)S	This command was introduced.
12.3(14)T	This command was integrated into Cisco IOS Release 12.3(14)T.
15.0(1)M	This command was modified. Address family topology configuration mode was added for EIGRP named configurations.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
Cisco IOS XE Release 2.6	This command was integrated into Cisco IOS XE Release 2.6.

Usage Guidelines

The **maximum-prefix** is used to configure an EIGRP process to limit the number prefixes that are accepted from all sources. When the maximum-prefix limit is exceeded, sessions with remote peers are torn down, all routes learned from remote peers and through redistribution are removed from the topology and routing tables, and redistribution and peering is suspended for the default or user-defined time period.

Inherited Timer Values

Default or user-defined restart, restart-count, and reset-time values for the process-level configuration of this feature, configured with the **maximum-prefix** command, are inherited by the **redistribute maximum-prefix** and **neighbor maximum-prefix** command configurations by default. If a single peer is configured with the **neighbor maximum-prefix** command, a process-level configuration or a configuration that is applied to all neighbors will be inherited.

Examples

The following example, starting in global configuration mode, configures the maximum prefix limit for an EIGRP process, which includes routes learned through redistribution and routes learned through EIGRP peering sessions. The maximum limit is set to 50000 prefixes. When the number of prefixes learned through redistribution reaches 37,500 (75 percent of 50,000), warning messages will be displayed in the console. When the maximum prefix limit is exceeded, all peering sessions will be reset, the topology and routing tables will be cleared and redistributed routes and all peering sessions will be placed in a penalty state.

```
Router(config)# router eigrp 100
Router(config-router)# address-family ipv4 vrf VRF1
Router(config-router-af)# maximum-prefix 50000
Router(config-router-af)# end
```

The following example configures the maximum prefix limit for an EIGRP named configuration process:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# topology base
Router(config-router-af-topology)# maximum-prefix 50000
```

Related Commands

Command	Description
clear ip eigrp neighbors	Deletes entries from the EIGRP neighbor table.
clear ip eigrp vrf neighbor	Deletes neighbor entries from the VRF table.
clear ip route	Deletes routes from the IP routing table.
neighbor maximum-prefix	Limits the number of prefixes that are accepted from a single EIGRP neighbor or from all EIGRP neighbors.
redistribute maximum-prefix	Limits the number of prefixes redistributed into an EIGRP process.

metric holddown

To keep new Enhanced Interior Gateway Routing Protocol (EIGRP) routing information from being used for a certain period of time, use the **metric holddown** command in router configuration mode. To disable this feature, use the **no** form of this command.

metric holddown

no metric holddown

Syntax Description

This command has no arguments or keywords.

Command Default

The holddown state is disabled.

Command Modes

Router configuration (config-router)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.

Usage Guidelines

The holddown state keeps new routing information from being used for a certain period of time. This function can prevent routing loops caused by slow convergence. It is sometimes advantageous to disable the holddown state to increase the ability of the network to quickly respond to topology changes; this command provides this function.

Use the **metric holddown** command if other routers or access servers within the EIGRP autonomous system are not configured with the **no metric holddown** command. If all routers are not configured the same way, you increase the possibility of routing loops.

Examples

The following example disables metric holddown:

```
Router(config)# router eigrp 15  
Router(config-router)# network 172.16.0.0  
Router(config-router)# network 192.168.7.0  
Router(config-router)# no metric holddown
```

Related Commands	Command	Description
	metric maximum-hops	Causes the IP routing software to advertise as unreachable those routes with a hop count higher than is specified by the command (EIGRP only).
	metric weights (EIGRP)	Allows the tuning of the EIGRP metric calculations.

metric maximum-hops

To have the IP routing software advertise as unreachable routes with a hop count higher than is specified by the command (Enhanced Interior Gateway Routing Protocol [EIGRP] only), use the **metric maximum-hops** command in router configuration mode or address family topology configuration mode. To reset the value to the default, use the **no** form of this command.

metric maximum-hops *hops-number*

no metric maximum-hops

Syntax Description

<i>hops-number</i>	Maximum hop count (in decimal). The default value is 100; the maximum number of hops that can be specified is 255.
--------------------	--------------------------------------------------------------------------------------------------------------------

Command Default

The maximum number of hops is 100.

Command Modes

Router configuration (config-router)
Address family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
15.0(1)M	This command was modified. The address-family topology configuration mode was added.
12.2(33)SRE	This command was modified. The address-family topology configuration mode was added.
Cisco IOS XE Release 2.5	This command was modified. The address-family topology configuration mode was added.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

This command provides a safety mechanism that breaks any potential *count-to-infinity* problems. It causes the IP routing software to advertise as unreachable routes with a hop count greater than the value assigned to the *hops-number* argument.

Examples

In the following example, a router in autonomous system 71 attached to network 10.0.0.0 wants a maximum hop count of 200, doubling the default. The network administrators configured the router hop count to 200 because they have a complex WAN that can generate a large hop count under normal (nonlooping) operations.

```
Router(config)# router eigrp 71
Router(config-router)# network 172.16.0.0
Router(config-router)# metric maximum-hops 200
```

The following example shows how to configure EIGRP autonomous-system 4453 to have a maximum hop count of 200:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# topology base
Router(config-router-af-topology)# metric maximum-hops 200
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
metric holddown	Keeps new EIGRP routing information from being used for a certain period of time.
metric weights (EIGRP)	Allows the tuning of the EIGRP metric calculations.
network (EIGRP)	Specifies the network for an EIGRP routing process.
router eigrp	Configures the EIGRP address-family process.
topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters address-family topology configuration mode.

metric weights (EIGRP)

To tune Enhanced Interior Gateway Routing Protocol (EIGRP) metric calculations, use the **metric weights** command in router configuration mode or address family configuration mode. To reset the values to their defaults, use the **no** form of this command.

metric weights *tos k1 k2 k3 k4 k5*

no metric weights

Syntax Description

<i>tos</i>	Type of service. This value must always be zero.
<i>k1 k2 k3 k4 k5</i>	Constants that convert an EIGRP metric vector into a scalar quantity. Valid values are 0 to 255. Default values are: <ul style="list-style-type: none"> <i>tos</i>: 0 <i>k1</i>: 1 <i>k2</i>: 0 <i>k3</i>: 1 <i>k4</i>: 0 <i>k5</i>: 0

Command Default

EIGRP metric K values are set to their default values.

Command Modes

Router configuration (config-router)
Address family configuration (config-router-af)

Command History

Release	Modification
10.0	This command was introduced.
12.4(6)T	Support for IPv6 was added.
12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. The address-family configuration mode was added.
12.2(33)SRE	This command was modified. The address-family configuration mode was added.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was modified. The address-family configuration mode was added.

Usage Guidelines

Use this command to alter the default behavior of EIGRP routing and metric computation and allow the tuning of the EIGRP metric calculation for a particular type of service (ToS).

If k5 equals 0, the composite EIGRP metric is computed according to the following formula:

$$\text{metric} = [k1 * \text{bandwidth} + (k2 * \text{bandwidth}) / (256 - \text{load}) + k3 * \text{delay}]$$

If k5 does not equal zero, an additional operation is performed:

$$\text{metric} = \text{metric} * [k5 / (\text{reliability} + k4)]$$

Bandwidth is inverse minimum bandwidth of the path in bps scaled by a factor of $2.56 * 10^{12}$. The range is from a 1200-bps line to 10 terabits per second.

Delay is in units of 10 microseconds. The range of delay is from 10 microseconds to 168 seconds. A delay of all ones indicates that the network is unreachable.

The delay parameter is stored in a 32-bit field, in increments of 39.1 nanoseconds. The range of delay is from 1 (39.1 nanoseconds) to hexadecimal FFFFFFFF (decimal 4,294,967,040 nanoseconds). A delay of all ones (that is, a delay of hexadecimal FFFFFFFF) indicates that the network is unreachable.

Table 2 lists the default values used for several common media.

Table 2 *Bandwidth Values by Media Type*

Media Type	Delay	Bandwidth
Satellite	51,200,000 (2 seconds)	5120 (500 megabits)
Ethernet	25600 (1 millisecond [ms])	256,000 (10 megabits)
1.544 Mbps	51,200,000 (20 ms)	1,657,856 bits
64 kbps	51,200,000 (20 ms)	40,000,000 bits
56 kbps	51,200,000 (20 ms)	45,714,176 bits
10 kbps	51,20,000 (20 ms)	256,000,000 bits
1 kbps	51,200,000 (20 ms)	2,560,000,000 bits

Reliability is given as a fraction of 255. That is, 255 is 100 percent reliability or a perfectly stable link.

Load is given as a fraction of 255. A load of 255 indicates a completely saturated link.

Examples

The following example sets the metric weights to slightly different values than the defaults:

```
Router(config)# router eigrp 109
Router(config-router)# network 192.168.0.0
Router(config-router)# metric weights 0 2 0 2 0 0
```

The following example configures an address-family metric weight to tos: 0; K1: 2; K2: 0; K3: 2; K4: 0; K5: 0.

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4533
Router(config-router-af)# metric weights 0 2 0 2 0 0
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
bandwidth (interface)	Sets a bandwidth value for an interface.
delay (interface)	Sets a delay value for an interface.
ipv6 router eigrp	Configures the EIGRP for IPv6 routing process.
metric holddown	Keeps new EIGRP routing information from being used for a certain period of time.
metric maximum-hops	Causes the IP routing software advertise as unreachable routes with a hop count higher than is specified by the command (EIGRP only).
router eigrp	Configures the EIGRP address-family process.

neighbor (EIGRP)

To define a neighboring router with which to exchange routing information on a router that is running Enhanced Interior Gateway Routing Protocol (EIGRP), use the **neighbor** command in router configuration mode or address-family configuration mode. To remove an entry, use the **no** form of this command.

neighbor {*ip-address* | *ipv6-address*} *interface-type* *interface-number* [**remote** *maximum-hops*]

no neighbor {*ip-address* | *ipv6-address*} *interface-type* *interface-number*

Syntax Description

<i>ip-address</i>	IP address of a peer router with which routing information will be exchanged.
<i>ipv6-address</i>	IPv6 address of a peer router with which routing information will be exchanged.
<i>interface-type</i>	Interface through which peering is established.
<i>interface-number</i>	Number of the interface or subinterface.
remote	(Optional) Specifies that the neighbor is remote. This keyword is available only for loopback interfaces.
<i>maximum-hops</i>	(Optional) Maximum hop count. Valid range is 3 to 100. This argument is available only when the remote keyword is configured.

Command Default

No neighboring routers are defined.

Command Modes

Router configuration (config-router)
Address-family configuration (config-router-af)

Command History

Release	Modification
10.0	This command was introduced.
12.4(6)T	The <i>ipv6-address</i> argument was added.
12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family configuration mode was added.
12.2(33)SRE	This command was modified. Address-family configuration mode was added.
Cisco IOS XE Release 2.5.	This command was modified. Address-family configuration mode was added.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

Multiple neighbor statements can be used to establish peering sessions with specific EIGRP neighbors. The interface through which EIGRP will exchange routing updates must be specified in the neighbor statement. The interfaces through which two EIGRP neighbors exchange routing updates must be configured with IP addresses from the same network.

**Note**

Configuring the **passive-interface** command suppresses all incoming and outgoing routing updates and hello messages. EIGRP neighbor adjacencies cannot be established or maintained over an interface that is configured as passive.

Examples

The following example configures EIGRP peering sessions with the 192.168.1.1 and 192.168.2.2 neighbors:

```
Router(config)# router eigrp 1
Router(config-router)# network 192.168.0.0
Router(config-router)# neighbor 192.168.1.1 Ethernet 0/0
Router(config-router)# neighbor 192.168.2.2 Ethernet 1/1
```

The following named configuration example configures EIGRP to send address-family updates to specific neighbors:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# neighbor 192.168.1.1 ethernet0/0
Router(config-router-af)# neighbor 10.1.1.2 loopback0 remote 10
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
ipv6 router eigrp	Configures the EIGRP for IPv6 routing process.
passive-interface	Disables sending EIGRP hello packets and disables routing updates on an interface.
router eigrp	Configures the EIGRP address-family process.

neighbor description

To associate a description with a neighbor, use the **neighbor description** command in router configuration mode or address family configuration mode. To remove the description, use the **no** form of this command.

neighbor {*ip-address* | *peer-group-name*} **description** *text*

no neighbor {*ip-address* | *peer-group-name*} **description** [*text*]

Syntax Description

<i>ip-address</i>	IP address of the neighbor.
<i>peer-group-name</i>	Name of an EIGRP peer group. This argument is not available in address-family configuration mode.
<i>text</i>	Text (up to 80 characters in length) that describes the neighbor.

Command Default

There is no description of the neighbor.

Command Modes

Router configuration (config-router)
Address family configuration (config-router-af)

Command History

Release	Modification
11.3	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family configuration mode was added.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
Cisco IOS XE Release 2.6	This command was integrated into Cisco IOS XE Release 2.6.

Examples

In the following examples, the description of the neighbor is “peer with example.com”:

```
Router(config)# router bgp 109
Router(config-router)# network 172.16.0.0
Router(config-router)# neighbor 172.16.2.3 description peer with example.com
```

In the following example, the description of the address family neighbor is “address-family-peer”:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# network 172.16.0.0
Router(config-router-af)# neighbor 172.16.2.3 description address-family-peer
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address family configuration mode to configure an EIGRP routing instance.
network (EIGRP)	Specifies the network for an EIGRP routing process.
router eigrp	Configures the EIGRP address family process.

neighbor maximum-prefix (EIGRP)

To limit the number of prefixes that are accepted from a single Enhanced Interior Gateway Protocol (EIGRP) neighbor or from all EIGRP neighbors, use the **neighbor maximum-prefix** command in address family configuration mode. To disable this function, use the **no** form of this command.

Single Neighbor Configuration

neighbor *ip-address* **maximum-prefix** *maximum* [*threshold*] [**warning-only**]

no neighbor *ip-address* **maximum-prefix**

All Neighbor Configuration

neighbor maximum-prefix *maximum* [*threshold*] [[**dampened**] [**reset-time** *minutes*] [**restart** *minutes*] [**restart-count** *number*] | **warning-only**]

no neighbor maximum-prefix

Syntax Description		
<i>ip-address</i>		IP address of a single peer.
<i>maximum</i>		Maximum number of prefixes accepted. The range for this argument is a number from 1 to 4294967295.
	Note	The number of prefixes that can be configured is limited only by the available system resources on the router.
<i>threshold</i>		(Optional) Configures the router to generate syslog warning messages when the specified percentage of the maximum-prefix limit has been reached. The prefix percentage number that can be configured for the <i>threshold</i> argument is from 1 to 100. The default is 75 percent.
warning-only		(Optional) Configures the router to generate syslog messages only when the maximum-prefix limit is reached, instead of terminating the peering session. This keyword is disabled by default.
dampened		(Optional) Configures a decay penalty to be applied to the restart-time period each time the maximum-prefix limit is reached. The half-life for the decay penalty is 150 percent of the default or user-defined restart-time value in minutes. This keyword is disabled by default.
reset-time <i>minutes</i>		(Optional) Configures the router to reset the restart count to 0 after the default or configured reset-time period has expired. The value for the <i>minutes</i> argument is from 1 to 65535 minutes. The default reset-time period is 15 minutes.

restart <i>minutes</i>	(Optional) Configures a time period in which the router will not form adjacencies or accept redistributed routes from the RIB after the maximum-prefix limit has been reached. The value for the <i>minutes</i> argument is from 1 to 65535 minutes. The default restart-time period is 5 minutes.
-------------------------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

restart-count <i>number</i>	(Optional) Configures the number of times a peering session can be automatically reestablished after the peering session has been torn down or after a redistribute route has been cleared and relearned because the maximum-prefix limit has been reached. The default restart-count limit is 3.
------------------------------------	---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

**Caution**

Once the restart count threshold has been crossed, you will need to enter the **clear ip route *** or **clear ip eigrp neighbor** command to reestablish normal peering and/or redistribution.

Command Default

The number of prefixes that can be configured is limited only by the available system resources on the router.

Command Modes

Address family configuration (config-router-af)

Command History

Release	Modification
12.0(29)S	This command was introduced.
12.3(14)T	This command was integrated into Cisco IOS Release 12.3(14)T.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
Cisco IOS XE Release 2.6	This command was integrated into Cisco IOS XE Release 2.6.

Usage Guidelines

The **neighbor maximum-prefix** command can be configured to protect an individual peering session or to protect all peering sessions. When this feature is enabled and the maximum-prefix limit has been reached, the router will tear down the peering session, clear all routes that were learned from the peer, and then place the peer in a penalty state for the default or user-defined time period. After the penalty time period expires, normal peering will be reestablished.

**Note**

In EIGRP, **neighbor** commands have been traditionally used to configure static neighbors. In the context of the EIGRP Prefix Limiting feature, however, the **neighbor maximum-prefix** command can be used to configure the maximum-prefix limit for both statically configured neighbors and dynamically discovered neighbors.

When you configure the **neighbor maximum-prefix** command to protect a single peering session, only the maximum-prefix limit, the percentage threshold, and the warning-only configuration options can be configured. Session dampening, restart, and reset timers are configured on a global basis.

Inherited Timer Values

Default or user-defined restart, restart-count, and reset-time values for the process-level configuration of this feature, configured with the **maximum-prefix** command, are inherited by the **redistribute maximum-prefix** and **neighbor maximum-prefix** command configurations by default. If a single peer is configured with the **neighbor maximum-prefix** command, a process-level configuration or a configuration that is applied to all neighbors will be inherited.

Examples

Configuring the Maximum Prefix Limit for a Single Peer

The following example, starting in global configuration mode, configures the maximum prefix limit for a single peer. The maximum limit is set to 1000 prefixes, and the warning threshold is set to 80 percent. When the maximum prefix limit is reached for the configured neighbor, adjacency with this neighbor will be brought down and all routes learned from it will be cleared. The neighbor will be placed in a penalty state for 4 minutes (user-defined penalty value). This function will not affect the relationship with any other neighbor.

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# neighbor 10.0.0.1 maximum-prefix 1000 80
Router(config-router-af)# end
```

Configuring the Maximum Prefix Limit for All Peers

The following example, starting in global configuration mode, configures the maximum prefix limit for all peers. The maximum limit is set to 10,000 prefixes, the warning threshold is set to 90 percent, the restart timer is set to 4 minutes, a decay penalty is configured for the restart timer with the **dampened** keyword, and all timers are configured to be reset to 0 every 60 minutes. When the maximum prefix limit is reached for any neighbor, adjacency with this neighbor will be brought down and all routes learned from it will be cleared. This function will not affect the relationship with any other neighbor. The offending peer will be placed in a penalty state for 4 minutes (user-defined penalty value). A dampening exponential decay penalty will also be applied.

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 virtual-name autonomous-system 4453
Router(config-router-af)# neighbor maximum-prefix 10000 90 dampened reset-time 60
restart 4
Router(config-router-af)# end
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address family configuration mode to configure an EIGRP routing instance.
clear ip eigrp neighbors	Deletes entries from the EIGRP neighbor table.
clear ip eigrp vrf neighbor	Deletes neighbor entries from the VRF table.
clear ip route	Deletes routes from the IP routing table.
neighbor maximum-prefix	Limits the number of prefixes that are accepted from a single EIGRP neighbor or from all EIGRP neighbors.
redistribute maximum-prefix (EIGRP)	Limits the number of prefixes redistributed into an EIGRP process.

network (EIGRP)

To specify the network for an Enhanced Interior Gateway Routing Protocol (EIGRP) routing process, use the **network** command in router configuration mode or address-family configuration mode. To remove an entry, use the **no** form of this command.

network *ip-address* [*wildcard-mask*]

no network *ip-address* [*wildcard-mask*]

Syntax Description

<i>ip-address</i>	IP address of the directly connected network.
<i>wildcard-mask</i>	(Optional) Wildcard mask.

Command Default

No networks are specified.

Command Modes

Router configuration (config-router)
Address-family configuration (config-router-af)

Command History

Release	Modification
10.0	This command was introduced.
12.0(4)T	The <i>network-mask</i> argument was added.
12.0(22)S	Address-family support for EIGRP was added.
12.2(15)T	Address-family support for EIGRP was added.
12.2(18)S	Address-family support for EIGRP was added.
12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

When the **network** command is configured for an EIGRP routing process, the router matches one or more local interfaces. The **network** command matches only local interfaces that are configured with addresses that are within the same subnet as the address that has been configured with the **network** command. The router then establishes neighbors through the matched interfaces. There is no limit to the number of network statements (**network** commands) that can be configured on a router.

When entered in address-family configuration mode, this command applies only to named EIGRP IPv4 configurations. Named IPv6 and Service Advertisement Framework (SAF) configurations do not support this command in address-family configuration mode.

Examples

The following example configures EIGRP autonomous system 1 and establishes neighbors through network 172.16.0.0 and 192.168.0.0:

```
Router(config)# router eigrp 1  
Router(config-router)# network 172.16.0.0  
Router(config-router)# network 192.168.0.0
```

The following example configures EIGRP address-family autonomous system 4453 and establishes neighbors through network 172.16.0.0 and 192.168.0.0:

```
Router(config)# router eigrp virtual-name  
Router(config-router)# address-family ipv4 autonomous-system 4453  
Router(config-router-af)# network 172.16.0.0  
Router(config-router-af)# network 192.168.0.0
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
router eigrp	Configures the EIGRP address-family process.

next-hop-self

To enable Enhanced Interior Gateway Routing Protocol (EIGRP) to advertise routes with the local outbound interface address as the next hop, use the **next-hop-self** command in address-family interface configuration mode. To instruct an EIGRP router to use the received next hop rather than the local outbound interface address, use the **no** form of this command.

next-hop-self

no next-hop-self

Syntax Description

This command has no arguments or keywords.

Command Default

The next-hop-self state is enabled, causing EIGRP to use a local address in the next-hop field of its routing advertisements.

Command Modes

Address-family interface (config-router-af-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

The **next-hop-self** command is an interface-based command. EIGRP will, by default, set the next-hop value to the local outbound interface address for routes that it is advertising, even when advertising those routes back out the same interface where it learned them. To change this default, you must use the **no next-hop-self** command to instruct EIGRP to use the received next hop value when advertising these routes. Disabling next-hop-self is primarily useful in Dynamic Multipoint VPN (DMVPN) spoke-to-spoke topologies.

Examples

The following example changes the default next-hop value and instructs EIGRP to use the received next-hop address in its routing advertisements:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 33
Router(config-router-af)# af-interface ethernet0/0
Router(config-router-af-interface)# no next-hop-self
```

nsf (EIGRP)

To enable Cisco nonstop forwarding (NSF) operations for Enhanced Interior Gateway Protocol (EIGRP), use the **nsf** command in router configuration mode or address-family configuration mode. To disable EIGRP NSF and remove the EIGRP NSF configuration from the running-config file, use the **no** form of this command.

nsf

no nsf

Syntax Description This command has no arguments or keywords.

Command Default EIGRP NSF capability is enabled by default.

Command Modes Router configuration (config-router)
Address-family configuration (config-router-af)

Command History	Release	Modification
	12.2(18)S	This command was introduced.
	12.2(28)SB	This command was integrated into Cisco IOS Release 12.2(28)SB.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
	15.0(1)M	This command was modified. Address-family configuration mode was added.
	12.2(33)SRE	This command was modified. Address-family configuration mode was added.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines This command is used to enable or disable EIGRP NSF support on an NSF capable router. EIGRP NSF capability is enabled by default on distributed platforms that run a supporting version of Cisco IOS software.

Examples The **nsf** command is used to enable or disable the EIGRP NSF capability. The following example disables NSF capability:

```
Router# configure terminal
Router(config)# router eigrp 101
Router(config-router)# no nsf
```

The **nsf** command is used to enable or disable the EIGRP NSF capability. The following EIGRP named configuration example disables NSF capability:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 as 10
Router(config-router-af)# no nsf
```

Related Commands

Command	Description
debug eigrp nsf	Displays notifications and information about NSF events for an EIGRP routing process.
debug ip eigrp notifications	Displays information and notifications for an EIGRP routing process. This output includes NSF notifications and events.
show ip protocols	Displays the parameters and current state of the active routing protocol process. The status of EIGRP NSF configuration and support is displayed in the output.
timers nsf converge	Adjusts the maximum time that restarting router will wait for the EOT notification from an NSF-capable or NSF-aware peer.
timers nsf route-hold	Adjusts the maximum period of time that a supporting peer will hold known routes for an NSF-capable router during a restart operation or during a well-known failure condition.
timers nsf signal	Adjusts the maximum time for the initial restart period.

offset-list (EIGRP)

To add an offset to incoming and outgoing metrics to routes learned via Enhanced Interior Gateway Routing Protocol (EIGRP), use the **offset-list** command in router configuration mode or address family topology configuration mode. To remove an offset list, use the **no** form of this command.

offset-list { *access-list-number* | *access-list-name* } { **in** | **out** } *offset* [*interface-type* *interface-number*]

no offset-list { *access-list-number* | *access-list-name* } { **in** | **out** } *offset* [*interface-type* *interface-number*]

Syntax Description

<i>access-list-number</i> <i>access-list-name</i>	Standard access list number or name to be applied. Access list number 0 indicates all networks (networks, prefixes, or routes). If the <i>offset</i> value is 0, no action is taken.
in	Applies the access list to incoming metrics.
out	Applies the access list to outgoing metrics.
<i>offset</i>	Positive offset to be applied to metrics for networks matching the access list. If the offset is 0, no action is taken.
<i>interface-type</i>	(Optional) Interface type to which the offset list is applied.
<i>interface-number</i>	(Optional) Interface number to which the offset list is applied.

Command Default

No offset values are added to incoming or outgoing metrics to routes learned via EIGRP.

Command Modes

Router configuration (config-router)
Address family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
10.3	The <i>interface-type</i> and <i>interface-number</i> arguments were added.
11.2	The <i>access-list-name</i> argument was added.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. The address family configuration mode was added.
12.2(33)SRE	This command was modified. The address family configuration mode was added.

Release	Modification
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was modified. The address family configuration mode was added.

Usage Guidelines

The offset value is added to the routing metric. An offset list with an interface type and interface number is considered extended and takes precedence over an offset list that is not extended. Therefore, if an entry passes the extended offset list and the normal offset list, the offset of the extended offset list is added to the metric.

Examples

In the following example, the router applies an offset of 10 to the delay component of the router only to access list 21:

```
Router(config-router)# offset-list 21 out 10
```

In the following example, the router applies an offset of 10 to routes learned from Ethernet interface 0:

```
Router(config-router)# offset-list 21 in 10 ethernet 0
```

In the following example, the router applies an offset of 10 to routes learned from Ethernet interface 0 in an EIGRP named configuration:

```
Router(config)# router eigrp virtual-name  
Router(config-router)# address-family ipv4 autonomous-system 1  
Router(config-router-af)# topology base  
Router(config-router-af-topology)# offset-list 21 in 10 ethernet0
```

passive-interface (EIGRP)

To suppress Enhanced Interior Gateway Routing Protocols (EIGRP) hello packets and routing updates on interfaces while still including the interface addresses in the topology database, use the **passive-interface** command in router configuration mode, address-family configuration mode, or address-family interface configuration mode. To reenable outgoing hello packets and routing updates, use the **no** form of this command.

passive-interface [**default**] [*interface-type interface-number*]

no passive-interface [**default**] [*interface-type interface-number*]

Syntax Description

default	(Optional) Configures all interfaces as passive.
<i>interface-type</i>	(Optional) The interface type.
<i>interface-number</i>	(Optional) The interface number.

Command Default

Hello packets and routing updates are sent and received on the interface.

Command Modes

Router configuration (config-router)
 Address-family configuration (config-router-af)
 Address-family interface configuration (config-router-af-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Use the **passive-interface** (EIGRP) command to select interfaces that will not form EIGRP neighbor adjacencies yet include the interface addresses in the EIGRP topology database. When the **passive-interface** (EIGRP) command is configured, networks defined on the interface are added to the EIGRP topology database while routing updates and hello packets over the passive interfaces are suppressed.

The **default** keyword sets all interfaces to passive. Individual interfaces can be specified to override the default passive-interface state. The **default** keyword is useful when there are more passive interfaces than active interfaces.

Examples

The following EIGRP autonomous-system (AS) configuration example sets all EIGRP interfaces to passive and then sets Ethernet 0/0 to a nonpassive state:

```
Router(config)# router eigrp 109
Router(config-router)# passive-interface default
Router(config-router)# no passive-interface ethernet0/0
```

The following EIGRP AS address-family configuration example sets all EIGRP interfaces in VRF RED to passive and then sets Ethernet 0/0 to a nonpassive state:

```
Router(config)# router eigrp 109
Router(config-router)# address-family ipv4 vrf RED
Router(config-router-af)# passive-interface default
Router(config-router-af)# no passive-interface ethernet0/0
```

The following EIGRP named address-family interface configuration example sets all interfaces in an address family to passive and then sets Ethernet 0/0 to a nonpassive state:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# af-interface default
Router(config-router-af-interface)# passive-interface
Router(config-router-af-interface)# exit
Router(config-router-af)# af-interface ethernet0/0
Router(config-router-af-interface)# no passive-interface
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
network (EIGRP)	Specifies the network for an EIGRP routing process.
router eigrp	Configures the EIGRP address-family process.

redistribute eigrp

To redistribute IPv4 routes from Enhanced Interior Gateway Routing Protocol (EIGRP), use the **redistribute eigrp** command in router configuration mode. To disable the configuration, use the **no** form of this command.

redistribute eigrp *system-number* [**metric** *bandwidth-metric delay-metric reliability-metric effective-bandwidth-metric mtu-bytes*] [**route-map** *pointer-name*]

no redistribute eigrp *system-number* [**metric** [*bandwidth-metric delay-metric reliability-metric effective-bandwidth-metric mtu-bytes*] | **route-map** *pointer-name*]

Syntax Description

<i>system-number</i>	Autonomous system number. The range is from 1 to 65535.
metric	(Optional) Specifies the metric for redistributed routes.
<i>bandwidth-metric</i>	(Optional) Maximum bandwidth of the route, in kilobits per second (kb/s). The range is from 1 to 4294967295.
<i>delay-metric</i>	(Optional) EIGRP route delay metric, in microseconds. The range is from 1 to 4294967295.
<i>reliability-metric</i>	(Optional) EIGRP reliability metric. The range is from 0 to 255. <ul style="list-style-type: none"> An EIGRP metric of 255 signifies 100 percent reliability.
<i>effective-bandwidth-metric</i>	(Optional) Effective bandwidth of the route. The range is from 1 to 255. <ul style="list-style-type: none"> Effective bandwidth of 255 denotes 100 percent load.
<i>mtu-bytes</i>	(Optional) The smallest allowed value for the maximum transmission unit (MTU), in bytes. The range is from 1 to 65535.
route-map	(Optional) Specifies the route map reference.
<i>pointer-name</i>	(Optional) Pointer to route-map entries.

Command Default

Route redistribution is disabled.

Command Modes

Router configuration (config-router)

Command History

Release	Modification
12.2(8)T	This command was introduced in a release earlier than Cisco IOS Release 12.2(8)T.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2(33)SXI	This command was integrated into Cisco IOS Release 12.2(33)SXI.
Cisco IOS XE Release 2.1	This command was implemented on the Cisco ASR 1000 Series Aggregation Services Routers.

Usage Guidelines

Use the **redistribute eigrp** command to redistribute the routes learned through the EIGRP routing instances to other routing protocols. Forward redistribution of the EIGRP routes is allowed before creating the EIGRP routing instance. The EIGRP redistribution takes place as soon as the routing instance is created.

The metric value specified in the **redistribute** command supersedes the metric value specified using the **default-metric** command.



Note

In Cisco IOS Release 12.0(33)S, the **redistribution eigrp** command is not allowed if the EIGRP router is not defined. The command terminates by displaying the following error message:

```
%Configure eigrp router mode before redistributing
```

Examples

The following example shows how to configure a router to redistribute EIGRP routes into an EIGRP process:

```
Router# configure terminal
Router(config)# router eigrp virtual-name
Router(config-router)# redistribute eigrp 6473 metric 1 2 3 4 5
```

The following example shows the behavior of the **redistribution eigrp** command when the EIGRP router is not defined in Cisco IOS Release 12.0(33)S:

```
Router# configure terminal
Router(config)# router ospf 100 vrf vrf1
Router(config-router)# redistribute eigrp 99
%Configure eigrp router mode before redistributing
```

Related Commands


Command	Description
default-metric	Sets metrics for EIGRP.

redistribute maximum-prefix (EIGRP)

To limit the number of prefixes redistributed into an Enhanced Interior Gateway Routing Protocol (EIGRP) process, use the **redistribute maximum-prefix** command in address family configuration mode or address-family topology configuration mode. To disable this function, use the **no** form of this command.

redistribute maximum-prefix *maximum* [*threshold*] [[**dampened**] [**reset-time** *minutes*] [**restart** *minutes*] [**restart-count** *number*] | [**warning-only**]]

no redistribute maximum-prefix

Syntax Description		
<i>maximum</i>	Maximum number of prefixes that are redistributed into EIGRP under an address family. The range for this argument is a number from 1 to 4294967295.	
	Note	The number of prefixes that can be configured is limited only by the available system resources on the router.
<i>threshold</i>	(Optional) The prefix percentage number. Valid values are 1 to 100. The default is 75. This value causes the router to generate syslog warning messages when the specified percentage of the maximum-prefix limit has been exceeded.	
dampened	(Optional) Configures a decay penalty to be applied to the restart-time period each time the maximum-prefix limit is exceeded. The half-life for the decay penalty is 150 percent of the default or user-defined restart-time value in minutes. This keyword is disabled by default.	
reset-time <i>minutes</i>	(Optional) Configures the router to reset the restart count to 0 after the default or configured reset-time period has expired. The value for the <i>minutes</i> argument is from 1 to 65535 minutes. The default reset-time period is 15 minutes.	
restart <i>minutes</i>	(Optional) Configures a time period in which the router will not form adjacencies or accept redistributed routes from the Routing Information Base (RIB) after the maximum-prefix limit has been exceeded. The value for the <i>minutes</i> argument is from 1 to 65535 minutes. The default restart-time period is 5 minutes.	
restart-count <i>number</i>	(Optional) Configures the number of times a peering session can be automatically be reestablished after the peering session has been torn down or after a redistribute route has been cleared and relearned because the maximum-prefix limit has been exceeded. The default restart-count limit is 3.	
		
	Caution	Once the restart count threshold has been crossed, you will need to enter the clear ip route * or clear ip eigrp neighbor command to reestablish normal peering and/or redistribution.
warning-only	(Optional) Configures the router to generate syslog messages only when the maximum-prefix limit is reached, instead of suspending redistribution. This keyword is disabled by default.	

Command Default

The number of prefixes redistributed into an EIGRP process is not limited.

Command Modes

Address family configuration (config-router-af)
Address family topology configuration (config-router-af-topology)

Command History

Release	Modification
12.0(29)S	This command was introduced.
12.3(14)T	This command was integrated into Cisco IOS Release 12.3(14)T.
15.0(1)M	This command was modified. Address family topology configuration mode was added.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
Cisco IOS XE Release 2.6	This command was integrated into Cisco IOS XE Release 2.6.

Usage Guidelines

The **redistribute maximum-prefix** command is used to configure limit prefixes learned through redistribution. When the maximum-prefix limit is exceeded, all routes learned from the RIB will be discarded and redistribution will be suspended for the default or user-defined time period. The maximum-prefix limit that can be configured for redistributed prefixes is limited only by the available system resources on the router.

Inherited Timer Values

Default or user-defined restart, restart-count, and reset-time values for the process-level configuration of this feature, configured with the **maximum-prefix** command, are inherited by the **redistribute maximum-prefix (EIGRP)** and **neighbor maximum-prefix (EIGRP)** command configurations by default. If a single peer is configured with the **neighbor maximum-prefix (EIGRP)** command, a process-level configuration or a configuration that is applied to all neighbors will be inherited.

Examples

The following example, starting in global configuration mode, configures the maximum prefix limit for routes learned through redistribution. The maximum limit is set to 5000 prefixes and the warning threshold is set to 95 percent. When the number of prefixes learned through redistribution reaches 4750 (95 percent of 5000), warning messages will be displayed in the console. Because the **warning-only** keyword was configured, the topology and routing tables will not be cleared and route redistribution will not be placed in a penalty state.

```
Router(config)# router eigrp 100
Router(config-router)# address-family ipv4 vrf RED
Router(config-router-af)# redistribute maximum-prefix 5000 95 warning-only
Router(config-router-af)# end
```

The following example shows this configuration in address-family topology configuration mode:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 vrf RED autonomous-system 4453
Router(config-router-af)# network 172.16.0.0
Router(config-router-af)# topology base
Router(config-router-af-topology)# redistribute maximum-prefix 5000 95 warning-only
Router(config-router-af-topology)# exit-af-topology
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
clear ip eigrp neighbors	Deletes entries from the EIGRP neighbor table.
clear ip eigrp vrf neighbor	Deletes neighbor entries from the VRF table.
clear ip route	Deletes routes from the IP routing table.
network (EIGRP)	Specifies the network for an EIGRP routing process.
redistribute maximum-prefix (EIGRP)	Limits the number of prefixes redistributed into an EIGRP process.
topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters address-family topology configuration mode.

router eigrp

To configure the Enhanced Interior Gateway Routing Protocol (EIGRP) routing process, use the **router eigrp** command in global configuration mode. To remove an EIGRP routing process, use the **no** form of this command.

router eigrp { *autonomous-system-number* | *virtual-instance-name* }

no router eigrp { *autonomous-system-number* | *virtual-instance-name* }

Syntax Description

<i>autonomous-system-number</i>	Autonomous system number that identifies the services to the other EIGRP address-family routers. It is also used to tag routing information. Valid range is 1 to 65535.
<i>virtual-instance-name</i>	EIGRP virtual instance name. This name must be unique among all address-family router processes on a single router, but need not be unique among routers.

Command Default

No EIGRP processes are configured.

Command Modes

Global configuration (config)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2(31)SB2	This command was integrated into Cisco IOS Release 12.2(31)SB2.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. The <i>virtual-instance-name</i> argument was added.
12.2(33)SRE	This command was modified. The <i>virtual-instance-name</i> argument was added.
12.2(33)XNE	This command was modified. The <i>virtual-instance-name</i> argument was added.
Cisco IOS XE Release 2.5	This command was modified. The <i>virtual-instance-name</i> argument was added.

Usage Guidelines

Configuring the **router eigrp** command with the *autonomous-system-number* argument creates an EIGRP configuration referred to as autonomous system (AS) configuration. An EIGRP AS configuration creates an EIGRP routing instance that can be used for tagging routing information.

Configuring the **router eigrp** command with the *virtual-instance-name* argument creates an EIGRP configuration referred to as EIGRP named configuration. An EIGRP named configuration does not create an EIGRP routing instance by itself. An EIGRP named configuration is a base configuration that is required to define address-family configurations under it that are used for routing.

Examples

The following example configures EIGRP process 109:

```
Router(config)# router eigrp 109
```

The following example configures an EIGRP address-family routing process and assigns it the name “virtual-name”:

```
Router(config)# router eigrp virtual-name
```

Related Commands

Command	Description
network (EIGRP)	Specifies a list of networks for the EIGRP process.

set metric (EIGRP)

To set the metric value for Enhanced Interior Gateway Routing Protocol (EIGRP) in a route map, use the **set metric** route-map configuration command. To return to the default metric value, use the **no** form of this command.

set metric *bandwidth delay reliability loading mtu*

no set metric *bandwidth delay reliability loading mtu*

Syntax Description

<i>bandwidth</i>	Metric value or EIGRP bandwidth of the route in kbps. The range is from 0 to 4294967295.
<i>delay</i>	Route delay (in tens of microseconds). It can be in the range from 0 to 4294967295.
<i>reliability</i>	Likelihood of successful packet transmission expressed as a number from 0 to 255. The value 255 means 100 percent reliability; 0 means no reliability.
<i>loading</i>	Effective bandwidth of the route expressed as a number from 0 to 255 (255 is 100 percent loading).
<i>mtu</i>	Minimum maximum transmission unit (MTU) size of the route, in bytes. It can be in the range from 0 to 4294967295.

Defaults

No metric will be set in the route map.

Command Modes

Route-map configuration (config-route-map)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
Cisco IOS XE Release 2.1	This command was integrated into Cisco IOS XE Release 2.1.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.

Usage Guidelines

We recommend you consult your Cisco technical support representative before changing the default value.

Use the **route-map** global configuration command, and the **match** and **set** route-map configuration commands, to define the conditions for redistributing routes from one routing protocol into another. Each **route-map** command has a list of **match** and **set** commands associated with it. The **match** commands specify the *match criteria*—the conditions under which redistribution is allowed for the current

route-map command. The **set** commands specify the *set actions*—the particular redistribution actions to perform if the criteria enforced by the **match** commands are met. The **no route-map** command deletes the route map.

The **set** route-map configuration commands specify the redistribution *set actions* to be performed when all of the match criteria for a router are met. When all match criteria are met, all set actions are performed.

Examples

The following example sets the bandwidth to 10,000, the delay to 10, the reliability to 255, the loading to 1, and the MTU to 1500:

```
Router(config-route-map)# set metric 10000 10 255 1 1500
```

show eigrp address-family accounting

To display prefix accounting information for Enhanced Interior Gateway Routing Protocol (EIGRP) processes, use the **show eigrp address-family accounting** command in user EXEC or privileged EXEC mode.

show eigrp address-family { ipv4 | ipv6 } [vrf vrf-name] [autonomous-system-number] [multicast] accounting

Syntax Description	ipv4	Selects the IPv4 protocol address family.
	ipv6	Selects the IPv6 protocol address family.
	vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF. This keyword/argument pair is available only for IPv4 configurations.
	<i>autonomous-system-number</i>	(Optional) Autonomous system number.
	multicast	(Optional) Displays information about multicast instances.

Command Modes	User EXEC (>) Privileged EXEC (#)
----------------------	--------------------------------------

Command Default	Prefix accounting information for all EIGRP processes is displayed.
------------------------	---------------------------------------------------------------------

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines	This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.
-------------------------	-----------------------------------------------------------------------------------------------------------------------------------

This command displays the same information as the **show ip eigrp accounting** command. Cisco recommends using the **show eigrp address-family accounting** command.

Examples	The following example shows how to display EIGRP prefix accounting information for autonomous-system 22:
-----------------	----------------------------------------------------------------------------------------------------------

```
Router# show eigrp address-family ipv4 22 accounting
```

```
EIGRP-IPv4 VR(saf) Accounting for AS(22)/ID(10.0.0.1)
Total Prefix Count: 3 States: A-Adjacency, P-Pending, D-Down
State Address/Source Interface Prefix Restart Restart/
```

show eigrp address-family accounting

```

A      10.0.0.2      Et0/0      Count      Count      Reset(s)
P      10.0.2.4      Se2/0      0           2           114
D      10.0.1.3      Et0/0      0           3           0

```

Table 3 describes the significant fields shown in the display.

Table 3 *show eigrp address-family accounting Field Descriptions*

Field	Description
IP-EIGRP accounting for AS...	Identifies the EIGRP instance, AS number, router ID, and table ID.
Total Prefix Count	Number of distinct prefixes that are present in this autonomous system.
State	State of the given neighbor: Adjacency, Pending, or Down.
Address/Source	IP address of the neighbor.
Interface	Interface on which the neighbor is connected.
Prefix Count	Number of prefixes that are advertised by this neighbor.
Restart Count	Number of times this neighbor has been restarted due to exceeding prefix limits.
Restart/Reset(s)	Time remaining until the neighbor will be restarted (if in Pending state) or until the restart count will be cleared (if in Adjacency state.)

Related Commands

Command	Description
show eigrp address-family events	Displays information about EIGRP events.
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.
show eigrp address-family neighbors	Displays the neighbors discovered by EIGRP.
show eigrp address-family sia-event	Displays information about EIGRP SIA events.
show eigrp address-family sia-statistics	Displays information about EIGRP SIA statistics.
show eigrp address-family timers	Displays information about EIGRP timers and expiration times.
show eigrp address-family topology	Displays entries in the EIGRP topology table.
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.

show eigrp address-family events

To display information about Enhanced Interior Gateway Routing Protocol (EIGRP) address-family events, use the **show eigrp address-family events** command in user EXEC or privileged EXEC mode.

```
show eigrp address-family { ipv4 | ipv6 } [vrf vrf-name] [autonomous-system-number] [multicast]
events [starting-event-number ending-event-number] [errmsg [starting-event-number
ending-event-number]] [sia [starting-event-number ending-event-number]] [type]
```

Syntax Description

ipv4	Selects the IPv4 protocol address family.
ipv6	Selects the IPv6 protocol address family.
vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
<i>autonomous-system-number</i>	(Optional) Autonomous system number.
multicast	(Optional) Displays information about multicast instances.
<i>starting-event-number</i>	(Optional) Number of first event to display.
<i>ending-event-number</i>	(Optional) Number of last event to display.
errmsg	(Optional) Displays error message events.
sia	(Optional) Displays Stuck in Active (SIA) events.
type	(Optional) Displays the types of events being logged.

Command Modes

User EXEC (>)
Privileged EXEC (#)

Command Default

All EIGRP address-family events are displayed.

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

The event log is used by Cisco technical support to display a history of EIGRP internal events that are specific to a particular address family.

To display information about EIGRP service-family events, use the **show eigrp service-family events** command.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show ip eigrp events** command. Cisco recommends using the **show eigrp address-family events** command.

Examples

The following example shows how to display EIGRP address-family events for autonomous-system 3:

```
Router# show eigrp address-family ipv4 3 events
```

```
Event information for AS 3:
1 15:37:47.015 Change queue emptied, entries: 1
2 15:37:47.015 Metric set: 10.0.0.0/24 307200
3 15:37:47.015 Update reason, delay: new if 4294967295
4 15:37:47.015 Update sent, RD: 10.0.0.0/24 4294967295
5 15:37:47.015 Update reason, delay: metric chg 4294967295
6 15:37:47.015 Update sent, RD: 10.0.0.0/24 4294967295
7 15:37:47.015 Route installed: 10.0.0.0/24 1.1.1.2
8 15:37:47.015 Route installing: 10.0.0.0/24 10.0.1.2
```

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.
show eigrp address-family neighbors	Displays the neighbors discovered by EIGRP.
show eigrp address-family sia-event	Displays information about EIGRP SIA events.
show eigrp address-family sia-statistics	Displays information about EIGRP SIA statistics.
show eigrp address-family timers	Displays information about EIGRP timers and expiration times.
show eigrp address-family topology	Displays entries in the EIGRP topology table.
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.
show eigrp service-family events	Displays information about EIGRP service-family events.

show eigrp address-family interfaces

To display information about interfaces that are configured for Enhanced Interior Gateway Routing Protocol (EIGRP), use the **show eigrp address-family interfaces** command in user EXEC or privileged EXEC mode.

show eigrp address-family {ipv4 | ipv6} [vrf vrf-name] [autonomous-system-number] [multicast] interfaces [detail] [interface-type interface-number]

Syntax Description	
ipv4	Selects the IPv4 protocol address family.
ipv6	Selects the IPv6 protocol address family.
vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
<i>autonomous-system-number</i>	(Optional) Autonomous system number.
multicast	(Optional) Displays information about multicast instances.
detail	(Optional) Displays detailed information about EIGRP interfaces.
<i>interface-type</i> <i>interface-number</i>	(Optional) Interface type and number to display. If unspecified, all enabled interfaces are displayed.

Command Default All enabled EIGRP interfaces are displayed.

Command Modes User EXEC (>)
Privileged EXEC (#)

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines Use the **show eigrp address-family interfaces** command to determine on which interfaces EIGRP is active and to learn EIGRP information about those interfaces.

If an interface is specified, only information about that interface is displayed. Otherwise, information about all interfaces on which EIGRP is running is displayed.

If an autonomous system is specified, only the routing process for the specified autonomous system is displayed. Otherwise, all EIGRP processes are displayed.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show ip eigrp interfaces** command. Cisco recommends using the **show eigrp address-family interfaces** command.

Examples

The following example shows how to display information about EIGRP interfaces for autonomous-system 4453:

```
Router# show eigrp address-family ipv4 4453 interfaces
```

```
EIGRP-IPv4 VR(Virtual-name) Address-family Neighbors for AS(4453)
      Xmit Queue   Mean   Pacing Time   Multicast   Pending
Interface  Peers  Un/Reliable  SRTT   Un/Reliable   Flow Timer  Services
Se0         1      0/0         28     0/15         127         0
Se1         1      0/0         44     0/15         211         0
```

The following example shows how to display detailed information about Loopback interface 1 in autonomous-system 2:

```
Router# show eigrp address-family ipv4 2 interfaces detail Loopback1
```

```
EIGRP-IPv4 VR(saf2) Address-family Neighbors for AS(2)
      Xmit Queue   Mean   Pacing Time   Multicast   Pending
Interface  Peers  Un/Reliable  SRTT   Un/Reliable   Flow Timer  Services
Lo1         166      0/0         48     0/1          258         0
  Hello-interval is 5, Hold-time is 15
  Split-horizon is enabled
  Next xmit serial <none>
  Un/reliable mcasts: 0/0 Un/reliable ucasts: 10148/67233
  Mcast exceptions: 0 CR packets: 0 ACKs suppressed: 8719
  Retransmissions sent: 2696 Out-of-sequence rcvd: 594
  Interface has all stub peers
  Topology-ids on interface - 0
  Authentication mode is not set
```

Table 4 describes the significant fields shown in the display.

Table 4 *show eigrp address-family interfaces Field Descriptions*

Field	Description
Interface	Interface over which EIGRP is configured.
Peers	Number of EIGRP neighbors connected on this interface.
Xmit Queue Un/Reliable	Number of packets remaining in the Unreliable and Reliable transmit queues.
Mean SRTT	Mean smooth round-trip time interval, in milliseconds.
Pacing Time Un/Reliable	Pacing time used to determine when reliable and unreliable EIGRP packets should be sent out of the interface.
Multicast Flow Timer	Maximum number of seconds the router sends multicast EIGRP packets.
Pending Services	Number of services in the packets in the transmit queue waiting to be sent.
CR packets	Packets marked for conditional Receive.

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.
show eigrp address-family events	Displays information about EIGRP events.
show eigrp address-family neighbors	Displays the neighbors discovered by EIGRP.
show eigrp address-family sia-event	Displays information about EIGRP SIA events.
show eigrp address-family sia-statistics	Displays information about EIGRP SIA statistics.
show eigrp address-family timers	Displays information about EIGRP timers and expiration times.
show eigrp address-family topology	Displays entries in the EIGRP topology table.
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.

show eigrp address-family neighbors

To display the neighbors that are discovered by Enhanced Interior Gateway Routing Protocol (EIGRP), use the **show eigrp address-family neighbors** command in user EXEC or privileged EXEC mode.

show eigrp address-family { **ipv4** | **ipv6** } [**vrf** *vrf-name*] [*autonomous-system-number*] [**multicast**] **neighbors** [**static**] [**detail**] [*interface-type interface-number*]

Syntax Description

ipv4	Selects the IPv4 protocol address family.
ipv6	Selects the IPv6 protocol address family.
vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
<i>autonomous-system-number</i>	(Optional) Autonomous system number.
multicast	(Optional) Displays information about multicast instances.
static	(Optional) Displays static neighbors.
detail	(Optional) Displays detailed EIGRP neighbor information.
<i>interface-type interface-number</i>	(Optional) Interface type and number to display. If unspecified, all enabled interfaces are displayed.

Command Default

Information about all neighbors discovered by EIGRP is displayed.

Command Modes

User EXEC (>)
Privileged EXEC (#)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Use the **show eigrp address-family neighbors** command to determine when neighbors become active and inactive. It is also useful for debugging certain types of transport problems.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show ip eigrp neighbors** command. Cisco recommends using the **show eigrp address-family neighbors** command.

Examples

The following example shows how to display neighbors that are discovered by EIGRP:

```
Router# show eigrp address-family ipv4 4453 neighbors

EIGRP-IPv4 VR(Virtual-name) Address-family Neighbors for AS(4453)
Address                Interface    Hold Uptime    SRTT  RTO    Q      Seq
                        (sec)      (ms)    (ms)  (ms)   Cnt    Num
172.16.81.28           Ethernet1    13    0:00:41    0      11     4     20
172.16.80.28           Ethernet0    14    0:02:01    0      10    12     24
172.16.80.31           Ethernet0    12    0:02:02    0       4     5     20
```

Table 5 describes the significant fields shown in the display.

The following example shows how to display detailed information about neighbors that are discovered by EIGRP, including whether a neighbor has been gracefully restarted:

```
Router# show eigrp address-family ipv4 neighbors detail

EIGRP-IPv4 VR(test) Address-Family Neighbors for AS(3)
H Address Interface Hold Uptime SRTT RTO Q Seq
      (sec)      (ms)  Cnt  Num
172.16.81.28 Et1/1 11 01:11:08 10 200 0 8
Time since Restart 00:00:05
Version 5.0/3.0, Retrans: 2, Retries: 0, Prefixes: 2
Topology-ids from peer - 0
```

Table 5 *show eigrp address-family neighbors Field Descriptions*

Field	Description
AS(4453)	Autonomous system number specified in the configuration command, in this example 4453.
Address	IP address of the peer.
Interface	Interface on which the router is receiving hello packets from the peer.
Hold time	Length of time, in seconds, that the router will wait to hear from the peer before declaring it down. If the peer is using the default hold time, this number will be less than 15. If the peer configures a nondefault hold time, it will be reflected here.
Uptime	Elapsed time since the local router first heard from this neighbor.
Q Cnt	Number of packets (update, query, and reply) that the software is waiting to send.
Seq Num	Sequence number of the last update, query, or reply packet that was received from this neighbor.
SRTT	Smooth round-trip time. This is the number of milliseconds that it takes for an EIGRP packet to be sent to this neighbor and for the local router to receive an acknowledgment of that packet.
RTO	Retransmission timeout, in milliseconds. Indicates the amount of time EIGRP waits before retransmitting a packet from the retransmission queue to a neighbor.
Time since Restart	Time elapsed since a neighbor has been gracefully restarted.

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.
show eigrp address-family events	Displays information about EIGRP events.
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.
show eigrp address-family sia-event	Displays information about EIGRP SIA events.
show eigrp address-family sia-statistics	Displays information about EIGRP SIA statistics.
show eigrp address-family timers	Displays information about EIGRP timers and expiration times.
show eigrp address-family topology	Displays entries in the EIGRP topology table.
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.

show eigrp address-family timers

To display information about Enhanced Interior Gateway Routing Protocol (EIGRP) timers and expiration times, use the **show eigrp address-family timers** command in user EXEC or privileged EXEC mode.

show eigrp address-family {ipv4 | ipv6} [vrf vrf-name] [autonomous-system-number] [multicast] timers

Syntax Description	ipv4	Selects the IPv4 protocol address family.
	ipv6	Selects the IPv6 protocol address family.
	vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
	<i>autonomous-system-number</i>	(Optional) Autonomous system number.
	multicast	(Optional) Displays information about multicast instances.

Command Default	Information about all EIGRP timers is displayed.
-----------------	--------------------------------------------------

Command Modes	User EXEC (>) Privileged EXEC (#)
---------------	--------------------------------------

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines	This command is useful for debugging and troubleshooting by Cisco technical support, but it is not intended for normal EIGRP administration tasks. This command should not be used without guidance from Cisco technical support.
------------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show ip eigrp timers** command. Cisco recommends using the **show eigrp address-family timers** command.

Examples	The following example shows how to display information about EIGRP timers:
----------	----------------------------------------------------------------------------

```
Router# show eigrp address-family ipv4 4453 timers
```

```
EIGRP-IPv4 VR(Virtual-name) Address-family Timers for AS(4453)
```

■ show eigrp address-family timers

```

Hello Process
Expiration Type
| 1.022 (parent)
| 1.022 Hello (Et0/0)

Update Process
Expiration Type
| 14.984 (parent)
| 14.984 (parent)
| 14.984 Peer holding

SIA Process
Expiration Type for Topo(base)
| 0.000 (parent)

```

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.
show eigrp address-family events	Displays information about EIGRP events.
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.
show eigrp address-family neighbors	Displays the neighbors discovered by EIGRP.
show eigrp address-family sia-event	Displays information about EIGRP SIA events.
show eigrp address-family sia-statistics	Displays information about EIGRP SIA statistics.
show eigrp address-family topology	Displays entries in the EIGRP topology table.
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.

show eigrp address-family topology

To display entries in the Enhanced Interior Gateway Routing Protocol (EIGRP) topology table, use the **show eigrp address-family topology** command in user EXEC or privileged EXEC mode.

```
show eigrp address-family { ipv4 | ipv6 } [vrf vrf-name] [autonomous-system-number] [multicast]
topology [topology-name] [ip-address] [active] [all-links] [detail-links] [pending]
[summary] [zero-successors] [route-type { connected | external | internal | local |
redistributed | summary | vpn }]
```

Syntax Description

ipv4	Selects the IPv4 protocol address family.
ipv6	Selects the IPv6 protocol address family.
vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
<i>autonomous-system-number</i>	(Optional) Specifies the autonomous system number.
multicast	(Optional) Displays information about multicast instances.
<i>topology-name</i>	(Optional) Named entry in the EIGRP topology table.
<i>ip-address</i>	(Optional) Network or network and mask. When specified, a detailed description of the entry is provided.
active	(Optional) Displays only active entries in the EIGRP topology table.
all-links	(Optional) Displays all entries in the EIGRP topology table (including non-feasible-successor sources).
detail-links	(Optional) Displays detailed information about all entries in the topology table.
pending	(Optional) Displays all entries in the EIGRP topology table that are waiting for an update from a neighbor or are waiting to reply to a neighbor.
summary	(Optional) Displays summary information about the EIGRP topology table.
zero-successors	(Optional) Displays available routes in the EIGRP topology table that have zero successors.
route-type	(Optional) Displays information about services of the specified route type.
connected	(Optional) Displays information about all connected routes.
external	(Optional) Displays information about all external routes.
internal	(Optional) Displays information about all internal routes.
local	(Optional) Displays information about all locally originated routes.
redistributed	(Optional) Displays information about all redistributed routes.
summary	(Optional) Displays information about all summary routes.
vpn	(Optional) Displays information about all VPN sourced routes. Applies to IPv4 only.

Command Default

If this command is used without any keywords or arguments, only routes that are feasible successors are displayed.

Command Modes

User EXEC (>)
Privileged EXEC (#)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show ip eigrp topology** command.
Cisco recommends using the **show eigrp address-family topology** command.

Examples

The following example shows how to display entries in the EIGRP topology table:

```
Router# show eigrp address-family ipv4 4453 topology

EIGRP-IPv4 VR(Virtual-name) Topology Table for AS(4453)/ID(10.0.0.1)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
       r - Reply status, s - sia Status
P 10.17.17.0/24, 1 successors, FD is 409600
    via 10.10.10.2 (409600/128256), Ethernet3/0
P 172.16.19.0/24, 1 successors, FD is 409600
    via 10.10.10.2 (409600/128256), Ethernet3/0
P 192.168.10.0/24, 1 successors, FD is 281600
    via Connected, Ethernet3/0
P 10.10.10.0/24, 1 successors, FD is 281600
    via Redistributed (281600/0)
```

The following example shows how to display EIGRP metrics for specified internal services and external services:

```
Router# show eigrp address-family ipv4 4453 topology 10.10.10.0/24

EIGRP-IPv4 VR(virtual-name) Topology Entry for AS(4453)/ID(10.0.0.1) for 10.10.10.0/24
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 128256
Descriptor Blocks:
0.0.0.0 (Null0), from Connected, Send flag is 0x0
Composite metric is (128256/0), service is Internal
Vector metric:
  Minimum bandwidth is 10000000 Kbit
  Total delay is 5000 microseconds
  Reliability is 255/255
  Load is 1/255
  Minimum MTU is 1514
  Hop count is 0
  Originating router is 10.0.0.1
```

Table 6 describes the significant fields shown in the display.

Table 6 *show eigrp address-family topology Field Descriptions*

Field	Description
Codes	State of this topology table entry. Passive and Active refer to the EIGRP state with respect to this destination; Update, Query, and Reply refer to the type of packet that is being sent.
P—Passive	No EIGRP computations are being performed for this destination.
A—Active	EIGRP computations are being performed for this destination.
U—Update	An update packet was sent to this destination.
Q—Query	A query packet was sent to this destination.
R—Reply	A reply packet was sent to this destination.
r—reply Status	Flag that is set after the software has sent a query and is waiting for a reply.
s—sia Status	Flag that is set if a route is in a stuck in active state.
successors	Number of successors. This number corresponds to the number of next hops in the IP routing table. If “successors” is capitalized, then the route or next hop is in a transition state.
FD	Feasible distance. The feasible distance is the best metric to reach the destination or the best metric that was known when the route went active. This value is used in the feasibility condition check. If the reported distance of the router (the metric after the slash) is less than the feasible distance, the feasibility condition is met and that path is a feasible successor. Once the software determines it has a feasible successor, it need not send a query for that destination.
replies	(Not shown in the output.) Number of replies that are still outstanding (have not been received) with respect to this destination. This information appears only when the destination is in the Active state.
state	(Not shown in the output) Exact EIGRP state that this destination is in. It can be the number 0, 1, 2, or 3. This information appears only when the destination is in the Active state.
via	IP address of the peer that told the software about this destination. The first N of these entries, where N is the number of successors, is the current successors. The remaining entries on the list are feasible successors.
(409600/128256)	The first number is the EIGRP metric that represents the cost to the destination. The second number is the EIGRP metric that this peer advertised.
Ethernet3/0	Interface from which this information was learned.

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.
show eigrp address-family events	Displays information about EIGRP events.
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.
show eigrp address-family neighbors	Displays the neighbors discovered by EIGRP.
show eigrp address-family sia-event	Displays information about EIGRP SIA events.
show eigrp address-family sia-statistics	Displays information about EIGRP SIA statistics.
show eigrp address-family timers	Displays information about EIGRP timers and expiration times.
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.

show eigrp address-family traffic

To display the number of Enhanced Interior Gateway Routing Protocol (EIGRP) packets that are sent and received, use the **show eigrp address-family traffic** command in user EXEC or privileged EXEC mode.

show eigrp address-family {ipv4 | ipv6} [vrf vrf-name] [autonomous-system-number] [multicast] traffic

Syntax Description	ipv4	Selects the IPv4 protocol address family.
	ipv6	Selects the IPv6 protocol address family.
	vrf vrf-name	(Optional) Displays information about the specified VRF.
	autonomous-system-number	(Optional) Autonomous system number.
	multicast	(Optional) Displays information about multicast instances.

Command Default The number of all EIGRP packets sent and received is displayed.

Command Modes User EXEC (>)
Privileged EXEC (#)

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show ip eigrp traffic** command. Cisco recommends using the **show eigrp address-family traffic** command.

Examples The following example shows how to display the number of EIGRP packets sent and received for autonomous system number 4453:

```
Router# show eigrp address-family ipv4 4453 traffic

EIGRP-IPv4 VR(virtual-name) Address-family Traffic Statistics for AS(4453)
  Hellos sent/received: 122/122
  Updates sent/received: 3/1
  Queries sent/received: 0/0
```

show eigrp address-family traffic

```

Replies sent/received: 0/0
Acks sent/received: 0/3
SIA-Queries sent/received: 0/0
SIA-Replies sent/received: 0/0
Hello Process ID: 128
PDM Process ID: 191
Socket Queue: 0/2000/1/0 (current/max/highest/drops)
Input Queue: 0/2000/1/0 (current/max/highest/drops)

```

Table 7 describes the significant fields shown in the display.

Table 7 *show eigrp address-family traffic Field Descriptions*

Field	Description
Hellos sent/received	Number of hello packets sent and received.
Updates sent/received	Number of update packets sent and received.
Queries sent/received	Number of query packets sent and received.
Replies sent/received	Number of reply packets sent and received.
Acks sent/received	Number of acknowledgement packets sent and received.
SIA-Queries sent/received	Number of stuck in active query packets sent and received.
SIA-Replies sent/received	Number of stuck in active reply packets sent and received.
Hello Process ID	Cisco IOS hello process identifier.
PDM Process ID	Protocol-dependent module IOS process identifier.
Socket Queue	IP to EIGRP Hello Process socket queue counters.
Input Queue	EIGRP Hello Process to EIGRP PDM socket queue counters.

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.
show eigrp address-family events	Displays information about EIGRP events.
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.
show eigrp address-family neighbors	Displays the neighbors discovered by EIGRP.
show eigrp address-family sia-event	Displays information about EIGRP SIA events.
show eigrp address-family sia-statistics	Displays information about EIGRP SIA statistics.
show eigrp address-family timers	Displays information about EIGRP timers and expiration times.
show eigrp address-family topology	Displays entries in the EIGRP topology table.

show eigrp plugins

To display general information including the versions of the Enhanced Interior Gateway Routing Protocol (EIGRP) protocol features that are currently running, use the **show eigrp plugins** command in user EXEC or privileged EXEC mode.

show eigrp [*vrf-name*] [*as-number*] **plugins** [*plugin-name*] [**detailed**]

Syntax Description	vrf-name	(Obsolete) (Optional) Specifies a particular VPN routing and forwarding (VRF) instance name.
	Note	This keyword and argument are obsolete and configuring them has no effect on the output displayed.
	as-number	(Obsolete) (Optional) Autonomous system number.
	Note	This argument is obsolete and configuring it has no effect on the output displayed.
	plugin-name	(Optional) Name of an EIGRP plugin to display.
	detailed	(Optional) Displays detailed information about EIGRP features.

Command Modes	User EXEC (>)
	Privileged EXEC (#)

Command History	Release	Modification
	12.4(15)T	This command was introduced.
	12.2(33)SXI	This command was integrated into Cisco IOS Release 12.2(33)SXI.
	15.0(1)M	This command was modified. The vrf keyword, the <i>name</i> , and the <i>as-number</i> arguments were removed.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines	Use the show eigrp plugins command in user EXEC or privileged EXEC mode to determine if a particular EIGRP feature is available in your Cisco IOS image. This command displays a summary of information about EIGRP service families and address families.
	This command is useful when contacting Cisco technical support.

Examples	The following example shows how to display EIGRP plugin information:
-----------------	----------------------------------------------------------------------

```
Router# show eigrp plugins

EIGRP feature plugins:::
  eigrp-release       :   5.00.00 : Portable EIGRP Release
```

■ show eigrp plugins

```

          : 19.00.00 : Source Component Release(rel5)
  igrp2   : 3.00.00 : Reliable Transport/Dual Database
  bfd     : 1.01.00 : BFD Platform Support
  mtr     : 1.00.01 : Multi-Topology Routing(MTR)
  eigrp-pfr : 1.00.01 : Performance Routing Support
  ipv4-af : 2.01.01 : Routing Protocol Support
  ipv4-sf  : 1.01.00 : Service Distribution Support
  external-client : 1.02.00 : Service Distribution Client Support
  ipv6-af : 2.01.01 : Routing Protocol Support
  ipv6-sf  : 1.01.00 : Service Distribution Support
  snmp-agent : 1.01.01 : SNMP/SNMPv2 Agent Support

```

Table 8 describes the significant fields shown in the display.

Table 8 *show eigrp plugins Field Descriptions*

Field	Description
eigrp release	Displays the portable EIGRP release version.
igrp2	Displays the reliable transport and dual database version.
bfd	Displays the EIGRP-BFD feature version.
mtr	Displays the EIGRP multitopology routing (MTR) version.
eigrp-pfr	Displays the EIGRP performance routing feature version.
ipv4-af	Displays the EIGRP IPv4 routing protocol feature version.
ipv4-sf	Displays the EIGRP IPv4 service distribution feature version.
external-client	Displays the EIGRP service distribution client support feature version.
ipv6-af	Displays the EIGRP IPv6 routing protocol feature version.
ipv6-sf	Displays the EIGRP IPv6 service distribution feature version.
snmp-agent	Displays the EIGRP SNMP and SNMPv2 Agent Support version.

■ Related Commands

Command	Description
clear eigrp service-family	Clears entries from the EIGRP neighbor table.
show eigrp service-family external-client	Displays information about the EIGRP service-family external clients.
show eigrp service-family ipv4 topology	Displays information from the EIGRP IPv4 service-family topology table.
show eigrp service-family ipv6 topology	Displays information from the EIGRP IPv6 service-family topology table.
show eigrp tech-support	Generates a report of all EIGRP-related information.

show eigrp protocols

To display general information about Enhanced Interior Gateway Routing Protocol (EIGRP) protocols that are currently running, use the **show eigrp protocols** command in user EXEC or privileged EXEC mode.

show eigrp protocols [*vrf vrf-name*]

Syntax Description

vrf vrf-name	(Optional) Displays information about the specified VRF.
---------------------	----------------------------------------------------------

Command Modes

User EXEC (>)
Privileged EXEC (#)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines

Use the **show eigrp protocols** command in user EXEC or privileged EXEC mode to see a summary of information on EIGRP IPv4 service families or address families.

Examples

The following example shows how to display general EIGRP information:

```
Router# show eigrp protocols

EIGRP-IPv4 Protocol for AS(10)
Metric weight K1=1, K2=0, K3=1, K4=0, K5=0
NSF-aware route hold timer is 240
Router-ID: 1.1.1.1
Topology : 0 (base)
Active Timer: 3 min
Distance: internal 90 external 170
Maximum path: 4
Maximum hopcount 100
Maximum metric variance 1
EIGRP-IPv4 Protocol for AS(5) VRF(red)
Metric weight K1=1, K2=0, K3=1, K4=0, K5=0
NSF-aware route hold timer is 240
Router-ID: 1.1.1.1
Topology : 0 (base)
Active Timer: 3 min
Distance: internal 90 external 170
Maximum path: 4
Maximum hopcount 100
Maximum metric variance 1
```

```
Total Prefix Count: 0
Total Redist Count: 0
```

The following example shows how to display general EIGRP information for VRF1:

```
Router# show eigrp protocols vrf vrf1

EIGRP-IPv4 Protocol for AS(5) VRF(vrf1)
Metric weight K1=1, K2=0, K3=1, K4=0, K5=0
NSF-aware route hold timer is 240
Router-ID: 1.1.1.1
Topology : 0 (base)
Active Timer: 3 min
Distance: internal 90 external 170
Maximum path: 4
Maximum hopcount 100
Maximum metric variance 1
Total Prefix Count: 0
Total Redist Count: 0
```

Table 9 describes the significant fields shown in the display.

Table 9 *show eigrp protocols Field Descriptions*

Field	Description
EIGRP-IPv4 Protocol for AS(10)	EIGRP instance and AS number.
Metric weight	EIGRP metric calculations.
NSF-aware route hold timer	Route-hold timer value for an NSF-aware router.
Router-ID	Router ID.
Topology	Number of entries in the EIGRP topology table.
Active Timer	EIGRP routing active time limit.
Distance	Internal and external administrative distance.
Maximum path	Maximum number of parallel routes that EIGRP can support.
Maximum hop count	Maximum hop count (in decimal).
Maximum metric variance	Metric variance used to find feasible paths for a route.
EIGRP-IPv4 Protocol	EIGRP instance and AS number for VRF Red.
Total Prefix Count	The aggregate sum of the prefixes in an EIGRP instance topology table. It includes prefixes learned from all neighbors or from redistribution.
Total Redist Count	The number of prefixes redistributed into an EIGRP process.

Related Commands	Command	Description
	clear eigrp service-family	Clears entries from the EIGRP neighbor table.
	show eigrp service-family external-client	Displays information about the EIGRP service-family external clients.
	show eigrp service-family ipv4 topology	Displays information from the EIGRP IPv4 service-family topology table.
	show eigrp service-family ipv6 topology	Displays information from the EIGRP IPv6 service-family topology table.
	show tech-support	Generates a report of all EIGRP-related information.

show eigrp tech-support

To generate a report of Enhanced Interior Gateway Routing Protocol (EIGRP) internal state information, use the **show eigrp tech-support** command in privileged EXEC mode.

show eigrp tech-support [detailed]

Syntax Description	detailed	(Optional) Displays additional detail not shown with the basic command.
---------------------------	-----------------	-------------------------------------------------------------------------

Command Modes	Privileged EXEC (#)
----------------------	---------------------

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
	12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines	Use the show eigrp tech-support command in privileged EXEC mode to display various internal EIGRP states.
-------------------------	------------------------------------------------------------------------------------------------------------------



Note

This command is useful for debugging and troubleshooting by Cisco technical support, but it is not intended for normal EIGRP administration tasks. This command should not be used without guidance from Cisco technical support.

Examples	The following is sample output from the show eigrp tech-support detailed command:
-----------------	------------------------------------------------------------------------------------------

```
Router# show eigrp tech-support detailed

EIGRP Internal Process States

procinfoQ:
1: 0x54ABD10 vrid:2 afi:1 as:2 tableid:0 vrfid:0 tid:0 name:
topo_ddbQ(1) 0x55243E8 tableid:0 name:base
topo_ddbQ.count: 1
procinfoQ.count: 1

deadQ:
ddbQ:
1: 0x55243E8 name:base
ddbQ.count: 1
-----
EIGRP-IPv4 Protocol for AS(2)
{vrid:2 afi:1 as:2 tableid:0 vrfid:0 tid:0 name: }
PIDs: Hello: 204 PDM: 203
```

```

Router-ID: 6.6.6.6
Threads: procinfo: 0x4A3EC70 ddb: 0x4A3EE50
workQ:
iadbQ: Se2/0 Se2/1 Se3/0 Et0/1
count: 4
temp_iadbQ:
passive_iadbQ: Et0/0
count: 1
peerQ:
static_peerQ:
suspendQ:
networkQ: 1.0.0.0
2.0.0.0
count: 2
summaryQ: 2.0.0.0/16 - Et0/1 (intf: 1)
1.0.0.0/8 - Et0/1 (intf: 1)
count: 2
Socket Queue: 0/2000/2/0 (current/max/highest/drops)
Input Queue: 0/2000/2/0 (current/max/highest/drops)
GRS/NSF: enabled hold-timer: 240
Active Timer: 3 min
Distance: internal 90 external 170
Max Path: 4
Max Hopcount: 100
Variance: 1
-----

```

Related Commands

Command	Description
show eigrp plugins	Displays general information including the versions of the EIGRP protocol features currently running.

show ip eigrp accounting

To display prefix accounting information for Enhanced Interior Gateway Routing Protocol (EIGRP) processes, use the **show ip eigrp accounting** command in privileged EXEC mode.

show ip eigrp [**vrf** {*vrf-name* | *}] [*autonomous-system-number*] **accounting**

Syntax Description

vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
vrf *	(Optional) Displays information about all VRFs.
<i>autonomous-system-number</i>	(Optional) Autonomous system number.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(29)S	This command was introduced.
12.3(14)T	This command was integrated into Cisco IOS Release 12.3(14)T.
15.0(1)M	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf accounting command.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family accounting** command. Cisco recommends using the **show eigrp address-family accounting** command.

Examples

The following is sample output from the **show ip eigrp accounting** command:

```
Router# show ip eigrp vrf RED accounting

EIGRP-IPv4 Accounting for AS(100)/ID(10.0.2.1) VRF(RED)
Total Prefix Count: 4 States: A-Adjacency, P-Pending, D-Down
State Address/Source Interface Prefix Count Restart Count Restart/Reset(s)
P Redistributed ---- 0 3 211
A 10.0.1.2 Et0/0 2 0 84
P 10.0.2.4 Se2/0 0 2 114
D 10.0.1.3 Et0/0 0 3 0
```

**Note**

Connected and summary routes are not listed individually in the output of this command but are counted in the total aggregate count per process.

Table 10 describes the significant fields shown in the display.

Table 10 *show ip eigrp accounting Field Descriptions*

Field	Description
EIGRP IPv4 Accounting for AS...	Identifies the EIGRP instance along with the AS number, router ID, and table ID.
Total Prefix Count	Shows the aggregate sum of the prefixes in an EIGRP instance topology table. It includes prefixes learned from all neighbors and redistribution sources.
States: A-Adjacency, P-Pending, D-Down	<p>A-Adjacency: Indicates a stable adjacency with the neighbor or a normal redistribution state.</p> <p>P-Pending: Neighbor adjacency or redistribution is suspended or in a penalized state because the maximum prefix limit has been exceeded.</p> <p>D-Down: Neighbor adjacency or redistribution is suspended permanently until a manually reset is performed with the clear ip eigrp neighbor command.</p>
Address/Source	Shows either the neighbor IP address or the redistribution source.
Interface	Shows the interface on which neighbor information is received.
Prefix Count	<p>Displays the total number of learned prefixes by source.</p> <p>Note Routes can be learned for the same prefix from multiple sources, and the sum of all prefix counts in this column may be greater than the figure displayed in the “Prefix Count” field.</p>
Restart Count	Number of times a route source has exceeded the maximum-prefix limit.
Restart Reset(s)	Displays the time, in seconds, that a route source is in a P (penalized) state. If the route source is in an A (stable or normal) state, the displayed time, in seconds, is the time period until penalization history is reset.

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.

show ip eigrp events

To display the Enhanced Interior Gateway Routing Protocol (EIGRP) event log, use the **show ip eigrp events** command in user EXEC or privileged EXEC mode.

```
show ip eigrp [vrf vrf-name] events [starting-event-number ending-event-number] | [errmsg
[starting-event-number ending-event-number]] [sia [starting-event-number
ending-event-number]] [type]
```

Syntax Description	vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
	<i>starting-event-number</i>	(Optional) Number of first event to display.
	<i>ending-event-number</i>	(Optional) Number of last event to display.
	errmsg	(Optional) Displays error message events.
	sia	(Optional) Displays Stuck in Active (SIA) events.
	type	(Optional) Displays the types of events being logged.

Command Default All events in the EIGRP event log are displayed.

Command Modes User EXEC (>)
Privileged EXEC (#)

Command History	Release	Modification
	10.0	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines The EIGRP event log is used by Cisco technical support to display a history of EIGRP internal events. This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family events** command. Cisco recommends using the **show eigrp address-family events** command.

The output of this command is displayed in reverse order, with the most recent events displayed first and the oldest events displayed last.

Examples The following example shows how to display the EIGRP event log:

```
Router# show ip eigrp events

1      02:37:58.171 NSF stale rt scan, peer: 10.0.0.0
```

```

2    02:37:58.167 Metric set: 10.0.0.1/24 284700416
3    02:37:58.167 FC sat rdbmet/succmet: 284700416 0
4    02:37:58.167 FC sat nh/ndbmet: 10.0.0.2 284700416
5    02:37:58.167 Find FS: 10.0.0.0/24 284700416
6    02:37:58.167 Rcv update met/succmet: 284956416 284700416
7    02:37:58.167 Rcv update dest/nh: 10.0.0.0/24 10.0.0.1
8    02:37:58.167 Peer nsf restarted: 10.0.0.1 Tunnel0
9    02:36:38.383 Metric set: 10.0.0.0/24 284700416
10   02:36:38.383 RDB delete: 10.0.0.0/24 10.0.0.1
11   02:36:38.383 FC sat rdbmet/succmet: 284700416 0
12   02:36:38.383 FC sat nh/ndbmet: 0.0.0.0 284700416

```

Related Commands

Command	Description
eigrp event-log size	Specifies the size of the EIGRP event log.
show eigrp address-family events	Displays the EIGRP event log.

show ip eigrp interfaces

To display information about interfaces that are configured for Enhanced Interior Gateway Routing Protocol (EIGRP), use the **show ip eigrp interfaces** command in privileged EXEC mode.

show ip eigrp [**vrf** {*vrf-name* | *}] [*autonomous-system-number*] **interfaces** [*type number*] [**detail**]

Syntax Description

vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
vrf *	(Optional) Displays information about all VRFs.
<i>autonomous-system-number</i>	(Optional) Filters that output by autonomous system number.
<i>type</i>	(Optional) Interface type.
<i>number</i>	(Optional) Interface number.
detail	(Optional) Displays detailed information about the EIGRP interfaces for a specific EIGRP process.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
11.2	This command was introduced.
12.2(18)SXE	Support for the Bidirectional Forwarding Detection (BFD) feature was added. The detail keyword was added.
12.0(31)S	The BFD feature was integrated into Cisco IOS Release 12.0(31)S. Support was added for the Cisco 12000 series Internet router.
12.4(4)T	Support for the BFD feature was added. The detail keyword was added.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
15.0(1)M	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf interfaces command.
12.2(33)SRE	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf interfaces command.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Use the **show ip eigrp interfaces** command to display active EIGRP interfaces, as well as EIGRP-specific interface settings and statistics.

If an interface is specified, only information about that interface is displayed. Otherwise, information about all interfaces on which EIGRP is running is displayed.

If an autonomous system is specified, only the routing process for the specified autonomous system is displayed. Otherwise, all EIGRP processes are displayed.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family interfaces** command. Cisco recommends using the **show eigrp address-family interfaces** command.

Examples

The following is sample output from the **show ip eigrp interfaces** command:

```
Router# show ip eigrp interfaces
```

```
EIGRP-IPv4 Interfaces for AS(60)
```

Interface	Peers	Xmit Queue Un/Reliable	Mean SRTT	Pacing Time Un/Reliable	Multicast Flow Timer	Pending Routes
Di0	0	0/0	0	11/434	0	0
Et0	1	0/0	337	0/10	0	0
SE0:1.16	1	0/0	10	1/63	103	0
Tu0	1	0/0	330	0/16	0	0

The following is sample output that displays detailed information about all active EIGRP interfaces:

```
Router# show ip eigrp interfaces detail
```

```
EIGRP-IPv4 Interfaces for AS(1)
```

Interface	Peers	Xmit Queue Un/Reliable	Mean SRTT	Pacing Time Un/Reliable	Multicast Flow Timer	Pending Routes
Et0/0	0	0/0	0	0/1	0	0
Hello-interval is 7, Hold-time is 21 Split-horizon is disabled Next xmit serial <none> Un/reliable mcasts: 0/0 Un/reliable ucasts: 0/0 Mcast exceptions: 0 CR packets: 0 ACKs suppressed: 0 Retransmissions sent: 0 Out-of-sequence rcvd: 0 Next-hop-self disabled, next-hop info forwarded Topology-ids on interface - 0 Authentication mode is md5, key-chain is "TEST" BFD is enabled						
Et0/1	0	0/0	0	0/10	0	0
Hello-interval is 5, Hold-time is 15 Split-horizon is enabled						

Table 11 describes the significant fields shown in the display.

Table 11 *show ip eigrp interfaces Field Descriptions*

Field	Description
Interface	Interface over which EIGRP is configured.
Peers	Number of directly connected EIGRP neighbors.
Xmit Queue Un/Reliable	Number of packets remaining in the Unreliable and Reliable transmit queues.
Mean SRTT	Mean smooth round-trip time (SRTT) interval (in seconds).
Pacing Time Un/Reliable	Pacing time (in seconds) used to determine when EIGRP packets should be sent out the interface (unreliable and reliable packets).
Multicast Flow Timer	Maximum number of seconds for which the router will send multicast EIGRP packets.

Table 11 *show ip eigrp interfaces Field Descriptions (continued)*

Field	Description
Pending Routes	Number of routes in the packets in the transmit queue waiting to be sent.
BFD is...	BFD enable state.

Related Commands

Command	Description
show ip eigrp neighbors	Displays the neighbors discovered by EIGRP.
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.

show ip eigrp neighbors

To display neighbors discovered by Enhanced Interior Gateway Routing Protocol (EIGRP), use the **show ip eigrp neighbors** command in privileged EXEC mode.

```
show ip eigrp [vrf { vrf-name | *}] [autonomous-system-number] neighbors [interface-type | static | detail]
```

Syntax Description

vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
vrf *	(Optional) Displays information about all VRFs.
<i>autonomous-system-number</i>	(Optional) Filters that output by <i>autonomous system number</i> .
<i>interface-type</i>	(Optional) Filters that output by interface.
static	(Optional) Displays static neighbors.
detail	(Optional) Displays detailed neighbor information.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
10.3	This command was introduced.
12.0(7)T	The static keyword was added.
12.2(15)T	Support for NSF restart operations was integrated into the output.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
15.0(1)M	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf neighbors command.
12.2(33)SRE	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf neighbors command.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Use the **show ip eigrp neighbors** command to display dynamic and static neighbor states. It is also useful for debugging certain types of transport problems.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family neighbors** command. Cisco recommends using the **show eigrp address-family neighbors** command.

Examples

The following is sample output from the **show ip eigrp neighbors** command:

show ip eigrp neighbors

Router# **show ip eigrp neighbors**

H	Address	Interface	Hold (sec)	Uptime	SRTT (ms)	RTO	Q Cnt	Seq Num
0	10.1.1.2	Et0/0	13	00:00:03	1996	5000	0	5
2	10.1.1.9	Et0/0	14	00:02:24	206	5000	0	5
1	10.1.2.3	Et0/1	11	00:20:39	2202	5000	0	5

Table 12 describes the significant fields shown in the display.

Table 12 *show ip eigrp neighbors Field Descriptions*

Field	Description
AS(60)	Autonomous system number for these neighbors.
Address	IP address of the EIGRP peer.
Interface	Interface on which the router is receiving hello packets from the peer.
Holdtime	Length of time EIGRP will wait to hear from the peer before declaring it down.
Uptime	Elapsed time (in hours:minutes: seconds) since the local router first heard from this neighbor.
Q Count	Number of EIGRP packets (update, query, and reply) that the software is waiting to send.
Seq Num	Sequence number of the last update, query, or reply packet that was received from this neighbor.
SRTT	Smooth round-trip time. This is the number of milliseconds required for an EIGRP packet to be sent to this neighbor and for the local router to receive an acknowledgment of that packet.
RTO	Retransmission timeout (in milliseconds). This is the amount of time the software waits before resending a packet from the retransmission queue to a neighbor.

The following is sample output from the **show ip eigrp neighbors** command when issued with the **detail** keyword:

Router# **show ip eigrp neighbors detail**

EIGRP-IPv4 Neighbors for AS(60)

H	Address	Interface	Hold (sec)	Uptime	SRTT (ms)	RTO	Q Cnt	Seq Num
3	1.1.1.3	Et0/0	12	00:04:48	1832	5000	0	14
Version 12.2/1.2, Retrans:0, Retries:0 Restart time 00:01:05								
0	10.4.9.5	Fa0/0	11	00:04:07	768	4608	0	4
Version 12.2/1.2, Retrans: 0, Retries: 0								
2	10.4.9.10	Fa0/0	13	1w0d	1	3000	0	6
Version 12.2/1.2, Retrans: 1, Retries: 0								
1	10.4.9.6	Fa0/0	12	1w0d	1	3000	0	4
Version 12.2/1.2, Retrans: 1, Retries: 0								

Table 13 describes the significant fields shown in the display.

Table 13 *show ip eigrp neighbors detail Field Descriptions*

Field	Description
AS(60)	Autonomous system number for these neighbors.
H	This column lists the order in which a peering session was established with the specified neighbor. The order is specified with sequential numbering starting with 0.
Address	IP address of the EIGRP peer.
Interface	Interface on which the router is receiving hello packets from the peer.
Holdtime	Length of time EIGRP will wait to hear from the peer before declaring it down.
Uptime	Elapsed time (in hours:minutes: seconds) since the local router first heard from this neighbor.
Q Count	Number of EIGRP packets (update, query, and reply) that the software is waiting to send.
Seq Num	Sequence number of the last update, query, or reply packet that was received from this neighbor.
SRTT	Smooth round-trip time. This is the number of milliseconds required for an EIGRP packet to be sent to this neighbor and for the local router to receive an acknowledgment of that packet.
RTO	Retransmission timeout (in milliseconds). This is the amount of time the software waits before resending a packet from the retransmission queue to a neighbor.
Version	The software version that the specified peer is running.
Retrans	The number of times that a packet has been retransmitted.
Retries	The number of times an attempt was made to retransmit a packet.
Restart time	Elapsed time (in hours:minutes: seconds) since the specified neighbor has restarted.

Related Commands

Command	Description
show eigrp address-family neighbors	Displays the neighbors discovered by EIGRP.

show ip eigrp topology

To display entries in the Enhanced Interior Gateway Routing Protocol (EIGRP) topology table, use the **show ip eigrp topology** command in privileged EXEC mode.

show ip eigrp [**vrf** {*vrf-name* | *}] [*autonomous-system-number*] **topology** [*ip-address* [*mask*]] | [**name**] [**active** | **all-links** | **detail-links** | **pending** | **summary** | **zero-successors**]

Syntax Description

vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
vrf *	(Optional) Displays information about all VRFs.
<i>autonomous-system-number</i>	(Optional) Autonomous system number.
<i>ip-address</i>	(Optional) IP address. When specified with a mask, a detailed description of the entry is provided.
<i>mask</i>	(Optional) Subnet mask. The mask is entered as a slash mark followed by the prefix length.
name	(Optional) EIGRP-IPv4 topology table name. This name is the topology identifier and shows the topology-related information for Multi-Topology Routing (MTR). Note Effective with Cisco IOS Release 12.2(33)SRE, this keyword was removed.
active	(Optional) Displays all topology entries that are in an active state.
all-links	(Optional) Displays all topology entries and all links (paths) instead of displaying only feasible paths.
detail-links	(Optional) Displays all topology entries with additional detail.
pending	(Optional) Displays all topology entries pending updates queued to send to neighbors.
summary	(Optional) Displays a summary of the EIGRP topology table.
zero-successors	(Optional) Displays topology entries that fail to install in the routing table due to administrative distance.

Command Default

If this command is used without any optional keywords, then only topology entries with feasible successors are displayed and only the feasible paths are shown.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
10.0	This command was introduced.
12.3(8)T	This command was enhanced to display internal and external EIGRP routes.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2(33)SRB	The name keyword was added to support MTR.
12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.

Release	Modification
15.0(1)M	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf topology command.
12.2(33)SRE	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. The name keyword was removed. This command replaces the show ip eigrp vrf topology command.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Use the **show ip eigrp topology** command to display topology entries, feasible and non-feasible paths, metrics, and states. This command can be used without any keywords or arguments, in which case only topology entries with feasible successors are displayed, and only the feasible paths are shown. The **all-links** keyword displays all paths, whether feasible successors or not, and the **detail-links** keyword displays additional detail about these paths.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family topology** command. Cisco recommends using the **show eigrp address-family topology** command.

Examples

The following is sample output from the **show ip eigrp topology** command:

```
Router# show ip eigrp topology

EIGRP-IPv4 Topology Table for AS(1)/ID(10.0.0.1)

Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
       r - Reply status, s - sia status
P 10.0.0.0/8, 1 successors, FD is 409600
    via 1.1.1.2 (409600/128256), Ethernet0/0
P 172.16.1.0/24, 1 successors, FD is 409600
    via 1.1.1.2 (409600/128256), Ethernet0/0
P 10.0.0.0/8, 1 successors, FD is 281600
    via Summary (281600/0), Null0
P 10.0.1.0/24, 1 successors, FD is 281600
    via Connected, Ethernet0/0
```

The following example displays detailed information for a single prefix. The prefix shown is an EIGRP internal route:

```
Router# show ip eigrp topology 10.0.0.0/8

EIGRP-IPv4 Topology Entry for AS(1)/ID(10.0.0.1) for 10.0.0.0/8
  State is Passive, Query origin flag is 1, 1 Successor(s), FD is 409600
  Descriptor Blocks:
    10.0.0.2 (Ethernet0/0), from 10.0.1.2, Send flag is 0x0
      Composite metric is (409600/128256), route is Internal
      Vector metric:
        Minimum bandwidth is 10000 Kbit
        Total delay is 6000 microseconds
        Reliability is 255/255
        Load is 1/255
```

■ show ip eigrp topology

```

Minimum MTU is 1500
Hop count is 1
Originating router is 10.0.1.2

```

The following example displays detailed information for a single prefix. The prefix shown is an EIGRP external route:

```
Router# show ip eigrp topology 172.16.1.0/24
```

```

EIGRP-IPv4 Topology Entry for AS(1)/ID(10.0.0.1) for 10.0.0.0/8
State is Passive, Query origin flag is 1, 1 Successor(s), FD is 409600
Descriptor Blocks:
  10.0.0.2 (Ethernet0/0), from 10.0.1.2, Send flag is 0x0
    Composite metric is (409600/128256), route is External
    Vector metric:
      Minimum bandwidth is 10000 Kbit
      Total delay is 6000 microseconds
      Reliability is 255/255
      Load is 1/255
      Minimum MTU is 1500
      Hop count is 1
      Originating router is 10.0.1.2
    External data:
      AS number of route is 0
      External protocol is Connected, external metric is 0
      Administrator tag is 0 (0x00000000)

```

The following example demonstrates the **all-links** keyword, which displays all paths, even those that are not feasible:

```
Router# show ip eigrp topology all-links
```

```

EIGRP-IPv4 Topology Table for AS(1)/ID(10.0.0.1)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
       r - reply Status, s - sia Status

P 172.16.1.0/24, 1 successors, FD is 409600, serno 14
    via 10.10.1.2 (409600/128256), Ethernet0/0
    via 10.1.04.3 (2586111744/2585599744), Serial3/0, serno 18

```

The following example demonstrates the **detail-links** keyword, which displays additional detail about the routes:

```
Router# show ip eigrp topology detail-links
```

```

EIGRP-IPv4 Topology Table for AS(1)/ID(10.0.0.1)
Codes: P - Passive, A - Active, U - Update, Q - Query, R - Reply,
       r - reply Status, s - sia Status

P 10.0.0.0/8, 1 successors, FD is 409600, serno 6
    via 1.1.1.2 (409600/128256), Ethernet0/0
P 172.16.1.0/24, 1 successors, FD is 409600, serno 14
    via 1.1.1.2 (409600/128256), Ethernet0/0
P 10.0.0.0/8, 1 successors, FD is 281600, serno 3
    via Summary (281600/0), Null0
P 10.1.1.0/24, 1 successors, FD is 281600, serno 1
    via Connected, Ethernet0/0

```

Table 14 describes the significant fields shown in the displays.

Table 14 *show ip eigrp topology Field Descriptions*

Field	Description
Codes	State of this topology table entry. Passive and Active refer to the EIGRP state with respect to this destination; Update, Query, and Reply refer to the type of packet that is being sent.
P – Passive	No EIGRP computations are being performed for this destination.
A – Active	EIGRP computations are being performed for this destination.
U – Update	Indicates that a pending update packet is waiting to be sent for this route.
Q – Query	Indicates that a pending query packet is waiting to be sent for this route.
R – Reply	Indicates that a pending reply packet is waiting to be sent for this route.
r – Reply status	Indicates that EIGRP has sent a query for the route and is waiting for a reply from the specified path.
10.16.90.0	Destination IP network number.
255.255.255.0	Destination subnet mask.
successors	Number of successors. This number corresponds to the number of next hops in the IP routing table. If “successors” is capitalized, then the route or next hop is in a transition state.
serno	Serial number.
FD	Feasible distance. The feasible distance is the best metric to reach the destination or the best metric that was known when the route went active. This value is used in the feasibility condition check. If the reported distance of the router (the metric after the slash) is less than the feasible distance, the feasibility condition is met and that path is a feasible successor. Once the software determines it has a feasible successor, it need not send a query for that destination.
via	IP address of the peer that told the software about this destination. The first <i>n</i> of these entries, where <i>n</i> is the number of successors, is the current successors. The remaining entries on the list are feasible successors.
(409600/128256)	The first number is the EIGRP metric that represents the cost to the destination. The second number is the EIGRP metric that this peer advertised.

Related Commands

Command	Description
show eigrp address-family topology	Displays entries in the EIGRP topology table.

show ip eigrp traffic

To display the number of Enhanced Interior Gateway Routing Protocol (EIGRP) packets sent and received, use the **show ip eigrp traffic** command in privileged EXEC mode.

show ip eigrp [**vrf** {*vrf-name* | *}] [*autonomous-system-number*] **traffic**

Syntax Description

vrf <i>vrf-name</i>	(Optional) Displays information about the specified VRF.
vrf *	(Optional) Displays information about all VRFs.
<i>autonomous-system-number</i>	(Optional) Autonomous system number.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf traffic command.
12.2(33)SRE	This command was modified. The vrf , <i>vrf-name</i> , and * keywords and arguments were added. This command replaces the show ip eigrp vrf traffic command.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family traffic** command. Cisco recommends using the **show eigrp address-family traffic** command.

Examples

The following is sample output from the **show ip eigrp traffic** command:

```
Router# show ip eigrp traffic

EIGRP-IPv4 Traffic Statistics for AS(60)
Hellos sent/received: 21429/2809
Updates sent/received: 22/17
Queries sent/received: 0/0
Replies sent/received: 0/0
Acks sent/received: 16/13
```

```

SIA-Queries sent/received: 0/0
SIA-Replies sent/received: 0/0
Hello Process ID: 204
PDM Process ID: 203
Socket Queue: 0/2000/2/0 (current/max/highest/drops)
Input Queue: 0/2000/2/0 (current/max/highest/drops)

```

Table 15 describes the significant fields shown in the display.

Table 15 *show ip eigrp traffic Field Descriptions*

Field	Description
Hellos sent/received	Number of hello packets sent and received.
Updates sent/received	Number of update packets sent and received.
Queries sent/received	Number of query packets sent and received.
Replies sent/received	Number of reply packets sent and received.
Acks sent/received	Number of acknowledgement packets sent and received.
SIA-Queries sent/received	Number of stuck in active query packets sent and received.
SIA-Replies sent/received	Number of stuck in active reply packets sent and received.
Hello Process ID	Hello process identifier.
PDM Process ID	Protocol-dependent module IOS process identifier.
Socket Queue	The IP to EIGRP Hello Process socket queue counters.
Input queue	The EIGRP Hello Process to EIGRP PDM socket queue counters.

Related Commands

Command	Description
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.

show ip eigrp vrf accounting



Note

Effective with Cisco IOS Release 15.0(1)M, this command was replaced by the **show ip eigrp accounting** command. See the **show ip eigrp accounting** command for more information.

To display prefix accounting information for an Enhanced Interior Gateway Routing Protocol (EIGRP) VPN routing and forwarding instance (VRF), use the **show ip eigrp vrf accounting** command in privileged EXEC mode.

show ip eigrp vrf {*vrf-name* | *} **accounting** [*autonomous-system-number*]

Syntax Description

<i>vrf-name</i>	Specifies the VRF name.
*	Displays all VRFs.
<i>autonomous-system-number</i>	(Optional) Specifies the autonomous system number.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(29)S	This command was introduced.
12.3(14)T	This command was integrated into Cisco IOS Release 12.3(14)T.
15.0(1)M	This command was replaced by the show ip eigrp accounting command.

Usage Guidelines

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family accounting** command. Cisco recommends using the **show eigrp address-family accounting** command.

Examples

The following is sample output from the **show ip eigrp vrf accounting** command:

```
Router# show ip eigrp vrf RED accounting
IP-EIGRP accounting for AS(100)/ID(10.0.2.1) Routing Table: RED
Total Prefix Count: 4 States: A-Adjacency, P-Pending, D-Down
State Address/Source Interface Prefix Restart Restart/
Count Count Reset(s)
P Redistributed ---- 0 3 211
A 10.0.1.2 Et0/0 2 0 84
P 10.0.2.4 Se2/0 0 2 114
D 10.0.1.3 Et0/0 0 3 0
```



Note

Connected and summary routes are not listed individually in the output of this command but are counted in the total aggregate count per process.

Table 16 describes the significant fields shown in the display.

Table 16 *show ip eigrp vrf accounting Field Descriptions*

Field	Description
IP-EIGRP accounting for AS...	Identifies the EIGRP instance along with the AS number, Router ID and Table ID.
Total Prefix Count	Shows the aggregate sum of the prefixes in an EIGRP instance topology table. It includes prefixes learnt from all neighbors or from redistribution.
States: A-Adjacency, P-Pending, D-Down	<p>A-Adjacency: Indicates a stable adjacency with the neighbor or a normal redistribution state.</p> <p>P-Pending: Neighbor adjacency or redistribution is suspended or in a penalized state because the maximum prefix limit has been exceeded.</p> <p>D-Down: Neighbor adjacency or redistribution is suspended permanently until a manually reset is performed with the clear ip route command.</p>
Address/Source	Shows the peer IP address of the redistribution source.
Prefix Count	<p>Displays the total number of learned prefixes by source.</p> <p>Note Routes can be learned for the same prefix from multiple sources, and the sum of all prefix counts in this column may be greater than the figure displayed in the “Prefix Count” field.</p>
Restart Count	Number of times a route source has exceeded the maximum-prefix limit.
Restart/Reset(s)	Displays the time, in seconds, that a route source is in a P (penalized) state. If the route source is in an A (stable or normal) state, the displayed time, in seconds, is the time period until penalization history is reset.

Related Commands

Command	Description
show eigrp address-family accounting	Displays prefix accounting information for EIGRP processes.

show ip eigrp vrf interfaces



Note

Effective with Cisco IOS Release 15.0(1)M, this command was replaced by the **show ip eigrp interfaces** command. See the **show ip eigrp interfaces** command for more information.

To display information about interfaces that carry VPN routing and forwarding (VRF) information and that are configured for Enhanced Interior Gateway Routing Protocol (EIGRP), use the **show ip eigrp vrf interfaces** command in privileged EXEC mode.

show ip eigrp vrf { *vrf-name* | * } **interfaces** [*autonomous-system-number*] [*interface-type*] [**detail** *interface-type*] [**static** *interface-type*]

Syntax Description

<i>vrf-name</i>	Specifies the VRF name.
*	Displays all VRFs.
<i>autonomous-system-number</i>	(Optional) Specifies the autonomous system number.
<i>interface-type</i>	(Optional) Specifies the VRF interface for which to display EIGRP information.
detail <i>interface-type</i>	(Optional) Displays detailed VRF peer information. The interface can be specified after this keyword is entered.
static <i>interface-type</i>	(Optional) Displays VRF information for static neighbors. The interface can be specified after this keyword is entered. The <i>interface-type</i> argument allows you to display information about static neighbors for VRFs that are configured on specific interfaces.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(15)T	This command was integrated into 12.2(15)T.
12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.
12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
15.0(1)M	This command was replaced by the show ip eigrp interfaces command.

Usage Guidelines

Use the **show ip eigrp vrf interfaces** command to display EIGRP interfaces that are defined under the specified VRF. If an interface is specified with the *interface-type* argument, only the specified interface is displayed. Otherwise, all interfaces on which EIGRP is running as part of the specified VRF are displayed.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family interfaces** command. Cisco recommends using the **show eigrp address-family interfaces** command.

Examples

The following is sample output from the **show ip eigrp vrf interfaces** command:

```
Router# show ip eigrp vrf VRF-PINK interfaces
```

```
IP-EIGRP interfaces for process 1
```

Interface	Peers	Xmit Queue Un/Reliable	Mean SRTT	Pacing Time Un/Reliable	Multicast Flow Timer	Pending Routes
Et3/0	1	0/0	131	0/10	528	0

[Table 17](#) describes the significant fields shown in the display.

Table 17 *show ip eigrp vrf interfaces Field Descriptions*

Field	Description
IP-EIGRP interfaces for process...	Displays the autonomous system number for the specified VRF.
Interface	Interface over which EIGRP is configured.
Peers	Number of directly connected EIGRP neighbors.
Xmit Queue Un/Reliable	Number of packets remaining in the Unreliable and Reliable transmit queues.
Mean SRTT	Mean smooth round-trip time (SRTT) interval (in milliseconds).
Pacing Time Un/Reliable	Pacing time used to determine when EIGRP packets should be sent out the interface (unreliable and reliable packets).
Multicast Flow Timer	Maximum number of seconds in which the router will send multicast EIGRP packets.
Pending Routes	Number of routes in the packets in the transmit queue waiting to be sent.

Related Commands

Command	Description
show eigrp address-family interfaces	Displays information about interfaces configured for EIGRP.
clear ip eigrp vrf neighbors	Clears neighbor entries of the specified VRF from the RIB.
show ip eigrp vrf neighbors	Displays neighbors discovered by EIGRP that carry VRF information.
show ip eigrp vrf topology	Displays VRF entries in the EIGRP topology table.
show ip eigrp vrf traffic	Displays EIGRP VRF traffic statistics.

show ip eigrp vrf neighbors



Note

Effective with Cisco IOS Release 15.0(1)M, this command was replaced by the **show ip eigrp neighbors** command. See the **show ip eigrp neighbors** command for more information.

To display Enhanced Interior Gateway Routing Protocol (EIGRP) neighbors that are on interfaces that are part of the specified Virtual Private Network (VPN) routing and forwarding instance (VRF), use the **show ip eigrp vrf neighbors** command privileged EXEC mode.

show ip eigrp vrf { *vrf-name* | * } **neighbors** [*autonomous-system-number*] [*interface-type*] [**detail** *interface-type*] [**static** *interface-type*]

Syntax Description

<i>vrf-name</i>	Specifies the VRF name.
*	Displays all VRFs.
<i>autonomous-system-number</i>	(Optional) Autonomous system number.
<i>interface-type</i>	(Optional) Interface to display neighbor information under the specified VRF.
detail <i>interface-type</i>	(Optional) Displays detailed VRF peer information. The interface can be specified after this keyword is entered.
static <i>interface-type</i>	(Optional) Displays VRF information for static neighbors. The interface can be specified after this keyword is entered. The <i>interface-type</i> argument allows you to display information about static neighbors for VRFs that are configured on specific interfaces.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(15)T	This command was integrated into 12.2(15)T.
12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.
12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
15.0(1)M	This command was replaced by the show ip eigrp neighbors command.

Usage Guidelines

Use the **show ip eigrp vrf neighbors** command to determine when VRF neighbors become active and inactive. This command is also useful for debugging certain types of transport problems.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family neighbors** command. Cisco recommends using the **show eigrp address-family neighbors** command.

Examples

The following is sample output from the **show ip eigrp vrf neighbors** command:

```
Router# show ip eigrp vrf VRF-GREEN neighbors
```

```
IP-EIGRP neighbors for process 1
H   Address                Interface      Hold Uptime    SRTT   RTO   Q
Seq Type                                     (sec)         (ms)         Cnt
Num
0   10.10.10.2              Et3/0         10 1d16h      131    786    0   3
```

Table 18 describes the significant fields shown in the display.

Table 18 *show ip eigrp vrf neighbors Field Descriptions*

Field	Description
IP-EIGRP neighbors for process...	Displays the autonomous-system number for the specified EIGRP VRF.
Address	IP address of the EIGRP peer.
Interface	Interface on which the router is receiving hello packets from the peer.
Hold Uptime	Length of time (in seconds) that the Cisco IOS software will wait to hear from the peer before declaring it down, and the length in time (in seconds) since the local router first heard from this neighbor.
SRTT	Smooth round-trip time. This is the number of milliseconds required for an EIGRP packet to be sent to this neighbor and for the local router to receive an acknowledgment of that packet.
RTO	Retransmission timeout (in milliseconds). This is the amount of time the software waits before resending a packet from the retransmission queue to a neighbor.
Q	Number of EIGRP packets (update, query, and reply) that the software is waiting to send.

Related Commands

Command	Description
show eigrp address-family neighbors	Displays neighbors discovered by EIGRP.

show ip eigrp vrf topology



Note

Effective with Cisco IOS Release 15.0(1)M, this command was replaced by the **show ip eigrp topology** command. See the **show ip eigrp topology** command for more information.

To display Virtual Private Network (VPN) routing and forwarding instance (VRF) entries in the Enhanced Interior Gateway Routing Protocol (EIGRP) topology table, use the **show ip eigrp topology** command in privileged EXEC mode.

show ip eigrp vrf { *vrf-name* | * } **topology** [*as-number*] [*ip-address* [*mask*]] [**active** | **all-links** | **pending** | **summary** | **zero-successors**]

Syntax Description

<i>vrf-name</i>	Specifies the VRF name.
*	Displays all VRFs.
<i>as-number</i>	(Optional) Autonomous system number.
<i>ip-address</i>	(Optional) IP address. When specified with a mask, a detailed description of the entry is provided.
<i>mask</i>	(Optional) Subnet mask.
active	(Optional) Displays only active entries in the EIGRP topology table.
all-links	(Optional) Displays all entries in the EIGRP topology table.
pending	(Optional) Displays all entries in the EIGRP topology table that are waiting for an update from a neighbor or are waiting to reply to a neighbor.
summary	(Optional) Displays a summary of the EIGRP topology table.
zero-successors	(Optional) Displays available routes in the EIGRP topology table.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(15)T	This command was integrated into 12.2(15)T.
12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.
12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
15.0(1)M	This command was replaced by the show ip eigrp topology command.

Usage Guidelines

The **show ip eigrp vrf topology** command can be used without any keywords or arguments, but you must specify either a VRF name or use the * character as a wild card. If this command entered this way, only routes that are feasible successors are displayed. The **show ip eigrp vrf topology** command can be used to determine Diffusing Update Algorithm (DUAL) states and to debug possible DUAL problems.

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family topology** command. Cisco recommends using the **show eigrp address-family topology** command.

Examples

The following is sample output from the **show ip eigrp vrf topology** command:

```
Router# show ip eigrp vrf VRF-PINK topology

IP-EIGRP Topology Table for AS(1)/ID(192.168.10.1) Routing Table:VRF-PINK

Codes:P - Passive, A - Active, U - Update, Q - Query, R - Reply,
      r - reply Status, s - sia Status

P 10.17.17.0/24, 1 successors, FD is 409600
    via 10.10.10.2 (409600/128256), Ethernet3/0
P 172.16.19.0/24, 1 successors, FD is 409600
    via 10.10.10.2 (409600/128256), Ethernet3/0
P 192.168.10.0/24, 1 successors, FD is 281600
    via Connected, Ethernet3/0
P 10.10.10.0/24, 1 successors, FD is 281600
    via Redistributed (281600/0)
```

Table 19 describes the significant fields shown in the display.

Table 19 *show ip eigrp vrf topology Field Descriptions*

Field	Description
Codes	State of this topology table entry. Passive and Active refer to the EIGRP state with respect to this destination; Update, Query, and Reply refer to the type of packet that is being sent.
P—Passive	No EIGRP computations are being performed for this destination.
A—Active	EIGRP computations are being performed for this destination.
U—Update	An update packet was sent to this destination.
Q—Query	A query packet was sent to this destination.
R—Reply	A reply packet was sent to this destination.
r—reply Status	Flag that is set after the software has sent a query and is waiting for a reply.
s—sia Status	Flag that is set if a route is in a stuck in active state.
successors	Number of successors. This number corresponds to the number of next hops in the IP routing table. If “successors” is capitalized, then the route or next hop is in a transition state.
FD	Feasible distance. The feasible distance is the best metric to reach the destination or the best metric that was known when the route went active. This value is used in the feasibility condition check. If the reported distance of the router (the metric after the slash) is less than the feasible distance, the feasibility condition is met and that path is a feasible successor. Once the software determines it has a feasible successor, it need not send a query for that destination.

Table 19 *show ip eigrp vrf topology Field Descriptions (continued)*

Field	Description
replies	(Not shown in the output) Number of replies that are still outstanding (have not been received) with respect to this destination. This information appears only when the destination is in Active state.
state	(Not shown in the output) Exact EIGRP state that this destination is in. It can be the number 0, 1, 2, or 3. This information appears only when the destination is in the active state.
via	IP address of the peer that told the software about this destination. The first N of these entries, where N is the number of successors, is the current successors. The remaining entries on the list are feasible successors.
(409600/128256)	The first number is the EIGRP metric that represents the cost to the destination. The second number is the EIGRP metric that this peer advertised.
Ethernet 3/0	Interface from which this information was learned.

Related Commands

Command	Description
show eigrp address-family topology	Displays entries in the EIGRP topology table.

show ip eigrp vrf traffic



Note

Effective with Cisco IOS Release 15.0(1)M, the **show ip eigrp vrf traffic** command is replaced by the **show ip eigrp traffic** command. See the **show ip eigrp traffic** command for more information.

To display sent and received statistics for Enhanced Interior Gateway Routing Protocol (EIGRP) Virtual Private Networking (VPN) routing and forwarding instance (VRF) packets, use the **show ip eigrp vrf traffic** command in privileged EXEC mode.

```
show ip eigrp vrf {vrf-name | *} traffic [as-number]
```

Syntax Description

<i>vrf-name</i>	VRF name.
*	Displays all VRFs.
<i>as-number</i>	(Optional) Autonomous system number.

Command Modes

Privileged EXEC (#)

Command History

Release	Modification
12.0(22)S	This command was introduced.
12.2(15)T	This command was integrated into 12.2(15)T.
12.2(18)S	This command was integrated into Cisco IOS Release 12.2(18)S.
12.2(27)SBC	This command was integrated into Cisco IOS Release 12.2(27)SBC.
15.0(1)M	This command was replaced by the show ip eigrp traffic command.

Usage Guidelines

This command can be used to display information about EIGRP named configurations and EIGRP autonomous-system (AS) configurations.

This command displays the same information as the **show eigrp address-family traffic** command. Cisco recommends using the **show eigrp address-family traffic** command.

Examples

The following is sample output from the **show ip eigrp vrf traffic** command:

```
Router# show ip eigrp vrf VRF-RED traffic
```

```
IP-EIGRP Traffic Statistics for AS 101
  Hellos sent/received: 600/585
  Updates sent/received: 23/22
  Queries sent/received: 7/0
  Replies sent/received: 0/6
  Acks sent/received: 55/42
  Input queue high water mark 0, 0 drops
```

Table 20 describes the significant fields shown in the display.

Table 20 *show ip eigrp vrf traffic Field Descriptions*

Field	Description
IP-EIGRP Traffic Statistics for AS...	Displays the autonomous system number for the specified EIGRP VRF .
Hellos sent/received	Number of hello packets sent and received.
Updates sent/received	Number of update packets sent and received.
Queries sent/received	Number of query packets sent and received.
Replies sent/received	Number of reply packets sent and received.
Acks sent/received	Number of acknowledgment packets sent and received.
Input queue high water mark..., ... drops	Number of received packets that are approaching the maximum receive threshold and number of dropped packets.

Related Commands

Command	Description
show eigrp address-family traffic	Displays the number of EIGRP packets sent and received.

shutdown (address-family)

To disable the Enhanced Interior Gateway Routing Protocol (EIGRP) address-family protocol for a specific routing instance without removing any existing address-family configuration parameters, use the **shutdown** command in the appropriate configuration mode. To reenable the EIGRP address-family protocol, use the **no** form of this command.

shutdown

no shutdown

Syntax Description This command has no arguments or keywords.

Command Default The EIGRP address-family protocol for routing instances is not disabled.

Command Modes
 Router configuration (config-router)
 Address-family configuration (config-router-af)
 Address-family interface configuration (config-router-af-interface)

Command History	Release	Modification
	15.0(1)M	This command was introduced.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines When you configure the **shutdown** (address-family) command, the EIGRP address-family protocol continues to run on the router and you can continue to use the current address-family configuration. The address-family will not form any adjacencies on any interface and the address-family topology database is cleared.

Configure the **shutdown** command in address-family configuration mode to shut down all topologies under that address family. Configure this command in router configuration mode to shut down all address and service families and their topologies.

Examples The following example shows how to disable the address-family protocol in router configuration mode:

```
Router(config)# router eigrp virtual-name
Router(config-router)# shutdown
```

The following example shows how to disable the address-family protocol in address-family configuration mode:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
```

shutdown (address-family)

```
Router(config-router-af)# shutdown
```

The following example shows how to disable the address-family protocol in address-family interface configuration mode:

```
Router(config)# router eigrp virtual-name  
Router(config-router)# address-family ipv4 autonomous-system 4453  
Router(config-router-af)# af-interface default  
Router(config-router-af-interface)# shutdown
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
router eigrp	Configures the EIGRP address-family process.

split-horizon (EIGRP)

To enable Enhanced Interior Gateway Routing Protocol (EIGRP) split-horizon, use the **split-horizon** command in address-family interface configuration mode or service-family interface configuration mode. To disable EIGRP split-horizon, use the **no** form of this command.

split-horizon

no split-horizon

Syntax Description

This command has no arguments or keywords.

Command Default

EIGRP split-horizon is enabled by default. However, for ATM interfaces and subinterfaces **split-horizon** is disabled by default.

Command Modes

Address-family interface configuration (config-router-af-interface)
Service-family interface configuration (config-router-sf-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines

The split-horizon rule prohibits a router from advertising a route through an interface that the router itself uses to reach the destination. The following are general rules for EIGRP split-horizon:

- Split-horizon behavior is turned on by default.
- When you change the EIGRP split-horizon setting on an interface, all adjacencies with EIGRP neighbors reachable over that interface are reset.
- Split-horizon should typically be disabled only on non-broadcast multi-access interfaces.
- The EIGRP split-horizon behavior is not controlled or influenced by the **ip split-horizon** command.

To configure split-horizon for an EIGRP address family, use the **split-horizon** command in address-family interface configuration mode.

To configure split-horizon for an EIGRP service family, use the **split-horizon** command in service-family interface configuration mode.

Examples

The following example disables EIGRP split-horizon for serial interface 3/0 in address-family 5400:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 5400
Router(config-router-af)# af-interface serial3/0
Router(config-router-af-interface)# no split-horizon
```

The following example disables EIGRP split-horizon for serial interface 3/0 in service-family 5400:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 5400
Router(config-router-sf)# sf-interface serial3/0
Router(config-router-sf-interface)# no split-horizon
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
router eigrp	Configures the EIGRP address-family process.
service-family ipv4	Configures commands under service-family configuration mode.
sf-interface	Configures interface-specific commands under service-family configuration mode.

stub



Note

Effective with Cisco IOS Release 15.0(1)M and 12.2(33)SRE, the **stub** command was replaced by the **eigrp stub** command. See the **eigrp stub** command for more information.

To configure a router as a stub using Enhanced Interior Gateway Routing Protocol (EIGRP), use the **stub** command in router configuration mode. To disable the EIGRP stub routing feature, use the **no** form of this command.

stub [**receive-only** | **connected** | **static** | **summary** | **redistributed**]

no stub [**receive-only** | **connected** | **static** | **summary** | **redistributed**]

Syntax Description

receive-only	(Optional) Sets the router as a receive-only neighbor.
connected	(Optional) Advertises connected routes.
static	(Optional) Advertises static routes.
summary	(Optional) Advertises summary routes.
redistributed	(Optional) Advertises redistributed routes from other protocols and autonomous systems.

Command Default

Stub routing is not enabled.

Command Modes

Router configuration (config-router)

Command History

Release	Modification
12.4(6)T	This command was introduced.
12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB.
12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
15.0(1)M	This command was replaced by the eigrp stub command.
12.2(33)SRE	This command was replaced by the eigrp stub command.

Usage Guidelines

Use the **stub** command to configure a router as a stub where the router directs all IPv6 traffic to a distribution router.

The **stub** command can be modified with keywords, and more than one keyword can be used in the same syntax. These options can be used in any combination, except for the **receive-only** keyword. The **receive-only** keyword will restrict the router from sharing any of its routes with any other router in that EIGRP autonomous system, and the **receive-only** keyword will not permit any other option to be specified because it prevents any type of route from being sent. The **connected**, **static**, **summary**, and **redistributed** keywords can be used in any combination but cannot be used with the **receive-only** keyword.

If any of these four keywords is used with the **stub** command, only the route types specified by the particular keywords will be sent. Route types specified by the nonused keywords will not be sent.

The **connected** keyword permits the EIGRP stub routing feature to send connected routes. If the connected routes are not covered by a network statement, it may be necessary to redistribute connected routes with the **redistribute connected** command under the EIGRP process. This option is enabled by default.

The **static** keyword permits the EIGRP stub routing feature to send static routes. Without the configuration of this option, EIGRP will not send any static routes, including internal static routes that normally would be automatically redistributed. It will still be necessary to redistribute static routes with the **redistribute static** command.

The **summary** keyword permits the EIGRP stub routing feature to send summary routes. Summary routes can be created manually with the **ipv6 summary address eigrp** command or automatically at a major network border router with the **auto-summary** command enabled. This option is enabled by default.

The **redistributed** keyword permits the EIGRP stub routing feature to send other routing protocols and autonomous systems. Without the configuration of this option, EIGRP will not advertise redistributed routes.



Note

Multiaccess interfaces such as ATM, Ethernet, Frame Relay, ISDN PRI, and X.25 are supported by the EIGRP stub routing feature only when all routers on that interface, except the hub, are configured as stub routers.

Examples

In the following example, the **stub** command is used to configure the router as a stub that advertises connected and summary routes:

```
ipv6 router eigrp 1
 network 3FEE:12E1:2AC1:EA32::/64
 stub
```

In the following example, the **stub** command is issued with the **connected** and **static** keywords to configure the router as a stub that advertises connected and static routes (sending summary routes will not be permitted):

```
ipv6 router eigrp 1
 network 3FEE:12E1:2AC1:EA32::/64
 stub connected static
```

In the following example, the **stub** command is issued with the **receive-only** keyword to configure the router as a receive-only neighbor (connected, summary, and static routes will not be sent):

```
ipv6 router eigrp 1
 network 3FEE:12E1:2AC1:EA32::/64 eigrp
 stub receive-only
```

In the following example, the **stub** command is issued with the **redistributed** keyword to configure the router to advertise other protocols and autonomous systems:

```
ipv6 router eigrp 1
 network 3FEE:12E1:2AC1:EA32::/64 eigrp
 stub redistributed
```

Related Commands

Command	Description
auto-summary (EIGRP)	Allows automatic summarization of subnet routes into network-level routes.
ipv6summary-address eigrp	Configures a summary aggregate address for a specified interface.
redistribute (IPv6)	Redistributes IPv6 routes from one routing domain into another routing domain.

summary-address (EIGRP)

To configure a summary address for Enhanced Interior Gateway Routing Protocol (EIGRP), use the **summary-address** (EIGRP) command in address-family interface configuration mode. To remove an EIGRP summary address, use the **no** form of this command.

summary-address *ip-address mask* [*administrative-distance* [**leak-map** *leak-map-name*]]

no summary-address *ip-address mask* [*administrative-distance* [**leak-map** *leak-map-name*]]

Syntax Description

<i>ip-address</i>	Summary address designated for a range of addresses.
<i>mask</i>	IP subnet mask used for the summary route.
<i>administrative-distance</i>	(Optional) Administrative distance. Valid range is 1 to 255. Default is 5.
leak-map	(Optional) Allows dynamic addresses based on a leak map.
<i>leak-map-name</i>	(Optional) The name of a leak-map.

Command Default

All routes are advertised individually.

Command Modes

Address-family interface configuration (config-router-af-interface)

Command History

Release	Modification
15.0(1)M	This command was introduced.
12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

The **summary-address** (EIGRP) command is used to configure interface-level address summarization. EIGRP summary routes are given an administrative distance value of 5. The administrative distance metric is used to advertise a summary address without installing it in the routing table.

By default, EIGRP summarizes subnet routes to the network level. The **no auto-summary** command can be entered to configure subnet-level summarization.

EIGRP Support for Leaking Routes

Configuring the **leak-map** keyword allows you to advertise a component route that would otherwise be suppressed by the manual summary. Any component subset of the summary routes or addresses can be leaked. A route map and access list must be defined to source the leaked route.

The following is default behavior if an incomplete configuration is entered:

- If the **leak-map** keyword is configured to reference a nonexistent route map, the configuration of this keyword has no effect. The summary address is advertised, but all component routes are suppressed.

- If the **leak-map** keyword is configured but the access list does not exist or the route map does not reference the access list, the summary address and all component routes are sent.

Examples

The following example shows how to configure an EIGRP summary address:

```
Router(config)# router eigrp virtual-name  
Router(config-router)# address-family ipv4 autonomous-system 4453  
Router(config-router-af)# af-interface ethernet0/0  
Router(config-router-af-interface)# summary-address 192.168.0.0 255.255.0.0 95
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
af-interface	Enters address-family interface configuration mode to configure interface-specific EIGRP commands.
auto-summary (EIGRP)	Allow automatic summarization of subnet routes into network-level routes.
router eigrp	Configures the EIGRP address-family process.

timers active-time

To adjust Enhanced Interior Gateway Routing Protocol (EIGRP) routing wait time, use the **timers active-time** command in router configuration mode or address-family topology configuration mode. To disable this function, use the **no** form of the command.

timers active-time [*time-limit* | **disabled**]

no timers active-time

Syntax Description	<i>time-limit</i>	(Optional) EIGRP active-time limit (in minutes). Valid range is 1 to 65535.
	disabled	(Optional) Disables the timers and permits the routing wait time to remain active indefinitely.

Command Default This command is disabled by default.

Command Modes Router configuration (config-router)
Address-family topology configuration (config-router-af-topology)

Command History	Release	Modification
	10.0	This command was introduced.
	12.4(6)T	Support for IPv6 was added.
	12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB.
	12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
	15.0(1)M	This command was modified. Address-family topology configuration mode was added. You must enter this command in address-family topology configuration mode for EIGRP named configurations.
	12.2(33)SRE	This command was modified. Address-family topology configuration mode was added. You must enter this command in address-family topology configuration mode for EIGRP named configurations.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines In EIGRP, there are timers that control the time that the router waits (after sending a query) before declaring the route to be in the stuck in active (SIA) state.

Examples

In the following example, the routing wait time is 200 minutes on the specified route:

```
Router(config)# router eigrp 5
Router(config-router)# timers active-time 200
```

In the following example, the routing wait time is 200 minutes on the specified address-family route:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# network 10.0.0.0
Router(config-router-af)# topology base
Router(config-router-af-topology)# timers active-time 200
```

In the following example, the routing wait time is indefinite if a route becomes active:

```
Router(config)# router eigrp 5
Router(config-router)# timers active-time disabled
```

In the following example, the routing wait time is indefinite on the specified address-family route:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
Router(config-router-af)# network 10.0.0.0
Router(config-router-af)# topology base
Router(config-router-af-topology)# timers active-time disabled
```

In the following example, the routing wait time is 100 minutes on the specified route:

```
Router(config)# ipv6 router eigrp 1
Router(config-router)# timers active-time 100
```

In the following example, the routing wait time is 100 minutes on the specified address-family route:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv6 autonomous-system 4453
Router(config-router-af)# topology base
Router(config-router-af-topology)# timers active-time disabled
```

Related Commands

Command	Description
address-family (EIGRP)	Enters address-family configuration mode to configure an EIGRP routing instance.
ipv6 router eigrp	Configures the EIGRP IPv6 routing process.
network (EIGRP)	Specifies the network for an EIGRP routing process.
router eigrp	Configures the EIGRP address-family process.
show ip eigrp topology	Displays the EIGRP topology table.
show ipv6 eigrp topology	Displays the IPv6 EIGRP topology table.
topology (EIGRP)	Configures an EIGRP process to route IP traffic under the specified topology instance and enters address-family topology configuration mode.

timers graceful-restart purge-time

To set the route-hold timer to determine how long a nonstop forwarding (NSF)-aware router that is running Enhanced Interior Gateway Routing Protocol (EIGRP) will hold routes for an inactive peer, use the **timers graceful-restart purge-time** command in router configuration, address-family, or service-family configuration mode. To return the route-hold timer to the default value, use the **no** form of this command.

timers graceful-restart purge-time *seconds*

no timers graceful-restart purge-time

Syntax Description	<i>seconds</i>	Time, in seconds, for which EIGRP will hold routes for an inactive peer. The configurable time range is from 20 to 300 seconds. The default is 240 seconds.
---------------------------	----------------	-------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Default	EIGRP NSF awareness is enabled by default. The default value for the route-hold timer is 240 seconds.
------------------------	-------------------------------------------------------------------------------------------------------

Command Modes	Router configuration (config-router) Address-family configuration (config-router-af) Service-family configuration (config-router-sf)
----------------------	--------------------------------------------------------------------------------------------------------------------------------------------

Command History	Release	Modification
	15.0(1)M	This command was introduced. This command replaces the timers nsf route-hold command.
	12.2(33)SRE	This command was integrated into Cisco IOS Release 12.2(33)SRE.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.
	12.2(33)SX14	This command was integrated into Cisco IOS Release 12.2(33)SX14.

Usage Guidelines	The route-hold timer sets the maximum period of time for which the NSF-aware router will hold known routes for an NSF-capable neighbor during a switchover operation or a well-known failure condition. The route-hold timer is configurable so that you can tune network performance and avoid undesired effects, such as “black holing” routes if the switchover operation takes too much time. When this timer expires, the NSF-aware router scans the topology table and discards any stale routes, allowing EIGRP peers to find alternate routes instead of waiting during a long switchover operation.
-------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Examples

The following configuration example sets the route-hold timer value for an NSF-aware address family. In the example, the route-hold timer is set to 1 minute:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 1
Router(config-router-af)# timers graceful-restart purge-time 60
```

The following configuration example sets the route-hold timer value for an NSF-aware service-family. In this example, the route-hold timer is set to 300 seconds:

```
Router(config)# router eigrp virtual-name
Router(config-router)# service-family ipv4 autonomous-system 4533
Router(config-router-sf)# timers graceful-restart purge-time 300
```

Related Commands

Command	Description
debug eigrp nsf	Displays EIGRP NSF-specific events in the console of a router.
debug ip eigrp notifications	Displays EIGRP events and notifications in the console of the router.
show eigrp neighbors	Displays the neighbors discovered by IP EIGRP.
show ip protocols	Displays the parameters and current state of the active routing protocol process.

timers nsf converge

To adjust the maximum time that a restarting router will wait for the end of table (EOT) notification from a nonstop forwarding (NSF)-capable or NSF-aware peer, use the **timers nsf converge** command in router configuration mode or address-family configuration mode. To return the signal timer to the default value, use the **no** form of this command.

timers nsf converge *seconds*

no timers nsf converge

Syntax Description	<i>seconds</i>	Time, in seconds, for which a restarting router will wait for an EOT notification. Valid range is 60 to 180 seconds. The default is 120 seconds.
---------------------------	----------------	--------------------------------------------------------------------------------------------------------------------------------------------------

Command Default	Enhanced Interior Gateway Routing Protocol (EIGRP) NSF awareness is enabled by default. EIGRP NSF awareness uses 120 seconds as the default value if this command is not configured or if the no form of this command is entered.
------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Modes	Router configuration (config-router) Address-family configuration (config-router-af)
----------------------	-----------------------------------------------------------------------------------------

Command History	Release	Modification
	12.2(18)S	This command was introduced.
	12.2(28)SB	This command was integrated into Cisco IOS Release 12.2(28)SB.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
	15.0(1)M	This command was modified. Address-family configuration mode was added.
	12.2(33)SRE	This command was modified. Address-family configuration mode was added.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines	This command is entered only on an NSF-capable router. The converge timer is be used to wait for the last EOT update if all startup updates have not been received within the signal timer period. If an EIGRP process discovers no neighbor, or if it has received all startup updates from its neighbor within the signal timer period, the converge timer will not be started.
-------------------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Examples	The following configuration example adjusts the converge timer on an NSF-capable router. In the example, the converge timer is set to 1 minute:
-----------------	-------------------------------------------------------------------------------------------------------------------------------------------------

```
Router(config-router)# timers nsf converge 60
```

The following EIGRP named configuration example adjusts the converge timer on an NSF-capable router. In the example, the converge timer is set to 1 minute:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 1
Router(config-router-af)# timers nsf converge 60
```

Related Commands

Command	Description
debug eigrp nsf	Displays notifications and information about NSF events for an EIGRP routing process.
debug ip eigrp notifications	Displays information and notifications for an EIGRP routing process. This output includes NSF notifications and events.
nsf (EIGRP)	Enables or disables EIGRP NSF on an NSF-capable router.
show ip protocols	Displays the parameters and current state of the active routing protocol process. The status of EIGRP NSF configuration and support is displayed in the output.
timers nsf graceful-restart purge-time	Sets the route-hold timer to determine how long a NSF-aware router that is running EIGRP will hold routes for an inactive peer.
timers nsf route-hold	Adjusts the maximum period of time that a supporting peer will hold known routes for an NSF-capable router during a restart operation or during a well-known failure condition.
timers nsf signal	Adjusts the maximum time for the initial restart period.

timers nsf route-hold



Note

Effective with Cisco IOS Release 15.0(1)M and 12.2(33)SRE, the **timers nsf route-hold** command was replaced by the **timers graceful-restart purge-time** command. See the **timers graceful-restart purge-time** command for more information.

To set the route-hold timer to determine how long a nonstop forwarding (NSF)-aware router that is running Enhanced Interior Gateway Routing Protocol (EIGRP) will hold routes for an inactive peer, use the **timers nsf route-hold** command in router configuration mode. To return the route-hold timer to the default value, use the **no** form of this command.

timers nsf route-hold *seconds*

no timers nsf route-hold

Syntax Description

<i>seconds</i>	Time, in seconds, for which EIGRP will hold routes for an inactive peer. Valid range is 20 to 300 seconds. The default is 240 seconds.
----------------	----------------------------------------------------------------------------------------------------------------------------------------

Command Default

EIGRP NSF awareness is enabled by default. The default value for the route-hold timer is 240 seconds.

Command Modes

Router configuration (config-router)

Command History

Release	Modification
12.2(15)T	This command was introduced.
12.2(28)SB	This command was integrated into Cisco IOS Release 12.2(28)SB.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
15.0(1)M	This command was replaced by the timers graceful-restart purge-time command.
12.2(33)SRE	This command was replaced by the timers graceful-restart purge-time command.

Usage Guidelines

The route-hold timer sets the maximum period of time that the NSF-aware router will hold known routes for an NSF-capable neighbor during a switchover operation or a well-known failure condition. The route-hold timer is configurable so that you can tune network performance and avoid undesired effects, such as “black holing” routes if the switchover operation takes too much time. When this timer expires, the NSF-aware router scans the topology table and discards any stale routes, allowing EIGRP peers to find alternate routes instead of waiting during a long switchover operation.

Examples

The following configuration example sets the route-hold timer value for an NSF-aware router. In the example, the route-hold timer is set to 2 minutes:

```
Router(config-router)# timers nsf route-hold 120
```

Related Commands

Command	Description
debug eigrp nsf	Displays EIGRP NSF-specific events in the console of a router.
debug ip eigrp notifications	Displays EIGRP events and notifications in the console of the router.
show ip eigrp neighbors	Displays the neighbors discovered by IP EIGRP.
show ip protocols	Displays the parameters and current state of the active routing protocol process.

timers nsf signal

To adjust the maximum time for the initial signal timer restart period, use the **timers nsf signal** command in router configuration mode or address-family configuration mode. To return the signal timer to the default value, use the **no** form of this command.

timers nsf signal *seconds*

no timers nsf signal

Syntax Description	<i>seconds</i>	Time, in seconds, for which Enhanced Interior Gateway Routing Protocol (EIGRP) will hold routes for an inactive peer. Valid range is 10 to 30 seconds. The default is 20 seconds.
---------------------------	----------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Default	EIGRP NSF awareness is enabled by default. EIGRP NSF awareness uses 20 seconds as the default value if this command is not configured or if the no form of this command is entered.
------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Command Modes	Router configuration (config-router) Address-family configuration (config-router-af)
----------------------	-----------------------------------------------------------------------------------------

Command History	Release	Modification
	12.2(15)T	This command was introduced.
	12.2(28)SB	This command was integrated into Cisco IOS Release 12.2(28)SB.
	12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
	12.2(33)SXH	This command was integrated into Cisco IOS Release 12.2(33)SXH.
	15.0(1)M	This command was modified. Address-family configuration mode was added.
	12.2(33)SRE	This command was modified. Address-family configuration mode was added.
	12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
	Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines	This command is entered only on a nonstop forwarding (NSF)-capable router. The EIGRP process starts a signal timer when it is notified of a switchover event. Hello packets with the RS bit set are sent during this period.
-------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

The converge timer is used to wait for the last end of table (EOT) update if all startup updates have not been received within the signal timer period. If an EIGRP process discovers no neighbor, or if it has received all startup updates from its neighbor within the signal timer period, the converge timer will not be started.

Examples

The following configuration example adjusts the signal timer value on an NSF-capable router. In the example, the signal timer is set to 30 seconds:

```
Router(config-router)# timers nsf signal 30
```

The following EIGRP named configuration example adjusts the signal timer value on an NSF-capable router. In the example, the signal timer is set to 30 seconds:

```
Router(config)# router eigrp virtual-name  
Router(config-router)# address-family ipv4 autonomous-system 1  
Router(config-router-af)# timers nsf signal 30
```

Related Commands

Command	Description
debug eigrp nsf	Displays notifications and information about NSF events for an EIGRP routing process.
debug ip eigrp notifications	Displays information and notifications for an EIGRP routing process. This output includes NSF notifications and events.
nsf (EIGRP)	Enables or disables EIGRP NSF on an NSF-capable router.
show ip protocols	Displays the parameters and current state of the active routing protocol process. The status of EIGRP NSF configuration and support is displayed in the output.
timers nsf converge	Adjusts the maximum time that restarting router will wait for the EOT notification from an NSF-capable or NSF-aware peer.
timers nsf graceful-restart purge-time	Sets the route-hold timer to determine how long a NSF-aware router that is running EIGRP will hold routes for an inactive peer.
timers nsf route-hold	Adjusts the maximum period of time that a supporting peer will hold known routes for an NSF-capable router during a restart operation or during a well-known failure condition.

topology (EIGRP)

To configure an Enhanced Interior Gateway Routing Protocol (EIGRP) process to route IP traffic under the specified topology instance and to enter address-family topology configuration mode, use the **topology** command in address-family configuration mode. To disassociate the EIGRP routing process from the topology instance, use the **no** form of this command.

topology {**base** | *topology-name* **tid** *number*}

no topology *topology-name*

Syntax Description

base	Specifies the base topology.
<i>topology-name</i>	Topology name. The <i>topology-name</i> argument is case-sensitive.
tid <i>number</i>	Specifies the topology ID number. The value for this argument can be a number from 1 to 65535.

Command Default

EIGRP routing processes are not configured to route IP traffic under a topology instance.

Command Modes

Address-family configuration (config-router-af)

Command History

Release	Modification
12.2(33)SRB	This command was introduced.
15.0(1)M	This command was integrated into Cisco IOS Release 15.0(1)M.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

The **topology** command is used in a Multi-Topology Routing (MTR) configuration to enable an EIGRP process under the specified topology. The **topology** command is entered under address-family configuration mode. Command configurations are applied only to the topology instance. The topology must be defined globally with the **global-address-family** command in global address-family configuration mode before the topology can be configured under the EIGRP process.

The **tid** keyword associates an ID with the topology instance. Each topology must be configured with a unique topology ID. The topology ID is used to identify and group Network Layer Reachability Information (NLRI) for each topology in EIGRP updates.

The topology ID must be consistent across routers so that EIGRP can correctly associate topologies.

Examples

The following example configures EIGRP process 1 to route traffic for the 192.168.0.0/16 network under the VOICE topology instance:

```
Router(config)# router eigrp 1
Router(config-router)# address-family ipv4 unicast autonomous-system 3
```

```
Router(config-router-af)# topology VOICE tid 100
Router(config-router-af-topology)# no auto-summary
Router(config-router-af-topology)# network 192.168.0.0 0.0.255.255
Router(config-router-af-topology)# end
```

Related Commands

Command	Description
clear ip eigrp	Resets EIGRP process and neighbor session information.
global-address-family ipv4	Enters global address family configuration mode to configure MTR.
topology (interface)	Configures an MTR topology instance on an interface.

traffic-share balanced

To control how traffic is distributed among routes when multiple routes for the same destination network have different costs, use the **traffic-share balanced** command in router configuration mode or address-family topology configuration mode. To disable this function, use the **no** form of the command.

traffic-share balanced

no traffic-share balanced

Syntax Description

This command has no arguments or keywords.

Command Default

Traffic is distributed proportionately to the ratios of the metrics.

Command Modes

Router configuration (config-router)

Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
12.2(33)SRA	This command was integrated into Cisco IOS Release 12.2(33)SRA.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)M	This command was modified. Address-family topology configuration mode was added.
12.2(33)SRE	This command was modified. Address-family topology configuration mode was added.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

This command applies only to Enhanced Interior Gateway Routing Protocol (EIGRP). With the default setting, routes that have higher metrics represent less-preferable routes and get less traffic.

Examples

In the following example, traffic is balanced across multiple routes:

```
Router(config)# router eigrp 5
Router(config-router)# traffic-share balanced
Router(config-router)# variance 1
```

In the following EIGRP named configuration example, traffic is balanced across multiple routes:

```
Router(config)# router eigrp virtual-name
Router(config-router)# address-family ipv4 autonomous-system 4453
```

```
Router(config-router-af)# network 10.0.0.0
Router(config-router-af)# topology base
Router(config-router-af-topology)# traffic-share balanced
Router(config-router-af-topology)# variance 1
```

Related Commands

Command	Description
variance (EIGRP)	Controls load balancing in an EIGRP network.

variance (EIGRP)

To control load balancing in an internetwork based on the Enhanced Interior Gateway Routing Protocol (EIGRP), use the **variance** command in router configuration mode or address-family topology configuration mode. To reset the variance to the default value, use the **no** form of this command.

variance *multiplier*

no variance

Syntax Description

<i>multiplier</i>	Metric value used for load balancing. It can be a value from 1 to 128. The default is 1, which means equal-cost load balancing.
-------------------	---------------------------------------------------------------------------------------------------------------------------------

Command Default

EIGRP uses equal-cost load balancing.

Command Modes

Router configuration (config-router)
Address-family topology configuration (config-router-af-topology)

Command History

Release	Modification
10.0	This command was introduced.
12.4(6)T	Support for IPv6 was added.
12.2(33)SRB	This command was integrated into Cisco IOS Release 12.2(33)SRB.
12.2SX	This command is supported in the Cisco IOS Release 12.2SX train. Support in a specific 12.2SX release of this train depends on your feature set, platform, and platform hardware.
15.0(1)	This command was modified. Address-family topology configuration mode was added.
12.2(33)SRE	This command was modified. Address-family topology configuration mode was added.
12.2(33)XNE	This command was integrated into Cisco IOS Release 12.2(33)XNE.
Cisco IOS XE Release 2.5	This command was integrated into Cisco IOS XE Release 2.5.

Usage Guidelines

Setting a variance value enables EIGRP to install multiple loop-free routes with unequal cost in a local routing table. A route learned through EIGRP must meet two criteria to be installed in the local routing table:

- The route must be loop-free. This condition is satisfied when the reported distance is less than the total distance or when the route is a feasible successor.
- The metric of the route must be lower than the metric of the best route (the successor) multiplied by the variance configured on the router.

Thus, if the variance is set to 1, only routes with the same metric as the successor are installed in the local routing table. If the variance is set to 2, any EIGRP-learned route with a metric less than 2 times the successor metric will be installed in the local routing table.

**Note**

EIGRP does not load-share between multiple routes; it only installs the routes in the local routing table. Then, the local routing table enables switching hardware or software to load-share between the multiple paths.

Examples

The following example sets a variance value of 4:

```
Router(config)# router eigrp 109  
Router(config-router)# variance 4
```

The following example sets a variance value of 4 in address-family topology configuration mode:

```
Router(config)# router eigrp virtual-name  
Router(config-router)# address-family ipv4 autonomous-system 4453  
Router(config-router-af)# network 10.0.0.0  
Router(config-router-af)# topology base  
Router(config-router-af-topology)# variance 4
```